

# RDK-B\_20170227

This is the summary page that describes the CMF RDK-B iteration rdkb-20170227.

Below are links to the relevant documents for the release.

- [RDK-B 20170227 Emulator Report](#) (Gerrit)
- A detailed changelog since the last iteration ([RDK-B\\_20170213](#)) can be found [here](#) (Gerrit).

For the Gerrit links, you need to log in before you will be able to see the contents.

*The latest RDK-B release addresses licensing issues so users are advised to move to the latest release.*

## Baseline

Baseline	CMF-20170227	2017-02-27 baseline.
Post-baseline updates		
TDK	M44	<a href="https://rdkwiki.com/rdk/display/TDK/TDK+Release+M44">https://rdkwiki.com/rdk/display/TDK/TDK+Release+M44</a>
Manifest	rdkb-20170227	

## Highlights since 20170213

- New components: None.
- Components updated:
  - ccsp/hal, ccsp/sysint, ccsp/rdkb, rdkbemu\_xb3, CcspWifiAgent, CcspCommonLibrary, CcspLMLite, CcspPandM, CcspSnmpPa, CcspTr069Pa, GwProvApp, TestAndDiagnostic, Utopia.
- Patches updated: None.
- Community contributions:
  - [7535 \(RDKBCMF-41\)](#) Changes In Utopia for making lan/wan services and firewall/parental control for RaspberryPi Platform
  - [7975](#) Revert "Revert "ARRISXB6-3328 RDKB-8135: CCSP WiFi Agent doesn't Restart if it crashes""

## Getting the code

```
$ mkdir rdkb
$ cd rdkb
$ repo init -u https://code.rdkcentral.com/r/manifests -m rdkb.xml -b rdkb-20170227
$ repo sync -j4 --no-clone-bundle
```

- The `-m rdkb.xml` in the build sequence above is important. If this is not specified, you will get an RDK-V tree by default.
- The `-b rdkb-20170227` in the build sequence above specifies the branch to use. If you omit the `-b rdkb-20170227` entirely, you will get the master (HEAD) of each component.
- At any time, the community can build latest master by dropping the `-b rdkb-20170227` option in the repo init command.
- We have verified that this iteration boots to a login prompt and that you can log in, and that you can connect with a web browser to the web admin page.

## Building the code

```
$ source meta-cmf-rdkb-bsp-emulator/setup-environment (select qemux86broadband)
$ bitbake rdk-generic-broadband-image
```

The image path will be: `build-qemux86broadband/tmp/deploy/images/qemux86broadband/rdk-generic-broadband-image-qemux86broadband.vmdk`

## Building TDK

Follow the steps as for a normal build, above, but use the following bitbake command:

```
$ bitbake rdk-generic-broadband-tdk-image
```

The image path will be: `build-qemux86broadband/tmp/deploy/images/qemux86broadband/rdk-generic-broadband-tdk-image-qemux86broadband.vmdk`

TDK for RDK-B documentation is available: <https://rdkwiki.com/rdk/display/TDK/TDK+Release+M44>

## Running the emulator

1. Start VirtualBox.

2. Click New -> Enter name -> Select type Linux -> Select version Other Linux (32 bit) -> Click Next
3. Select Memory size - 512MB -> Click Next
4. Select option Use an existing virtual hard drive -> Select the built image above -> Click Create
5. Once the VM has been created, select the new image and click Settings -> Network -> Select Attached to: 'Bridged Adapter' -> Click Ok
6. Click Start. This will bring up the emulator with the initial splash screen

## Known Issues

- [TDK-312](#) RDK-B TCL test retrieves wrong IP
- [TDK-313](#) RDK-B PAM tests fail after CcspPandMSsp process dies
- [TDK-324](#) RDK-B CCSPCOMMON\_MBUS Emulator Tests Failing on TDKB.cfg Load Error