

Telemetry 2.0 support for RDKB RPI -User Manual

- [Introduction](#)
- [RDKB Telemetry Components](#)
- [Environment Setup](#)
 - [2.1. Build procedure](#)
 - [2.2. Pre- requisites for enabling Telemetry2_0 \(Version : 2\) - Single profile](#)
- [Xconf server](#)
 - [Change Application to stb in top right corner of the window](#)
 - [Create Formula](#)
 - [Create Device Settings](#)
 - [Create Upload Repository](#)
 - [Create LogUpload Settings](#)
 - [Test Page](#)
 - [Create Permanent Profiles](#)
 - [Create Targeting Rules](#)
 - [Test Page](#)
 - [JSON Response](#)
 - [RAW data Response](#)
 - [RAW Data Response of T1](#)
- [RPI\(target\) devices Response's](#)
 - [DCMresponse Text Data](#)
 - [RPI device Logs](#)
 - [JSON Report](#)
 - [Configuration file](#)
 - [Log File](#)
- [Log upload onto HTTPS Server](#)
 - [JSON file upload](#)
- [Telemetry Version : 2.0.1 - Multiprofile](#)
 - [Pre- requisites for enabling Telemetry2_0](#)
 - [Telemetry 2.0 Report Profiles](#)
 - [T2 DataModel](#)
 - [DMCLI SET Command for T2 Report Profile](#)
 - [Dmcli Get](#)
 - [RPI Device Logs](#)
 - [cJSON Report](#)
 - [Log Upload](#)
 - [Telemetry 2.0 ProfileMsgPack](#)
 - [Sample JSON Profile](#)
 - [Convert JSON into base-64](#)
 - [dmcli set](#)
 - [dmcli Get](#)
 - [profiles.msgpack](#)
 - [Telemetry 2 Log data](#)
 - [cJSON Report](#)
 - [Log upload](#)
- [Report Profiles Validation through WebPA Commands](#)
 - [ReportProfilesMsgPack](#)
 - [Webpa Set](#)
 - [Webpa Get](#)
 - [Device Logs](#)
- [Limitations](#)
- [References](#)

Introduction

While migrating to Telemetry2.0 from DCA telemetry, the traditional log grepping is targetted to reduce as much as possible by instrumenting the markers coming from RDKB components. To achieve this, RDKB components are supposed to make required changes with the use of APIs from Telemetry 2.0 shared library.

RDKB Telemetry Components

1. Xconf Server
2. RPI with rdkb image
3. telemetry2_0

Environment Setup

2.1. Build procedure

Follow the wiki page to make yocto's RDK-B image from yocto workspace in your PC.

[RDK-B R-Pi Yocto 3.1 - Dunfell](#)

Note: Proceed the build procedure in Ubuntu18 version VM

2.2. Pre- requisites for enabling Telemetry2_0 (Version : 2) - Single profile

Telemetry Version : 2 (by default telemetry version as 1)


Below are the steps for enabling Telemetry 2.0 in RPI,

1. dmcli eRT setv Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.Enable bool true
2. dmcli eRT setv Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.Version string 2
3. dmcli eRT setv Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.ConfigURL string <https://xconf.rdkcentral.com:19092/loguploader/getT2Settings>
4. touch /nvram/enable_t2_debug
5. reboot the device
6. pidof "telemetry2_0" - check the running status of telemetry2

After board boot up, disable log rotation by using the command:

```
$ systemctl disable rdkbLogMonitor
```

Below sample screenshots are enabling the T2 process of version 2 in target device(rpi),



After reboot the device,


Sample Successful logs for Telemetry 2 process Initialization in /rdklogs/logs/telemetry2_0.txt.0 ,

Xconf server

- Xconf server page : <https://xconf.rdkcentral.com:19093/admin/ux/>
- With default credentials 'admin' as both UserName/Password

Configuring Telemetry on Xconf server

Change Application to stb in top right corner of the window



Create Formula

Login to Xconf Server and go to DCM menu item and click on "Formulas" sub menu and create Formula

A screenshot of the 'Edit Formula' page in the Xconf Server web interface. The page has a header with the Xconf logo and navigation tabs: Common, Firmware, DCM, Telemetry, Settings, RFC, Tools, and Changes. The 'Application' dropdown is set to 'stb'. The main content area is titled 'Edit Formula' and contains several sections: 'Properties' with fields for Name (RDKB-RPI-TEST), Description (Telemetry - RPI Model), Percentage (100), and Priority; 'Percentage of responses with level one/two/three logs' with L1, L2, and L3 percentage fields; 'Define settings' with buttons for 'Edit Device settings', 'Edit Log Upload settings', and 'Create VOD settings'; and 'Build condition' with a field for 'estbMacAddress'. The page is viewed in a browser window with the URL 'xconf.rdkcentral.com'.

Create Device Settings

Xconf Server DCM Device Settings

A screenshot of the 'Edit Device Settings' dialog box overlaid on the 'Edit Formula' page. The dialog box contains fields for Name (RDKB-RPI-TEST), Expression (2 2 * * *), CheckOnReboot (true), Are active (true), Type (ActNow), Time zone (UTC), Minutes (2), Hours (2), Day of month (*), Month (*), dayOfWeek (*), and Time Window (minutes) (0). There are 'Save' and 'Cancel' buttons at the bottom right of the dialog box. The background shows the 'Edit Formula' page with the 'Edit Device settings' button highlighted.

Create Upload Repository

Xconf Server DCM Upload Repository

Upload Repository : HTTPS Server

Repository URL: https://xconf.rdkcentral.com/xconf/telemetry_upload.php

← → ↻ xconf.rdkcentral.com:19093/admin/ux/#/uploadrepository/edit/900658b7-4098-4037-9e88-fbfcfd17e634/UPDATE

XConf Common ▾ Firmware ▾ DCM ▾ Telemetry ▾ Settings ▾ RFC ▾ Tools ▾ Changes ▾

Application: admin 01/06/2023 04:37:43 UTC

Update Upload repository

Name:

Description:

URL:

Create LogUpload Settings

Xconf Server DCM LogUpload Settings

← → ↻ xconf.rdkcentral.com:9093/admin/ux/7#/formula/edit/9e8ad5bb-38eb-4f4c-9d36-96851e76d320?formulaSize=1

XConf Common ▾ Firmware ▾ DCM ▾ Telemetry ▾ Settings ▾ RFC ▾ Tools ▾ Changes ▾

Application: admin 05/26/2021 13:58:35 UTC

Edit Log Upload Settings

Settings

Name: Number Of Days:

Upload On Reboot: Are Settings Active:

Upload repository:

Schedule

Type:

Cron Expression: Time zone:

Minutes: ExpressionL1:

Hours: ExpressionL2:

Day of month: ExpressionL3:


Month:

dayOfWeek:

Test Page

Xconf Server DCM Test Page

In the Test Page, give estbMacAddress(B8:27:EB:1B:56:4C Mac Address of RPI) and ensure the parameters that has been configured in the DCM.



Create Permanent Profiles

The markers are of 3 types .

1. Split based markers.
2. Count based markers
3. TR-181 based markers.

Marker Type	Sample configuration from xconf	Description with respect to sample configuration
Count based markers	<code>{"header": "RF_ERROR_IPv4PingFailed", "content": "Ping to IPv4 Gateway Address are failed", "type": "SelfHeal.txt.0", "pollingFrequency": "0"}</code>	Expects the occurrence count of content "Ping to IPv4 Gateway Address are failed"
Split based markers	<code>{"header": "bootuptime_ClientConnectComplete_split", "content": "Client_Connect_complete: ", "type": "LM.txt.log", "pollingFrequency": "0"}</code>	Expects the value after content "Client_Connect_complete:"
TR-181 based markers	<code>{"header": "CMMAC_split", "content": "Device.DeviceInfo.X_COMCAST-COM_CM_MAC", "type": "<message_bus>", "pollingFrequency": "48"}</code>	Markers whose type is configured as "<message_bus>"

In T2.0, the aim is to instrument possible number of split and count based markers from component side. These are termed as event markers. Can be classified as one more type under the classification of markers.

Once a marker is instrumented from component side, its configuration on xconf will be changed from the configured file name to "<event>" in 'type:' section.

Example:

```
{ "header": "bootuptime_ClientConnectComplete_split", "content": "ccsp-lm-lite", "type": "<event>", "pollingFrequency": "0" }
```

Xconf Server Telemetry Permanent Profiles

1. In the Telemetry Permanent Profile page, there will be a 5th column that allows a component name to be entered. The component name is optional and may be present for only some of the entries in the Telemetry profile.

← → ↻ xconf.rdkcentral.com:19093/admin/ux/#/permanentprofile/edit/04e97048-4b56-4680-b88a-7dc73dc794d0

Application: admin 01/06/2023 04:37:15 UTC

Common Firmware DCM Telemetry Settings RFC Tools Changes

Permanent profile

Name
RDKB-RPI-TEST

Schedule
2

Upload repository
HTTPS https://xconf.rdkcentral.com

Telemetry profile entries:

PAM	enteredhotspot_update_circ	PAMlog.txt.0	2	Component (optional)
Total_online_clients_split	RDKB_CONNECTED_CLIENT	LM.txt.0	0	Component (optional)
Total_online_clients_split	RDKB_CONNECTED_CLIENT	LM.txt.0	0	ccsp-lm-lite
Total_Hosts_Count_split	RDK_LOG_WARN, Total H	WiFiLog.txt.0	0	ccsp-wifi-agent
bootuptime_wifi_split	boot_to_WIFI_uptime=	BootTime.log	0	Component (optional)

2. Once you save the permanent profile, you will get a message overlay 'Profile added to the pending changes'. Then go to Changes -> select the profile you create -> Click on "Approve selected changes".
Then the permanent profile will be listed under Telemetry - > Permanent profiles

Create Targeting Rules

Create targeting rule via Telemetry -> Targeting rules. Targeting rules is to map the profiles with rules.

← → ↻ xconf.rdkcentral.com:3093/admin/ux/?#/targetingrule/edit/719fec82-cc2a-4e1f-8601-9d92ebccb6b0

Application: admin 05/26/2021 14:14:52 UTC

Common Firmware DCM Telemetry Settings RFC Tools Changes

Targeting rule

Rule name:
RDKB-RPI-TEST

estbMacAddress IS B8:27:EB:1B:56:4C

AND OR ☐ not IS

Bound profile:
RDKB-RPI-TEST

Save Cancel

Test Page

Xconf Server Telemetry Test page

After creating the permanent profile and targeting rules, go to Telemetry->Test page and give a parameter that will match the one of the rule that you have created. Then matched rule will be displayed like below.

In the Test Page, give estbMacAddress(B8:27:EB:1B:56:4C Mac Address of RPI)

Test page

Parameters

estbMacAddress B8:27:EB:1B:56:4C

Test With Parameters

Context

{\"estbMacAddress\": \"B8:27:EB:1B:56:4C\", \"applicationType\": \"stb\"}

Matched rules

Name: RDKB-RPI-TEST
Profile: RDKB-RPI-TEST


JSON Response

https://xconf.rdkcentral.com:19092/loguploader/getT2Settings?estbMacAddress=b8:27:eb:1b:56:4c&firmwareVersion=rdkb-generic-broadband-image_rdk-next_20210329055811&model=&partnerId=RDKM&accountId=&ecmMacAddress=B8:27:EB:1B:56:4C&env=dev&controllerId=2504&channelMapId=2345&vodId=15660&version=2

JSON Response


```
{  \"urn:settings:LogUploadSettings:Message\": null,  \"urn:settings:LogUploadSettings:Name\": \"RDKB-RPI-TEST\",  \"urn:settings:LogUploadSettings:NumberOfDays\": 0,  \"urn:settings:LogUploadSettings:UploadRepositoryName\": \"RDKB-RPI-TEST\",  \"urn:settings:LogUploadSettings:UploadRepositoryURL\": \"http://35.161.239.220/xconf/telemetry_upload.php\",  \"urn:settings:LogUploadSettings:UploadRepositoryProtocol\": \"HTTP\",  \"urn:settings:LogUploadSettings:UploadOnReboot\": true,  \"urn:settings:LogUploadSettings:UploadImmediately\": false,  \"urn:settings:LogUploadSettings:upload\": true,  \"urn:settings:LogUploadSettings:UploadSchedule:cron\": \"* * * * *\",  \"urn:settings:LogUploadSettings:UploadSchedule:levelone:cron\": null,  \"urn:settings:LogUploadSettings:UploadSchedule:leveltwo:cron\": null,  \"urn:settings:LogUploadSettings:UploadSchedule:levelthree:cron\": null,  \"urn:settings:LogUploadSettings:UploadSchedule:DurationMinutes\": 0,  \"urn:settings:VOISettings:Name\": null,  \"urn:settings:VOISettings:LocationsURL\": null,  \"urn:settings:VOISettings:SRNIPList\": null,  \"urn:settings:TelemetryProfile\": {    \"id\": \"84e97848-4b56-4688-b88a-7dc73dc794db\",    \"telemetryProfile\": {      \"0\": {        \"header\": \"PAN\",        \"content\": \"entered hotspot_update_circuit_ids\",        \"type\": \"PANLog.txt.0\",        \"pollingFrequency\": \"3\"      },      \"1\": {        \"header\": \"Total online clients split\",        \"content\": \"RDKB_CONNECTED_CLIENTS:Total_Online_Clients=\",        \"type\": \"LN.txt.0\"      }    }  } }
```

RAW data Response



RAW Data Response of T1

https://xconf.rdkcentral.com:9092/loguploader/getSettings?estbMacAddress=b8:27:eb:1b:56:4c&firmwareVersion=rdkb-generic-broadband-image_rdkb-next_20210329055811&model=&partnerId=RDKM&accountId=&ecmMacAddress=B8:27:EB:1B:56:4C&env=dev&controllerId=2504&channelMapId=2345&vodId=15660&version=2



RPI(target) devices Response's

DCMresponse Text Data

DCMresponse.txt

```
root@RaspberryPi-Gateway:~# cat /tmp/DCMresponse.txt
"urn:settings:GroupName": "RDKB-RPI-TEST"
"urn:settings:CheckOnReboot": true
"urn:settings:CheckSchedule:cron": "2 2 * * *"
"urn:settings:CheckSchedule:DurationMinutes": 0
"urn:settings:LogUploadSettings:Message": null
"urn:settings:LogUploadSettings:Name": "RDKB-RPI-TEST"
"urn:settings:LogUploadSettings:NumberOfDays": 0
"urn:settings:LogUploadSettings:UploadRepositoryName": "RDKB-RPI-TEST"
"urn:settings:LogUploadSettings:UploadRepository:URL": "https://xconf.rdkcentral.com/xconf/telemetry_upload.php"
"urn:settings:LogUploadSettings:UploadRepository:uploadProtocol": "HTTP"
"urn:settings:LogUploadSettings:UploadOnReboot": true
"urn:settings:LogUploadSettings:UploadImmediately": false
"urn:settings:LogUploadSettings:upload": true
"urn:settings:LogUploadSettings:UploadSchedule:cron": "2 2 * * *"
"urn:settings:LogUploadSettings:UploadSchedule:levelone:cron": null
"urn:settings:LogUploadSettings:UploadSchedule:leveltwo:cron": null
"urn:settings:LogUploadSettings:UploadSchedule:levelthree:cron": null
"urn:settings:LogUploadSettings:UploadSchedule:DurationMinutes": 0
"urn:settings:VODSettings:Name": null
"urn:settings:VODSettings:LocationsURL": null
"urn:settings:VODSettings:SRMIPList": null
"urn:settings:TelemetryProfile": {"id": "04e97048-4b56-4680-b88a-7dc73dc794d0", "telemetryProfile": [{"header": "PAM", "content": "enteredhotspot_update_circuit_ids", "type": "PAMlog.txt.0", "pollingFrequency": "2"}, {"header": "Total_online_clients_split", "content": "RDKB_CONNECTED_CLIENTS:Total_Online_Clients=", "type": "LM.txt.0", "pollingFrequency": "0"}, {"header": "Total_online_clients_split", "content": "ccsp-lm-lite", "type": "<event>", "pollingFrequency": "0"}, {"header": "Total_Hosts_Count_split", "content": "ccsp-wifi-agent", "type": "<event>", "pollingFrequency": "0"}, {"header": "bootuptime_wifi_split", "content": "boot_to_WIFI_uptime=", "type": "BootTime.log", "pollingFrequency": "0"}, {"header": "bootuptime_Ethernet_split", "content": "boot_to_ETH_uptime=", "type": "BootTime.log", "pollingFrequency": "0"}, {"header": "bootuptime_ClientConnectComplete_split", "content": "ccsp-lm-lite", "type": "<event>", "pollingFrequency": "0"}, {"header": "WIFI_INFO_clientdisconnect", "content": "ccsp-lm-lite", "type": "<event>", "pollingFrequency": "0"}, {"header": "UPDays_split", "content": "test-and-diagnostic", "type": "<event>", "pollingFrequency": "0"}, {"header": "UPTIME_split", "content": "Device.DeviceInfo.UpTime", "type": "<message_bus>", "pollingFrequency": "24"}, {"header": "CMMAC_split", "content": "Device.DeviceInfo.X_COMCAST-COM_CM_MAC", "type": "<message_bus>", "pollingFrequency": "24"}, {"header": "XDNS_split", "content": "Device.DeviceInfo.X_RDKCENTRAL-COM_EnableXDNS", "type": "<message_bus>", "pollingFrequency": "48"}, {"header": "xwifi2g_split", "content": "Device.WiFi.SSID.5.Enable", "type": "<message_bus>", "pollingFrequency": "4"}, {"header": "xwifienable_split", "content": "Device.DeviceInfo.X_COMCAST_COM_xfinitywifiEnable", "type": "<message_bus>", "pollingFrequency": "4"}, {"header": "2G_Radio_Status_split", "content": "Device.WiFi.Radio.1.Status", "type": "<message_bus>", "pollingFrequency": "24"}, {"header": "5G_Radio_Status_split", "content": "Device.WiFi.Radio.2.Status", "type": "<message_bus>", "pollingFrequency": "24"}, {"header": "HWREV_split", "content": "Device.DeviceInfo.HardwareVersion", "type": "<message_bus>", "pollingFrequency": "96"}, {"header": "FT_split", "content": "Device.DeviceInfo.FirstUseDate", "type": "<message_bus>", "pollingFrequency": "80"}, {"header": "LT_split", "content": "Device.Time.CurrentLocalTime", "type": "<message_bus>", "pollingFrequency": "0"}, {"header": "LoadAvg_split", "content": "test-and-diagnostic", "type": "<event>", "pollingFrequency": "0"}, {"header": "SYS_ERROR_PSMCrash_reboot", "content": "Psm_crash", "type": "BootTime.log", "pollingFrequency": "0"}, {"header": "SYS_INFO_Hostname_changed", "content": "ccsp-lm-lite", "type": "<event>", "pollingFrequency": "0"}, {"header": "WIFI_ERROR_PSM_GetRecordFail", "content": "ccsp-wifi-agent", "type": "<event>", "pollingFrequency": "0"}, {"header": "WIFI_INFO_CosaWifiiinit", "content": "ccsp-wifi-agent", "type": "<event>", "pollingFrequency": "0"}, {"header": "SYS_INFO_CaptivePortal", "content": "WiFi SSID and Passphrase are not modified", "type": "Consolelog.txt.0", "pollingFrequency": "0"}, {"header": "btime_moca_split", "content": "boot_to_MOCA_uptime=", "type": "BootTime.log", "pollingFrequency": "0"}, {"header": "bootuptime_SNMPV2Ready_split", "content": "boot_to_snmp_subagent_v2_uptime", "type": "BootTime.log", "pollingFrequency": "0"}, {"header": "btime_wcpcnter_split", "content": "Enter_WiFi_Personalization_captive_mode=", "type": "Consolelog.txt.0", "pollingFrequency": "0"}, {"header": "SYS_SH_RDKB_FIREWALL_RESTART", "content": "LAN HANDLER : Triggering RDKB_FIREWALL_RESTART after nfqhandler", "type": "Consolelog.txt.0", "pollingFrequency": "0"}, {"header": "btime_laninit_split", "content": "Lan_init_complete=", "type": "ArmConsolelog.txt.0", "pollingFrequency": "0"}, {"header": "btime_laninit_split", "content": "Laninit_complete=", "type": "BootTime.log", "pollingFrequency": "0"}, {"header": "btime_waninit_split", "content": "Waninit_complete=", "type": "BootTime.log", "pollingFrequency": "0"}, {"header": "btime_waninit_split", "content": "Wan_init_complete=", "type": "ArmConsolelog.txt.0", "pollingFrequency": "0"}
```

```

0"}, {"header": "btime_wanup_split", "content": "boot_to_wan_uptime=", "type": "BootTime.log", "pollingFrequency": "0"},
{"header": "btime_webpa_split", "content": "boot_to_WEBPA_READY_uptime=", "type": "WEBPAllog.txt.0", "
pollingFrequency": "0"}, {"header": "btime_webpa_split", "content": "boot_to_WEBPA_READY_uptime=", "type": "BootTime.
log", "pollingFrequency": "0"}, {"header": "MAXRX_1_split", "content": "ccsp-wifi-agent", "type": "<event>", "
pollingFrequency": "0"}, {"header": "MAXTX_1_split", "content": "ccsp-wifi-agent", "type": "<event>", "
pollingFrequency": "0"}, {"header": "SYS_SH_DhcpArpProcess_restart", "content": "test-and-diagnostic", "type": "
<event>", "pollingFrequency": "0"}, {"header": "SYS_SH_PAM_CRASH_RESTART", "content": "test-and-diagnostic", "type": "
<event>", "pollingFrequency": "0"}, {"header": "SYS_ERROR_5min_avg_cpu_100", "content": "test-and-diagnostic", "type": "
<event>", "pollingFrequency": "0"}, {"header": "WIFI_INFO_2GPrivateSSID_OFF", "content": "test-and-diagnostic", "
type": "<event>", "pollingFrequency": "0"}, {"header": "SYS_SH_WebPA_restart", "content": "test-and-diagnostic", "
type": "<event>", "pollingFrequency": "0"}, {"header": "WIFI_ERROR_WIFI_Not_Registered", "content": "ccsp-cr", "type": "
<event>", "pollingFrequency": "0"}, {"header": "SYS_ERROR_PSM_Not_Registered", "content": "ccsp-cr", "type": "<event>", "
pollingFrequency": "0"}, {"header": "WIFI_ERROR_WifiDmCliError", "content": "test-and-diagnostic", "type": "<event>", "
pollingFrequency": "0"}, {"header": "RF_ERROR_IPV4PingFailed", "content": "test-and-diagnostic", "type": "<event>", "
pollingFrequency": "0"}, {"header": "RF_ERROR_IPV4IPV6PingFailed", "content": "test-and-diagnostic", "type": "
<event>", "pollingFrequency": "0"}, {"header": "WIFI_INFO_2G_DISABLED", "content": "test-and-diagnostic", "type": "
<event>", "pollingFrequency": "0"}, {"header": "SYS_INFO_LOGS_UPLOADED", "content": "sysint-broadband", "type": "
<event>", "pollingFrequency": "0"}, {"header": "SYS_ERROR_DHCP_RANGE_CORRUPTION", "content": "bad dhcp-range at
line", "type": "Consolelog.txt.0", "pollingFrequency": "0"}, {"header": "SYS_ERROR_SegFault", "content": "Segmentation
fault", "type": "Consolelog.txt.0", "pollingFrequency": "0"}, {"header": "SYS_INFO_ip_address_recovered", "content": "
sysevent_set_wr:  ipv4_wan_ipaddr", "type": "Consolelog.txt.0", "pollingFrequency": "0"}, {"header": "
RF_INFO_RDKB_FIREWALL_RESTART", "content": "Triggering RDKB_FIREWALL_RESTART", "type": "Consolelog.txt.0", "
pollingFrequency": "0"}, {"header": "SYS_INFO_Factory_reset", "content": "Received reboot_reason as: factory-reset", "
type": "BootTime.log", "pollingFrequency": "0"}, {"header": "SYS_INFO_SW_upgrade_reboot", "content": "
Software_upgrade", "type": "BootTime.log", "pollingFrequency": "0"}, {"header": "XCONF_Dwld_failed", "content": "ccsp-
xconf", "type": "<event>", "pollingFrequency": "0"}, {"header": "bootuptime_EnterWifiCaptivemode_split", "content": "
Enter_WiFi_Personalization_captive_mode", "type": "Consolelog.txt.0", "pollingFrequency": "0"}, {"header": "
SYS_INFO_WANSSH_enabled", "content": "FillPartnerIDValues - Enabling SSH on WAN side", "type": "PAMlog.txt.0", "
pollingFrequency": "0"}, {"header": "Log_upload_disabled", "content": "Log upload is disabled", "type": "Consolelog.
txt.0", "pollingFrequency": "0"}, {"header": "SYS_INFO_ParodusDown", "content": "Unable to connect to server since
interface is down", "type": "PARODUSlog.txt.0", "pollingFrequency": "0"}, {"header": "SYS_INFO_ParodusCurlOK", "
content": "PARODUS: cURL success", "type": "PARODUSlog.txt.0", "pollingFrequency": "0"}, {"header": "
SYS_ERROR_TR69_Not_Registered", "content": "ccsp-cr", "type": "<event>", "pollingFrequency": "0"}, {"header": "
WIFI_ACS_2_split", "content": "Device.WiFi.Radio.2.AutoChannelEnable", "type": "<message_bus>", "pollingFrequency": "
4"}, {"header": "WIFI_INFO_Zero_5G_Clients", "content": "ccsp-wifi-agent", "type": "<event>", "pollingFrequency": "0"},
{"header": "WIFI_INFO_Zero_2G_Clients", "content": "ccsp-wifi-agent", "type": "<event>", "pollingFrequency": "0"},
{"header": "UsedMem_split", "content": "test-and-diagnostic", "type": "<event>", "pollingFrequency": "0"}, {"header": "
UsedCPU_split", "content": "test-and-diagnostic", "type": "<event>", "pollingFrequency": "0"}, {"header": "
WIFI_NF_2_split", "content": "Device.WiFi.Radio.2.Stats.X_COMCAST-COM_NoiseFloor", "type": "<message_bus>", "
pollingFrequency": "24"}, {"header": "WIFI_NF_1_split", "content": "Device.WiFi.Radio.1.Stats.X_COMCAST-
COM_NoiseFloor", "type": "<message_bus>", "pollingFrequency": "24"}, {"header": "HWREV_split", "content": "Device.
DeviceInfo.HardwareVersion", "type": "<message_bus>", "pollingFrequency": "24"}, {"header": "
WIFI_ERROR_Wifi_query_timeout", "content": "test-and-diagnostic", "type": "<event>", "pollingFrequency": "0"},
{"header": "SYS_INFO_Create_GRE_Tunnel", "content": "ccsp-hotspot", "type": "<event>", "pollingFrequency": "0"},
{"header": "WIFI_INFO_Hotspot_client_disconnected", "content": "ccsp-hotspot", "type": "<event>", "pollingFrequency": "
0"}, {"header": "WIFI_INFO_Hotspot_client_connected", "content": "ccsp-hotspot", "type": "<event>", "
pollingFrequency": "0"}, {"header": "SYS_INFO_Hotspot_MaxClients", "content": "ccsp-hotspot", "type": "<event>", "
pollingFrequency": "0"}, {"header": "WIFI_INFO_ClientTransitionToXfinityWifi", "content": "ccsp-hotspot", "type": "
<event>", "pollingFrequency": "0"}, {"header": "Total_Ethernet_Clients_split", "content": "ccsp-lm-lite", "type": "
<event>", "pollingFrequency": "0"}, {"header": "Total_online_clients_split", "content": "ccsp-lm-lite", "type": "
<event>", "pollingFrequency": "0"}, {"header": "Total_devices_connected_split", "content": "ccsp-lm-lite", "type": "
<event>", "pollingFrequency": "0"}, {"header": "Total_offline_clients_split", "content": "ccsp-lm-lite", "type": "
<event>", "pollingFrequency": "0"}, {"header": "Total_wifi_clients_split", "content": "ccsp-lm-lite", "type": "
<event>", "pollingFrequency": "0"}, {"header": "Total_moca_clients_split", "content": "ccsp-lm-lite", "type": "
<event>", "pollingFrequency": "0"}, {"header": "SYS_ERROR_CPU100", "content": "test-and-diagnostic", "type": "<event>", "
pollingFrequency": "0"}], "schedule": "2", "expires": 0, "telemetryProfile": "name": "RDKB-RPI-TEST", "uploadRepository:
URL": "http://xconf.rdkcentral.com/xconf/telemetry_upload.php", "uploadRepository:uploadProtocol": "HTTP"}
root@RaspberryPi-Gateway:~#

```

RPI device Logs

Successful communication logs between device and xconf server in /rdklogs/logs/telemetry2_0.txt.0,


```
210527-06:23:58.447697 [mod=T2, lvl=DEBUG] [tid=2411] T2ER_PushDataWithDelin --out
210527-06:23:59.437327 [mod=T2, lvl=INFO] [tid=2426] doHttpGet:320, T2:Telemetry XCONF communication success
210527-06:23:59.462733 [mod=T2, lvl=DEBUG] [tid=2426] doHttpGet --out
210527-06:23:59.462922 [mod=T2, lvl=DEBUG] [tid=2426] fetchRemoteConfiguration --out
210527-06:23:59.464149 [mod=T2, lvl=DEBUG] [tid=2426] Config received successfully from URL : https://xconf.rdkcentral.com:9892/loguploader/ge
210527-06:23:59.467286 [mod=T2, lvl=DEBUG] [tid=2426] Config received = {"urn:settings:GroupName":"RDKB-RPI-TEST","urn:settings:CheckOnReboot":tru
210527-06:23:59.470951 [mod=T2, lvl=DEBUG] [tid=2426] Config data = {"urn:settings:GroupName":"RDKB-RPI-TEST","urn:settings:CheckOnReboot":tru
210527-06:23:59.476278 [mod=T2, lvl=DEBUG] [tid=2426] upload url = http://35.161.239.220/xconf/telemetry_upload.php
210527-06:23:59.478008 [mod=T2, lvl=DEBUG] [tid=2426] schedule = 2
210527-06:23:59.478164 [mod=T2, lvl=DEBUG] [tid=2426] marker count = 84
210527-06:23:59.478293 [mod=T2, lvl=INFO] [tid=2426] Received profile name : RDKB-RPI-TEST with interval of : 900 secs and upload url : http:/
210527-06:23:59.479719 [mod=T2, lvl=INFO] [tid=2426] Number of tri81params/markers successfully added in profile = 84
210527-06:23:59.482973 [mod=T2, lvl=DEBUG] [tid=2426] processConfigurationXconf --out
210527-06:23:59.483409 [mod=T2, lvl=DEBUG] [tid=2426] clearPersistenceFolder ++in
210527-06:23:59.483595 [mod=T2, lvl=DEBUG] [tid=2426] Executing command : rm -f /nvram/.t2persistentfolder/*
210527-06:23:59.500796 [mod=T2, lvl=DEBUG] [tid=2426] clearPersistenceFolder --out
210527-06:23:59.501002 [mod=T2, lvl=DEBUG] [tid=2426] saveConfigToFile ++in
210527-06:23:59.501634 [mod=T2, lvl=DEBUG] [tid=2426] saveConfigToFile --out
210527-06:23:59.501737 [mod=T2, lvl=DEBUG] [tid=2426] Set new profile : RDKB-RPI-TEST
210527-06:23:59.501840 [mod=T2, lvl=DEBUG] [tid=2426] ReportProfiles_setProfileXconf ++in
210527-06:23:59.501928 [mod=T2, lvl=DEBUG] [tid=2426] ProfileXconf_set ++in
210527-06:23:59.502086 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.502199 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.502320 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.502418 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.502518 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.502618 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.502717 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.502819 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.502920 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.503043 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.503150 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.503257 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.503402 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
210527-06:23:59.503544 [mod=T2, lvl=DEBUG] [tid=2426] updateComponentList --out
- telemetry2_0.txt.0 149/368 40%
```

In T2, Receiving events from RDKB components and comparing those events in Uploaded Makers list in xconf in /rdklogs/logs/telemetry2_0.txt.0,

```
210527-06:24:20.984662 [mod=T2, lvl=DEBUG] [tid=2606] Received signal from T2ER_Push
210527-06:24:20.984762 [mod=T2, lvl=DEBUG] [tid=2606] Checking for events in event queue , event count = 1
210527-06:24:20.984893 [mod=T2, lvl=DEBUG] [tid=2606] Found matching profileIds for event with markerName : WIFI_INFO_CosmWifInit value : 1
210527-06:24:20.984977 [mod=T2, lvl=DEBUG] [tid=2606] Storing in profile : RDKB-RPI-TEST
210527-06:24:20.985059 [mod=T2, lvl=DEBUG] [tid=2606] ReportProfiles_storeMarkerEvent ++in
210527-06:24:20.985141 [mod=T2, lvl=DEBUG] [tid=2606] ProfileXconf_storeMarkerEvent ++in
210527-06:24:20.985289 [mod=T2, lvl=DEBUG] [tid=2606] Increment marker count to : 1
210527-06:24:20.985372 [mod=T2, lvl=DEBUG] [tid=2606] ProfileXconf_storeMarkerEvent --out
210527-06:24:20.985452 [mod=T2, lvl=DEBUG] [tid=2606] ReportProfiles_storeMarkerEvent --out
210527-06:24:20.985537 [mod=T2, lvl=DEBUG] [tid=2606] Checking for events in event queue , event count = 0
210527-06:24:20.985616 [mod=T2, lvl=DEBUG] [tid=2606] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:24:21.343415 [mod=T2, lvl=DEBUG] [tid=2411] T2ER_PushDataWithDelin ++in
210527-06:24:21.343592 [mod=T2, lvl=DEBUG] [tid=2411] Received eventInfo : bootuptime_wifi_split#=#56
210527-06:24:21.343689 [mod=T2, lvl=DEBUG] [tid=2411] Adding eventName : bootuptime_wifi_split eventValue : 56 to t2event queue
210527-06:24:21.343787 [mod=T2, lvl=DEBUG] [tid=2411] T2ER_PushDataWithDelin --out
210527-06:24:21.343836 [mod=T2, lvl=DEBUG] [tid=2606] Received signal from T2ER_Push
210527-06:24:21.343948 [mod=T2, lvl=DEBUG] [tid=2606] Checking for events in event queue , event count = 1
210527-06:24:21.344081 [mod=T2, lvl=WARN] [tid=2606] No Matching Profiles for event with MarkerName : bootuptime_wifi_split Value : 56 - Ignor
210527-06:24:21.344165 [mod=T2, lvl=DEBUG] [tid=2606] Checking for events in event queue , event count = 0
210527-06:24:21.344246 [mod=T2, lvl=DEBUG] [tid=2606] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:27:32.188927 [mod=T2, lvl=DEBUG] [tid=2411] T2ER_PushDataWithDelin ++in
210527-06:27:32.189112 [mod=T2, lvl=DEBUG] [tid=2411] Received eventInfo : bootuptime_ClientConnectComplete_split#=#247
210527-06:27:32.189335 [mod=T2, lvl=DEBUG] [tid=2411] Adding eventName : bootuptime_ClientConnectComplete_split eventValue : 247 to t2event qu
210527-06:27:32.189379 [mod=T2, lvl=DEBUG] [tid=2411] T2ER_PushDataWithDelin --out
210527-06:27:32.189399 [mod=T2, lvl=DEBUG] [tid=2606] Received signal from T2ER_Push
210527-06:27:32.189498 [mod=T2, lvl=DEBUG] [tid=2606] Checking for events in event queue , event count = 1
210527-06:27:32.189755 [mod=T2, lvl=DEBUG] [tid=2606] Found matching profileIds for event with markerName : bootuptime_ClientConnectComplete_s
210527-06:27:32.189844 [mod=T2, lvl=DEBUG] [tid=2606] Starting in profile : RDKB-RPI-TEST
210527-06:27:32.189926 [mod=T2, lvl=DEBUG] [tid=2606] ReportProfiles_storeMarkerEvent ++in
210527-06:27:32.190010 [mod=T2, lvl=DEBUG] [tid=2606] ProfileXconf_storeMarkerEvent ++in
210527-06:27:32.190115 [mod=T2, lvl=DEBUG] [tid=2606] New marker value saved : 247
210527-06:27:32.190231 [mod=T2, lvl=DEBUG] [tid=2606] ProfileXconf_storeMarkerEvent --out
210527-06:27:32.190350 [mod=T2, lvl=DEBUG] [tid=2606] ReportProfiles_storeMarkerEvent --out
210527-06:27:32.190468 [mod=T2, lvl=DEBUG] [tid=2606] Checking for events in event queue , event count = 0
210527-06:27:32.190582 [mod=T2, lvl=DEBUG] [tid=2606] Event Queue size is 0, Waiting events from T2ER_Push
- telemetry2_0.txt.0 368/368 100%
```

JSON Report

Successful logs for sending the JSON report to xconf server in /rdklogs/logs/telemetry2_0.txt.0,


```
$ cat /rdklogs/logs/telemetry2_0.txt.0
```

Telemetry2 Logs

```
RaspberryPi-Gateway:/rdklogs/logs# cat telemetry2_0.txt.0
210527-06:50:44.224195 [mod=T2, lvl=INFO] [tid=2480] Initializing Telemetry 2.0 Component
210527-06:50:44.226510 [mod=T2, lvl=DEBUG] [tid=2480] initTelemetry ++in
210527-06:50:44.226645 [mod=T2, lvl=DEBUG] [tid=2480] initReportProfiles ++in
210527-06:50:44.226775 [mod=T2, lvl=DEBUG] [tid=2480] initScheduler ++in
210527-06:50:44.226867 [mod=T2, lvl=DEBUG] [tid=2480] initScheduler --out
210527-06:50:44.226956 [mod=T2, lvl=DEBUG] [tid=2480] initT2MarkerComponentMap ++in
210527-06:50:44.227054 [mod=T2, lvl=DEBUG] [tid=2480] initT2MarkerComponentMap --out
210527-06:50:44.227137 [mod=T2, lvl=DEBUG] [tid=2480] T2ER_Init ++in
210527-06:50:44.227253 [mod=T2, lvl=DEBUG] [tid=2480] isRBusEnabled ++in
210527-06:50:44.227507 [mod=T2, lvl=DEBUG] [tid=2480] RBUS mode active status = false
210527-06:50:44.227592 [mod=T2, lvl=DEBUG] [tid=2480] isRBusEnabled --out
210527-06:50:44.227673 [mod=T2, lvl=DEBUG] [tid=2480] Register event call back function T2ER_PushDataWithDelim
210527-06:50:44.227764 [mod=T2, lvl=DEBUG] [tid=2480] registerForTelemetryEvents ++in
210527-06:50:44.227870 [mod=T2, lvl=DEBUG] [tid=2480] busInit ++in
210527-06:50:44.227974 [mod=T2, lvl=DEBUG] [tid=2480] isRBusEnabled ++in
210527-06:50:44.228084 [mod=T2, lvl=DEBUG] [tid=2480] RBUS mode active status = false
210527-06:50:44.228167 [mod=T2, lvl=DEBUG] [tid=2480] isRBusEnabled --out
210527-06:50:44.228246 [mod=T2, lvl=DEBUG] [tid=2480] busInit --out
210527-06:50:44.228335 [mod=T2, lvl=DEBUG] [tid=2480] registerCcspT2EventListener ++in
210527-06:50:44.228417 [mod=T2, lvl=DEBUG] [tid=2480] CCSPInterface_Init ++in
210527-06:50:44.242998 [mod=T2, lvl=DEBUG] [tid=2480] CCSPInterface_Init --out
210527-06:50:44.245132 [mod=T2, lvl=INFO] [tid=2480] Registration with CCSP Bus successful, waiting for
Telemetry Events from components...
210527-06:50:44.245330 [mod=T2, lvl=DEBUG] [tid=2480] registerCcspT2EventListener --out
210527-06:50:44.245440 [mod=T2, lvl=DEBUG] [tid=2480] registerForTelemetryEvents --out
210527-06:50:44.356471 [mod=T2, lvl=DEBUG] [tid=2480] T2ER_Init --out
210527-06:50:44.356699 [mod=T2, lvl=DEBUG] [tid=2480] ProfileXConf_init ++in
210527-06:50:44.356829 [mod=T2, lvl=DEBUG] [tid=2480] fetchLocalConfigs ++in
210527-06:50:44.357081 [mod=T2, lvl=DEBUG] [tid=2480] Config file : /nvram/.t2persistentfolder/DCMresponse.txt
210527-06:50:44.357228 [mod=T2, lvl=INFO] [tid=2480] Filename : DCMresponse.txt Size : 11126
210527-06:50:44.357468 [mod=T2, lvl=DEBUG] [tid=2480] Config data size = 11126
210527-06:50:44.358279 [mod=T2, lvl=DEBUG] [tid=2480] Config data = {"urn:settings:GroupName":"RDKB-RPI-TEST",
"urn:settings:CheckOnReboot":true,"urn:settings:CheckSchedule:cron":"2 2 * * *","urn:settings:CheckSchedule:
DurationMinutes":0,"urn:settings:LogUploadSettings:Message":null,"urn:settings:LogUploadSettings:Name":"RDKB-
RPI-TEST","urn:settings:LogUploadSettings:NumberOfDays":0,"urn:settings:LogUploadSettings:
UploadRepositoryName":"RDKB-RPI-TEST","urn:settings:LogUploadSettings:UploadRepository:URL":"h210527-06:50:
44.358694 [mod=T2, lvl=INFO] [tid=2480] Returning 1 local configurations
210527-06:50:44.358823 [mod=T2, lvl=DEBUG] [tid=2480] fetchLocalConfigs --out
210527-06:50:44.358916 [mod=T2, lvl=DEBUG] [tid=2480] Processing config with name : DCMresponse.txt
210527-06:50:44.359020 [mod=T2, lvl=DEBUG] [tid=2480] Config Size = 11126
210527-06:50:44.359138 [mod=T2, lvl=DEBUG] [tid=2480] processConfigurationXConf ++in
210527-06:50:44.359872 [mod=T2, lvl=DEBUG] [tid=2480] config data = {"urn:settings:GroupName":"RDKB-RPI-TEST",
"urn:settings:CheckOnReboot":true,"urn:settings:CheckSchedule:cron":"2 2 * * *","urn:settings:CheckSchedule:
DurationMinutes":0,"urn:settings:LogUploadSettings:Message":null,"urn:settings:LogUploadSettings:Name":"RDKB-
RPI-TEST","urn:settings:LogUploadSettings:NumberOfDays":0,"urn:settings:LogUploadSettings:
UploadRepositoryName":"RDKB-RPI-TEST","urn:settings:LogUploadSettings:UploadRepository:URL":"h210527-06:50:
44.361926 [mod=T2, lvl=DEBUG] [tid=2480] profile name = RDKB-RPI-TEST
210527-06:50:44.362060 [mod=T2, lvl=DEBUG] [tid=2480] upload url = http://35.161.239.220/xconf/telemetry_upload.
php
210527-06:50:44.362203 [mod=T2, lvl=DEBUG] [tid=2480] schedule = 2
210527-06:50:44.362285 [mod=T2, lvl=DEBUG] [tid=2480] marker count = 84
210527-06:50:44.362391 [mod=T2, lvl=INFO] [tid=2480] Received profile name : RDKB-RPI-TEST with interval of :
900 secs and upload url : http://35.161.239.220/xconf/telemetry_upload.php
210527-06:50:44.363169 [mod=T2, lvl=INFO] [tid=2480] Number of tr181params/markers successfully added in
profile = 84
210527-06:50:44.363740 [mod=T2, lvl=DEBUG] [tid=2480] processConfigurationXConf --out
210527-06:50:44.363835 [mod=T2, lvl=DEBUG] [tid=2480] ProfileXConf_set ++in
210527-06:50:44.363992 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364088 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364197 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364294 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364389 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364502 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364602 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
```

```

210527-06:50:44.364703 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364804 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364905 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365010 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365116 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365224 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365360 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365473 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365586 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365701 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365820 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366031 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366159 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366291 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366421 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366554 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366692 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366893 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.367043 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.367246 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.367474 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.367680 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.367811 [mod=T2, lvl=DEBUG] [tid=2480] Found a matching T2Marker
210527-06:50:44.367905 [mod=T2, lvl=DEBUG] [tid=2480] RDKB-RPI-TEST already present in eventlist of
Total_online_clients_split . Ignore updates
210527-06:50:44.368117 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.368339 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.368577 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.368812 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.368996 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.369127 [mod=T2, lvl=DEBUG] [tid=2480] registerProfileWithScheduler ++in : profile - RDKB-RPI-
TEST
210527-06:50:44.369281 [mod=T2, lvl=INFO] [tid=2480] Starting TimeoutThread for profile : RDKB-RPI-TEST
210527-06:50:44.369610 [mod=T2, lvl=DEBUG] [tid=2480] registerProfileWithScheduler --out
210527-06:50:44.369716 [mod=T2, lvl=INFO] [tid=2480] Successfully set profile : RDKB-RPI-TEST
210527-06:50:44.369828 [mod=T2, lvl=DEBUG] [tid=2480] ProfileXConf_set --out
210527-06:50:44.369935 [mod=T2, lvl=DEBUG] [tid=2504] TimeoutThread ++in
210527-06:50:44.370145 [mod=T2, lvl=INFO] [tid=2504] Waiting for 900 sec for next TIMEOUT for profile - RDKB-
RPI-TEST
210527-06:50:44.369943 [mod=T2, lvl=INFO] [tid=2480] Successfully set new profile: RDKB-RPI-TEST
210527-06:50:44.384757 [mod=T2, lvl=DEBUG] [tid=2480] ProfileXConf_init --out
210527-06:50:44.384917 [mod=T2, lvl=DEBUG] [tid=2480] getParameterValue ++in
210527-06:50:44.385043 [mod=T2, lvl=DEBUG] [tid=2480] getCCSPParamVal ++in
210527-06:50:44.385178 [mod=T2, lvl=DEBUG] [tid=2480] ccspGetParameterValues ++in
210527-06:50:44.385275 [mod=T2, lvl=DEBUG] [tid=2480] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENTRAL-COM_RFC.Feature.Telemetry.Version
210527-06:50:44.393891 [mod=T2, lvl=DEBUG] [tid=2480] destCompName = eRT.com.cisco.sptvg.ccsp.pam destPath =
/com/cisco/sptvg/ccsp/pam
210527-06:50:44.394110 [mod=T2, lvl=DEBUG] [tid=2480] findDestComponent --out
210527-06:50:44.394244 [mod=T2, lvl=DEBUG] [tid=2480] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.Version, paramCount : 1 Destination name : eRT.com.cisco.
sptvg.ccsp.pam and path /com/cisco/sptvg/ccsp/pam
210527-06:50:44.397406 [mod=T2, lvl=DEBUG] [tid=2480] ccspGetParameterValues --out
210527-06:50:44.397582 [mod=T2, lvl=DEBUG] [tid=2480] Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.
Version = 2
210527-06:50:44.397708 [mod=T2, lvl=DEBUG] [tid=2480] getCCSPParamVal --out
210527-06:50:44.397794 [mod=T2, lvl=DEBUG] [tid=2480] getParameterValue --out
210527-06:50:44.397927 [mod=T2, lvl=DEBUG] [tid=2480] ProfileXConf is set
210527-06:50:44.398020 [mod=T2, lvl=DEBUG] [tid=2480] isRbusEnabled ++in
210527-06:50:44.398161 [mod=T2, lvl=DEBUG] [tid=2480] RBUS mode active status = false
210527-06:50:44.398258 [mod=T2, lvl=DEBUG] [tid=2480] isRbusEnabled --out
210527-06:50:44.398368 [mod=T2, lvl=DEBUG] [tid=2480] T2ER_StartDispatchThread ++in
210527-06:50:44.398693 [mod=T2, lvl=DEBUG] [tid=2480] T2ER_StartDispatchThread --out
210527-06:50:44.398800 [mod=T2, lvl=DEBUG] [tid=2512] T2ER_EventDispatchThread ++in
210527-06:50:44.398931 [mod=T2, lvl=DEBUG] [tid=2512] Checking for events in event queue , event count = 0
210527-06:50:44.399016 [mod=T2, lvl=DEBUG] [tid=2512] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:44.398806 [mod=T2, lvl=DEBUG] [tid=2480] initReportProfiles --out
210527-06:50:44.400249 [mod=T2, lvl=INFO] [tid=2480] Init ReportProfiles Successful
210527-06:50:44.400369 [mod=T2, lvl=DEBUG] [tid=2480] initXConfClient ++in
210527-06:50:44.400490 [mod=T2, lvl=DEBUG] [tid=2480] startXConfClient ++in
210527-06:50:44.400962 [mod=T2, lvl=DEBUG] [tid=2480] startXConfClient --out

```

```
210527-06:50:44.401059 [mod=T2, lvl=DEBUG] [tid=2513] getUpdatedConfigurationThread ++in
210527-06:50:44.401179 [mod=T2, lvl=DEBUG] [tid=2513] getRemoteConfigURL ++in
210527-06:50:44.401336 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.401462 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.401580 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.401725 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENTRAL-COM_RFC.Feature.Telemetry.ConfigURL
210527-06:50:44.401078 [mod=T2, lvl=DEBUG] [tid=2480] initXConfClient --out
210527-06:50:44.402751 [mod=T2, lvl=INFO] [tid=2480] Init Xconf Client Success
210527-06:50:44.403713 [mod=T2, lvl=DEBUG] [tid=2480] initTelemetry --out
210527-06:50:44.403814 [mod=T2, lvl=DEBUG] [tid=2480] initTelemetry --out
210527-06:50:44.403907 [mod=T2, lvl=INFO] [tid=2480] Telemetry 2.0 Component Init Success
210527-06:50:44.404502 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.404643 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.404751 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.ConfigURL, paramCount : 1 Destination name : eRT.com.cisco.
spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-06:50:44.408259 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.408442 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.
ConfigURL = https://xconf.rdkcentral.com:9092/loguploader/getT2Settings
210527-06:50:44.408533 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.408616 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.408719 [mod=T2, lvl=INFO] [tid=2513] Setting config URL base location to : https://xconf.
rdkcentral.com:9092/loguploader/getT2Settings
210527-06:50:44.408803 [mod=T2, lvl=DEBUG] [tid=2513] getRemoteConfigURL --out
210527-06:50:44.408884 [mod=T2, lvl=DEBUG] [tid=2513] fetchRemoteConfiguration ++in
210527-06:50:44.408968 [mod=T2, lvl=DEBUG] [tid=2513] appendRequestParams ++in
210527-06:50:44.409073 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.409180 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.409284 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.409375 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
X_COMCAST-COM_WAN_MAC
210527-06:50:44.412200 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.412414 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.412521 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST-COM_WAN_MAC, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com
/cisco/spvtg/ccsp/pam
210527-06:50:44.417216 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.417385 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.X_COMCAST-COM_WAN_MAC = b8:27:eb:1b:56:
4c
210527-06:50:44.417476 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.417558 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.417688 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.417773 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.417854 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.417937 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
SoftwareVersion
210527-06:50:44.422401 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.422576 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.422698 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.SoftwareVersion, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco
/spvtg/ccsp/pam
210527-06:50:44.446401 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.446590 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.SoftwareVersion = rdkb-generic-
broadband-image_TDK_rdk-next_20210526115302
210527-06:50:44.446709 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.446793 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.446880 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.446977 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.447059 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.447146 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
ModelName
210527-06:50:44.450205 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.450402 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.450495 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.ModelName, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg
/ccsp/pam
```

```
210527-06:50:44.482267 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.482567 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.ModelName = RPI
210527-06:50:44.482709 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.482795 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.482913 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.483015 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.483101 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.483202 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENTRAL-COM_Syndication.PartnerId
210527-06:50:44.491006 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.491186 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.491275 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_RDKCENTRAL-COM_Syndication.PartnerId, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.
pam and path /com/cisco/spvtg/ccsp/pam
210527-06:50:44.493930 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.494096 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.X_RDKCENTRAL-COM_Syndication.PartnerId
= RDKM
210527-06:50:44.494189 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.494280 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.494410 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.494521 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.494639 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.494742 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENTRAL-COM_RFC.Feature.AccountInfo.AccountID
210527-06:50:44.499092 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.499265 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.499373 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AccountInfo.AccountID, paramCount : 1 Destination name : eRT.com.cisco.
spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-06:50:44.502496 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.502698 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.
AccountInfo.AccountID =
210527-06:50:44.502818 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.502938 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.503045 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.503143 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.503249 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.503368 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
X_COMCAST-COM_CM_MAC
210527-06:50:44.510118 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.510291 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.510395 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST-COM_CM_MAC, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com
/cisco/spvtg/ccsp/pam
210527-06:50:44.555974 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.556186 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.X_COMCAST-COM_CM_MAC = B8:27:EB:1B:56:4C
210527-06:50:44.556290 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.556379 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.556661 [mod=T2, lvl=DEBUG] [tid=2513] appendRequestParams:216 Final http get URL if size 782 is
:
https://xconf.rdkcentral.com:9092/loguploader/getT2Settings?estbMacAddress=b8:27:eb:1b:56:
4c&firmwareVersion=rdkb-generic-broadband-image_TDK_rdk-
next_20210526115302&model=RPI&partnerId=RDKM&accountId=&ecmMacAddress=B8:27:EB:1B:56:
4C&env=dev&controllerId=2504&channelMapId=2345&vodId=15660&version=2
210527-06:50:44.556829 [mod=T2, lvl=DEBUG] [tid=2513] appendRequestParams --out
210527-06:50:44.556912 [mod=T2, lvl=DEBUG] [tid=2513] doHttpGet ++in
210527-06:50:44.556995 [mod=T2, lvl=INFO] [tid=2513] doHttpGet with url https://xconf.rdkcentral.com:19092
/loguploader/getT2Settings?estbMacAddress=b8:27:eb:1b:56:4c&firmwareVersion=rdkb-generic-broadband-
image_TDK_rdk-next_20210526115302&model=RPI&partnerId=RDKM&accountId=&ecmMacAddress=B8:27:EB:1B:56:
4C&env=dev&controllerId=2504&channelMapId=2345&vodId=15660&version=2
210527-06:50:44.722913 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:44.723097 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : SYS_SH_RDKB_FIREWALL_RESTART<#=#>1
210527-06:50:44.723246 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : SYS_SH_RDKB_FIREWALL_RESTART
eventValue : 1 to t2event queue
210527-06:50:44.723418 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:50:44.723604 [mod=T2, lvl=DEBUG] [tid=2512] Received signal from T2ER_Push
210527-06:50:44.723692 [mod=T2, lvl=DEBUG] [tid=2512] Checking for events in event queue , event count = 1
210527-06:50:44.723824 [mod=T2, lvl=WARN] [tid=2512] No Matching Profiles for event with MarkerName :
```



```
SYS_SH_RDKB_FIREWALL_RESTART Value : 1 - Ignoring
210527-06:50:44.723917 [mod=T2, lvl=DEBUG] [tid=2512] Checking for events in event queue , event count = 0
210527-06:50:44.724027 [mod=T2, lvl=DEBUG] [tid=2512] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:44.861693 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:44.861876 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : RF_ERROR_wan_restart<##=>1
210527-06:50:44.861988 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : RF_ERROR_wan_restart eventValue : 1 to
t2event queue
210527-06:50:44.862098 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:50:44.862271 [mod=T2, lvl=DEBUG] [tid=2512] Received signal from T2ER_Push
210527-06:50:44.862375 [mod=T2, lvl=DEBUG] [tid=2512] Checking for events in event queue , event count = 1
210527-06:50:44.862523 [mod=T2, lvl=WARN] [tid=2512] No Matching Profiles for event with MarkerName :
RF_ERROR_wan_restart Value : 1 - Ignoring
210527-06:50:44.862617 [mod=T2, lvl=DEBUG] [tid=2512] Checking for events in event queue , event count = 0
210527-06:50:44.862713 [mod=T2, lvl=DEBUG] [tid=2512] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:45.733183 [mod=T2, lvl=INFO] [tid=2513] doHttpGet:320, T2:Telemetry XCONF communication success
210527-06:50:45.747311 [mod=T2, lvl=DEBUG] [tid=2513] doHttpGet --out
210527-06:50:45.747489 [mod=T2, lvl=DEBUG] [tid=2513] fetchRemoteConfiguration --out
210527-06:50:45.747576 [mod=T2, lvl=DEBUG] [tid=2513] Config received successfully from URL : https://xconf.
rdkcentral.com:19092/loguploader/getT2Settings
210527-06:50:45.748496 [mod=T2, lvl=DEBUG] [tid=2513] Config received = {"urn:settings:GroupName":"RDKB-RPI-
TEST","urn:settings:CheckOnReboot":true,"urn:settings:CheckSchedule:cron":"2 2 * * *","urn:settings:
CheckSchedule:DurationMinutes":0,"urn:settings:LogUploadSettings:Message":null,"urn:settings:LogUploadSettings:
Name":"RDKB-RPI-TEST","urn:settings:LogUploadSettings:NumberOfDays":0,"urn:settings:LogUploadSettings:
UploadRepositoryName":"RDKB-RPI-TEST","urn:settings:LogUploadSettings:UploadRepository:URL":210527-06:50:
45.749017 [mod=T2, lvl=DEBUG] [tid=2513] processConfigurationXConf ++in
210527-06:50:45.749773 [mod=T2, lvl=DEBUG] [tid=2513] config data = {"urn:settings:GroupName":"RDKB-RPI-TEST","
urn:settings:CheckOnReboot":true,"urn:settings:CheckSchedule:cron":"2 2 * * *","urn:settings:CheckSchedule:
DurationMinutes":0,"urn:settings:LogUploadSettings:Message":null,"urn:settings:LogUploadSettings:Name":"RDKB-
RPI-TEST","urn:settings:LogUploadSettings:NumberOfDays":0,"urn:settings:LogUploadSettings:
UploadRepositoryName":"RDKB-RPI-TEST","urn:settings:LogUploadSettings:UploadRepository:URL":"h210527-06:50:
45.752717 [mod=T2, lvl=DEBUG] [tid=2513] profile name = RDKB-RPI-TEST
210527-06:50:45.752899 [mod=T2, lvl=DEBUG] [tid=2513] upload url = http://35.161.239.220/xconf/telemetry_upload.
php
210527-06:50:45.752990 [mod=T2, lvl=DEBUG] [tid=2513] schedule = 2
210527-06:50:45.753074 [mod=T2, lvl=DEBUG] [tid=2513] marker count = 84
210527-06:50:45.753160 [mod=T2, lvl=INFO] [tid=2513] Received profile name : RDKB-RPI-TEST with interval of :
900 secs and upload url : http://35.161.239.220/xconf/telemetry_upload.php
210527-06:50:45.754081 [mod=T2, lvl=INFO] [tid=2513] Number of tr181params/markers successfully added in
profile = 84
210527-06:50:45.755185 [mod=T2, lvl=DEBUG] [tid=2513] processConfigurationXConf --out
210527-06:50:45.755354 [mod=T2, lvl=INFO] [tid=2513] Profile exists already, updating the config in file system
210527-06:50:45.755447 [mod=T2, lvl=DEBUG] [tid=2513] saveConfigToFile ++in
210527-06:50:45.757114 [mod=T2, lvl=DEBUG] [tid=2513] saveConfigToFile --out
210527-06:50:45.757265 [mod=T2, lvl=DEBUG] [tid=2513] Disable and Delete old profile RDKB-RPI-TEST
210527-06:50:45.757368 [mod=T2, lvl=DEBUG] [tid=2513] ReportProfiles_deleteProfileXConf ++in
210527-06:50:45.757452 [mod=T2, lvl=DEBUG] [tid=2513] ProfileXConf is set
210527-06:50:45.757540 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_StopDispatchThread ++in
210527-06:50:45.757688 [mod=T2, lvl=DEBUG] [tid=2512] Received signal from T2ER_Push
210527-06:50:45.757791 [mod=T2, lvl=DEBUG] [tid=2512] T2ER_EventDispatchThread --out
210527-06:50:45.757976 [mod=T2, lvl=DEBUG] [tid=2513] flushCacheFromFile ++in
210527-06:50:45.758350 [mod=T2, lvl=DEBUG] [tid=2513] T2: Sending cache event : btime_moca_split<##=>30
210527-06:50:45.758457 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim ++in
210527-06:50:45.758542 [mod=T2, lvl=DEBUG] [tid=2513] Received eventInfo : btime_moca_split<##=>30
210527-06:50:45.758630 [mod=T2, lvl=DEBUG] [tid=2513] Adding eventName : btime_moca_split eventValue : 30 to
t2event queue
210527-06:50:45.758732 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim --out
210527-06:50:45.758816 [mod=T2, lvl=DEBUG] [tid=2513] T2: Sending cache event :
bootuptime_SNMPV2Ready_split<##=>32
210527-06:50:45.758897 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim ++in
210527-06:50:45.758978 [mod=T2, lvl=DEBUG] [tid=2513] Received eventInfo : bootuptime_SNMPV2Ready_split<##=>32
210527-06:50:45.759063 [mod=T2, lvl=DEBUG] [tid=2513] Adding eventName : bootuptime_SNMPV2Ready_split
eventValue : 32 to t2event queue
210527-06:50:45.759145 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim --out
210527-06:50:45.759445 [mod=T2, lvl=DEBUG] [tid=2513] T2: Sending cache event :
SYS_SH_RDKB_FIREWALL_RESTART<##=>1
210527-06:50:45.759559 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim ++in
210527-06:50:45.759643 [mod=T2, lvl=DEBUG] [tid=2513] Received eventInfo : SYS_SH_RDKB_FIREWALL_RESTART<##=>1
210527-06:50:45.759730 [mod=T2, lvl=DEBUG] [tid=2513] Adding eventName : SYS_SH_RDKB_FIREWALL_RESTART
eventValue : 1 to t2event queue
210527-06:50:45.760031 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim --out
210527-06:50:45.760494 [mod=T2, lvl=DEBUG] [tid=2513] fopen failed for /tmp/t2_atom_caching_file
```

```
210527-06:50:45.761094 [mod=T2, lvl=DEBUG] [tid=2513] flushCacheFromFile --out
210527-06:50:45.761251 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_StopDispatchThread --out
210527-06:50:45.761352 [mod=T2, lvl=DEBUG] [tid=2513] clearT2MarkerComponentMap ++in
210527-06:50:45.761868 [mod=T2, lvl=DEBUG] [tid=2513] clearT2MarkerComponentMap --out
210527-06:50:45.761989 [mod=T2, lvl=DEBUG] [tid=2513] updateMarkerComponentMap ++in
210527-06:50:45.762073 [mod=T2, lvl=DEBUG] [tid=2513] updateMarkerComponentMap --out
210527-06:50:45.762166 [mod=T2, lvl=DEBUG] [tid=2513] ProfileXConf_delete ++in
210527-06:50:45.762266 [mod=T2, lvl=INFO] [tid=2513] removing profile : RDKB-RPI-TEST
210527-06:50:45.762502 [mod=T2, lvl=DEBUG] [tid=2513] ProfileXConf_delete --out
210527-06:50:45.762590 [mod=T2, lvl=DEBUG] [tid=2513] Set new profile : RDKB-RPI-TEST
210527-06:50:45.762951 [mod=T2, lvl=DEBUG] [tid=2513] ReportProfiles_setProfileXConf ++in
210527-06:50:45.763076 [mod=T2, lvl=DEBUG] [tid=2513] ProfileXConf_set ++in
210527-06:50:45.767168 [mod=T2, lvl=ERROR] [tid=2513] Component name list is not initialized . Re-initializing
210527-06:50:45.767419 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.767541 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.767657 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.767775 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.767874 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.767974 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.768073 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.768330 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.773294 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.773469 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.773610 [mod=T2, lvl=DEBUG] [tid=2513] Found a matching T2Marker
210527-06:50:45.773695 [mod=T2, lvl=DEBUG] [tid=2513] RDKB-RPI-TEST already present in eventlist of
Total_online_clients_split . Ignore updates
210527-06:50:45.774410 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.774631 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.774800 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.774987 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.775328 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.775434 [mod=T2, lvl=DEBUG] [tid=2513] registerProfileWithScheduler ++in : profile - RDKB-RPI-
TEST
210527-06:50:45.775542 [mod=T2, lvl=INFO] [tid=2513] Scheduler already assigned for profile RDKB-RPI-TEST ,
exiting .
210527-06:50:45.775624 [mod=T2, lvl=DEBUG] [tid=2513] registerProfileWithScheduler --out
210527-06:50:45.775705 [mod=T2, lvl=INFO] [tid=2513] Successfully set profile : RDKB-RPI-TEST
210527-06:50:45.775785 [mod=T2, lvl=DEBUG] [tid=2513] ProfileXConf_set --out
210527-06:50:45.775865 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_StartDispatchThread ++in
210527-06:50:45.776072 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_StartDispatchThread --out
210527-06:50:45.776116 [mod=T2, lvl=DEBUG] [tid=2806] T2ER_EventDispatchThread ++in
210527-06:50:45.776312 [mod=T2, lvl=DEBUG] [tid=2513] ReportProfiles_setProfileXConf --out
210527-06:50:45.776391 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 3
210527-06:50:45.776544 [mod=T2, lvl=INFO] [tid=2513] Successfully set new profile : RDKB-RPI-TEST
210527-06:50:45.776661 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
btime_moca_split Value : 30 - Ignoring
210527-06:50:45.776721 [mod=T2, lvl=DEBUG] [tid=2513] getUpdatedConfigurationThread --out
210527-06:50:45.776750 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 2
210527-06:50:45.776926 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
bootuptime_SNMPV2Ready_split Value : 32 - Ignoring
210527-06:50:45.777011 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:50:45.777148 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
SYS_SH_RDKB_FIREWALL_RESTART Value : 1 - Ignoring
210527-06:50:45.777233 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:50:45.777325 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:47.890478 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:47.890740 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : btime_waninit_split<##>38
210527-06:50:47.890878 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : btime_waninit_split eventValue : 38 to
t2event queue
210527-06:50:47.891062 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:50:47.891285 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:50:47.891387 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:50:47.891574 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
btime_waninit_split Value : 38 - Ignoring
210527-06:50:47.891681 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:50:47.891771 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:55.141136 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:55.141327 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : SYS_SH_RDKB_FIREWALL_RESTART<##>1
210527-06:50:55.141422 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : SYS_SH_RDKB_FIREWALL_RESTART
eventValue : 1 to t2event queue
210527-06:50:55.141527 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
```

```
210527-06:50:55.141669 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:50:55.141755 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:50:55.141886 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
SYS_SH_RDKB_FIREWALL_RESTART Value : 1 - Ignoring
210527-06:50:55.141969 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:50:55.142048 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:55.903766 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:55.903975 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : btime_eth_split<#=#>46
210527-06:50:55.904092 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : btime_eth_split eventValue : 46 to
t2event queue
210527-06:50:55.904205 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:50:55.904385 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:50:55.904480 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:50:55.904616 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
btime_eth_split Value : 46 - Ignoring
210527-06:50:55.904721 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:50:55.904804 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:56.103099 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:56.103339 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : SYS_SH_RDKB_FIREWALL_RESTART<#=#>1
210527-06:50:56.103435 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : SYS_SH_RDKB_FIREWALL_RESTART
eventValue : 1 to t2event queue
210527-06:50:56.103565 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:50:56.103705 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:50:56.103791 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:50:56.103920 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
SYS_SH_RDKB_FIREWALL_RESTART Value : 1 - Ignoring
210527-06:50:56.104005 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:50:56.104084 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:04.031749 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:04.031940 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_ERROR_PSM_GetRecordFail<#=#>1
210527-06:51:04.032051 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_ERROR_PSM_GetRecordFail
eventValue : 1 to t2event queue
210527-06:51:04.032161 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:51:04.032301 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:04.032388 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:04.032542 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_ERROR_PSM_GetRecordFail value : 1
210527-06:51:04.032626 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:51:04.032718 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:51:04.032805 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:51:04.032890 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 1
210527-06:51:04.032970 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:51:04.033062 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:51:04.033147 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:04.033227 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:04.405652 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:04.405769 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_ERROR_PSM_GetRecordFail<#=#>1
210527-06:51:04.405862 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_ERROR_PSM_GetRecordFail
eventValue : 1 to t2event queue
210527-06:51:04.405966 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:51:04.406103 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:04.406190 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:04.406316 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_ERROR_PSM_GetRecordFail value : 1
210527-06:51:04.406412 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:51:04.406493 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:51:04.406574 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:51:04.406659 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 2
210527-06:51:04.406737 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:51:04.406817 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:51:04.406899 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:04.406980 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:05.996497 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:05.996640 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_ERROR_PSM_GetRecordFail<#=#>1
210527-06:51:05.996797 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_ERROR_PSM_GetRecordFail
eventValue : 1 to t2event queue
210527-06:51:05.996903 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:51:05.997036 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:05.997122 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:05.997251 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_ERROR_PSM_GetRecordFail value : 1
```



```
210527-06:51:05.997333 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:51:05.997414 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:51:05.997495 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:51:05.997581 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 3
210527-06:51:05.997661 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:51:05.997740 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:51:05.997836 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:05.997917 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:06.142735 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:06.142882 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_ERROR_PSM_GetRecordFail<##=>1
210527-06:51:06.142977 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_ERROR_PSM_GetRecordFail
eventValue : 1 to t2event queue
210527-06:51:06.143088 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:51:06.143230 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:06.143345 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:06.143495 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_ERROR_PSM_GetRecordFail value : 1
210527-06:51:06.143607 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:51:06.143709 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:51:06.143835 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:51:06.143935 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 4
210527-06:51:06.144020 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:51:06.144099 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:51:06.144186 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:06.144283 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:06.804651 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:06.804836 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_INFO_CosaWifiiinit<##=>1
210527-06:51:06.804949 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_INFO_CosaWifiiinit eventValue : 1
to t2event queue
210527-06:51:06.805112 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:51:06.805274 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:06.805375 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:06.805501 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_INFO_CosaWifiiinit value : 1
210527-06:51:06.805599 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:51:06.805682 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:51:06.805767 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:51:06.805852 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 1
210527-06:51:06.805931 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:51:06.806032 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:51:06.806116 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:06.806267 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:07.121048 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:07.121249 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : bootuptime_wifi_split<##=>57
210527-06:51:07.121345 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : bootuptime_wifi_split eventValue : 57
to t2event queue
210527-06:51:07.121450 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:51:07.121591 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:07.121677 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:07.121806 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
bootuptime_wifi_split Value : 57 - Ignoring
210527-06:51:07.121891 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:07.121986 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:52:48.327283 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:52:48.327453 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo :
bootuptime_ClientConnectComplete_split<##=>158
210527-06:52:48.327610 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : bootuptime_ClientConnectComplete_split
eventValue : 158 to t2event queue
210527-06:52:48.327782 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:52:48.327936 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:52:48.328048 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:52:48.328246 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
bootuptime_ClientConnectComplete_split value : 158
210527-06:52:48.328353 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:52:48.328443 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:52:48.328537 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:52:48.328622 [mod=T2, lvl=DEBUG] [tid=2806] New marker value saved : 158
210527-06:52:48.328702 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:52:48.328781 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:52:48.328865 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:52:48.328944 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
```

```
210527-06:53:48.952569 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:53:48.952792 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_INFO_clientdisconnect<#=#>1
210527-06:53:48.952899 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_INFO_clientdisconnect eventValue
: 1 to t2event queue
210527-06:53:48.953031 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:53:48.953241 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:53:48.953353 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:53:48.953550 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_INFO_clientdisconnect value : 1
210527-06:53:48.953690 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:53:48.953822 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:53:48.953916 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:53:48.954000 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 1
210527-06:53:48.954080 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:53:48.954169 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:53:48.954299 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:53:48.954433 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:55:50.562218 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:55:50.562399 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_INFO_clientdisconnect<#=#>1
210527-06:55:50.562502 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_INFO_clientdisconnect eventValue
: 1 to t2event queue
210527-06:55:50.562605 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:55:50.562643 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:55:50.562893 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:55:50.563036 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_INFO_clientdisconnect value : 1
210527-06:55:50.563126 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:55:50.563214 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:55:50.563303 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:55:50.563401 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 2
210527-06:55:50.563481 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:55:50.563561 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:55:50.563644 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:55:50.563724 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:56:50.182976 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:56:50.183138 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_INFO_clientdisconnect<#=#>1
210527-06:56:50.183238 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_INFO_clientdisconnect eventValue
: 1 to t2event queue
210527-06:56:50.183342 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:56:50.183381 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:56:50.183497 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:56:50.183632 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_INFO_clientdisconnect value : 1
210527-06:56:50.183716 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:56:50.183797 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:56:50.183880 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:56:50.183984 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 3
210527-06:56:50.184064 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:56:50.184142 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:56:50.184225 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:56:50.184304 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-07:05:44.000155 [mod=T2, lvl=INFO] [tid=2504] TIMEOUT for profile - RDKB-RPI-TEST
210527-07:05:44.000380 [mod=T2, lvl=INFO] [tid=2504] ReportProfiles_TimeoutCb ++in
210527-07:05:44.000479 [mod=T2, lvl=DEBUG] [tid=2504] ProfileXConf_notifyTimeout ++in
210527-07:05:44.000763 [mod=T2, lvl=DEBUG] [tid=2504] ProfileXConf_notifyTimeout --out
210527-07:05:44.000840 [mod=T2, lvl=INFO] [tid=10812] CollectAndReportXconf ++in profileName : RDKB-RPI-TEST
210527-07:05:44.000850 [mod=T2, lvl=INFO] [tid=2504] ReportProfiles_TimeoutCb --out
210527-07:05:44.001026 [mod=T2, lvl=INFO] [tid=2504] Waiting for 900 sec for next TIMEOUT for profile - RDKB-
RPI-TEST
210527-07:05:44.001185 [mod=T2, lvl=DEBUG] [tid=10812] getProfileParameterValues ++in
210527-07:05:44.001289 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPPProfileParamValues ++in
210527-07:05:44.001381 [mod=T2, lvl=INFO] [tid=10812] TR-181 Param count : 7
210527-07:05:44.001469 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.001552 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_COMCAST-COM_WAN_MAC
210527-07:05:44.003602 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.003719 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.003805 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST-COM_WAN_MAC, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com
/cisco/spvtg/ccsp/pam
```

```
210527-07:05:44.005938 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.006072 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.006158 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_COMCAST-COM_WAN_IP
210527-07:05:44.007953 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.008067 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.008169 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST-COM_WAN_IP, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com
/cisco/spvtg/ccsp/pam
210527-07:05:44.010227 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.010346 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.010430 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_COMCAST-COM_WAN_IPv6
210527-07:05:44.012460 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.012606 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.012693 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST-COM_WAN_IPv6, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com
/cisco/spvtg/ccsp/pam
210527-07:05:44.014713 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.014833 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.014920 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENTRAL-COM_Syndication.PartnerId
210527-07:05:44.016763 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.016881 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.016969 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_RDKCENTRAL-COM_Syndication.PartnerId, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.
pam and path /com/cisco/spvtg/ccsp/pam
210527-07:05:44.019001 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.019121 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.019207 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
SoftwareVersion
210527-07:05:44.021236 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.021362 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.021452 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.SoftwareVersion, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco
/spvtg/ccsp/pam
210527-07:05:44.035007 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.035167 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.035253 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENTRAL-COM_RFC.Feature.AccountInfo.AccountID
210527-07:05:44.037183 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.037302 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.037454 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AccountInfo.AccountID, paramCount : 1 Destination name : eRT.com.cisco.
spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-07:05:44.039472 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.039596 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.039682 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.Time.
CurrentLocalTime
210527-07:05:44.041650 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.041776 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.041865 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.Time.
CurrentLocalTime, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp
/pam
210527-07:05:44.074549 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.074704 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPProfileParamValues --Out
210527-07:05:44.074789 [mod=T2, lvl=DEBUG] [tid=10812] getProfileParameterValues --Out
210527-07:05:44.074870 [mod=T2, lvl=INFO] [tid=10812] Fetch complete for TR-181 Object/Parameter Values for
parameters
210527-07:05:44.074990 [mod=T2, lvl=DEBUG] [tid=10812] encodeParamResultInJSON ++in
210527-07:05:44.075080 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : mac valueCount = 1
210527-07:05:44.075193 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : erouterIpv4 valueCount = 1
210527-07:05:44.075282 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : erouterIpv6 valueCount = 1
210527-07:05:44.075369 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : PartnerId valueCount = 1
210527-07:05:44.075454 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : Version valueCount = 1
```

```

210527-07:05:44.075540 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : AccountId valueCount = 1
210527-07:05:44.075641 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : LT_split valueCount = 1
210527-07:05:44.075725 [mod=T2, lvl=DEBUG] [tid=10812] encodeParamResultInJSON --Out
210527-07:05:44.075806 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.075905 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.075986 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076067 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.076146 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076228 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.076307 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076389 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.076468 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076550 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.076629 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076718 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.076797 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076881 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.076974 [mod=T2, lvl=DEBUG] [tid=10812] getGrepResults ++in
210527-07:05:44.077063 [mod=T2, lvl=DEBUG] [tid=10812] getDCAResultsInVector ++in
210527-07:05:44.077162 [mod=T2, lvl=DEBUG] [tid=10812] initProperties ++in
210527-07:05:44.077377 [mod=T2, lvl=DEBUG] [tid=10812] updateIncludeConfVal ++in
210527-07:05:44.077577 [mod=T2, lvl=DEBUG] [tid=10812] updateIncludeConfVal --out
210527-07:05:44.077682 [mod=T2, lvl=DEBUG] [tid=10812] initProperties --out
210527-07:05:44.077768 [mod=T2, lvl=DEBUG] [tid=10812] parseMarkerList ++in
210527-07:05:44.077854 [mod=T2, lvl=DEBUG] [tid=10812] vMarkerList for profile RDKB-RPI-TEST is of count = 41
210527-07:05:44.077940 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekMapForProfile ++in
210527-07:05:44.078073 [mod=T2, lvl=DEBUG] [tid=10812] Get profileseek map for RDKB-RPI-TEST
210527-07:05:44.078154 [mod=T2, lvl=DEBUG] [tid=10812] Profile seek map doesn't exist, creating one ...
210527-07:05:44.078240 [mod=T2, lvl=DEBUG] [tid=10812] profileSeekMap count 0
210527-07:05:44.078328 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekMapForProfile --out
210527-07:05:44.078409 [mod=T2, lvl=DEBUG] [tid=10812] logSeekMap is null, add logSeekMap for RDKB-RPI-TEST
210527-07:05:44.078495 [mod=T2, lvl=DEBUG] [tid=10812] addToProfileSeekMap ++in for profileName = RDKB-RPI-TEST
210527-07:05:44.078576 [mod=T2, lvl=DEBUG] [tid=10812] Adding GrepSeekProfile for profile RDKB-RPI-TEST in
profileSeekMap
210527-07:05:44.078667 [mod=T2, lvl=DEBUG] [tid=10812] addToProfileSeekMap --out
210527-07:05:44.079089 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:44.079178 [mod=T2, lvl=DEBUG] [tid=10812] processTr181Objects ++in
210527-07:05:44.079269 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.079356 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.079436 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.079517 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
UpTime
210527-07:05:44.081727 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.081863 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.081951 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.UpTime, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp
/pam
210527-07:05:44.084014 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.084125 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.UpTime = 934
210527-07:05:44.084213 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.084294 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.084389 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.084492 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.084585 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.084666 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.084746 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.084828 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_COMCAST-COM_CM_MAC
210527-07:05:44.086695 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.086811 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.086899 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST-COM_CM_MAC, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com
/cisco/spvtg/ccsp/pam
210527-07:05:44.106190 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.106363 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.X_COMCAST-COM_CM_MAC = B8:27:EB:1B:56:
4C
210527-07:05:44.106454 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.106536 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.106618 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in

```

```
210527-07:05:44.106699 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.106781 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.106860 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.106941 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.107023 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENTRAL-COM_EnableXDNS
210527-07:05:44.108916 [mod=T2, lvl=ERROR] [tid=10812] Failed to get component for Device.DeviceInfo.
X_RDKCENTRAL-COM_EnableXDNS ret: 204
210527-07:05:44.109025 [mod=T2, lvl=ERROR] [tid=10812] Unable to find supporting component for parameter :
Device.DeviceInfo.X_RDKCENTRAL-COM_EnableXDNS
210527-07:05:44.109167 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.109251 [mod=T2, lvl=ERROR] [tid=10812] Unable to get Device.DeviceInfo.X_RDKCENTRAL-
COM_EnableXDNS
210527-07:05:44.109331 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.109412 [mod=T2, lvl=DEBUG] [tid=10812] Telemetry data source not found. Type = <message_bus>.
Content string = Device.DeviceInfo.X_RDKCENTRAL-COM_EnableXDNS
210527-07:05:44.109494 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.109573 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.109653 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.109734 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.SSID.
5.Enable
210527-07:05:44.111634 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath =
/com/cisco/spvtg/ccsp/wifi
210527-07:05:44.111768 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.111856 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.
SSID.5.Enable, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and path /com/cisco/spvtg/ccsp
/wifi
210527-07:05:44.113744 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.113845 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.SSID.5.Enable = false
210527-07:05:44.113932 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.114013 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.114093 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.114173 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.114255 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.114334 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.114415 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.114508 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_COMCAST_COM_xfinitywifiEnable
210527-07:05:44.116339 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.116455 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.116542 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST_COM_xfinitywifiEnable, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and
path /com/cisco/spvtg/ccsp/pam
210527-07:05:44.118521 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.118629 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.X_COMCAST_COM_xfinitywifiEnable = false
210527-07:05:44.118717 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.118798 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.118879 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.118976 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.119057 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.119137 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.119217 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.119298 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.Radio.
1.Status
210527-07:05:44.121226 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath =
/com/cisco/spvtg/ccsp/wifi
210527-07:05:44.121345 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.121432 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.
Radio.1.Status, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and path /com/cisco/spvtg/ccsp
/wifi
210527-07:05:44.151756 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.151905 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.Radio.1.Status = Up
210527-07:05:44.152058 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.152141 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.152223 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.152404 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.152491 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.152572 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.152652 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.152733 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.Radio.
```

2.Status

```
210527-07:05:44.154799 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath =
/com/cisco/spvtg/ccsp/wifi
210527-07:05:44.154916 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.155005 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.
Radio.2.Status, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and path /com/cisco/spvtg/ccsp
/wifi
210527-07:05:44.185642 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.185792 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.Radio.2.Status = Up
210527-07:05:44.185882 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.185963 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.186044 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.186227 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.186316 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.186397 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.186478 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.186560 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
HardwareVersion
210527-07:05:44.188560 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.188691 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.188780 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.HardwareVersion, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco
/spvtg/ccsp/pam
210527-07:05:44.202859 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.203016 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.HardwareVersion = a020d3
210527-07:05:44.203107 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.203189 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.203371 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.203458 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.203541 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.203622 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.203716 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.203799 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
FirstUseDate
210527-07:05:44.205906 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.206019 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.206107 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.FirstUseDate, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco
/spvtg/ccsp/pam
210527-07:05:44.208435 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.208558 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.FirstUseDate = 2013-11-22T00:00:00
210527-07:05:44.208648 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.208729 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.208966 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.209058 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.209142 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.209222 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.209302 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.209384 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.Radio.
2.AutoChannelEnable
210527-07:05:44.211659 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath =
/com/cisco/spvtg/ccsp/wifi
210527-07:05:44.211792 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.211881 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.
Radio.2.AutoChannelEnable, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and path /com/cisco
/spvtg/ccsp/wifi
210527-07:05:44.213861 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.213985 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.Radio.2.AutoChannelEnable = false
210527-07:05:44.214074 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.214157 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.214238 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.214319 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.214402 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.214482 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.214744 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.214830 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.Radio.
2.Stats.X_COMCAST-COM_NoiseFloor
210527-07:05:44.216751 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath =
/com/cisco/spvtg/ccsp/wifi
```



```

210527-07:05:44.216870 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.217069 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.
Radio.2.Stats.X_COMCAST-COM_NoiseFloor, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and
path /com/cisco/spvtg/ccsp/wifi
210527-07:05:44.671877 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.672030 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.Radio.2.Stats.X_COMCAST-COM_NoiseFloor = -99
210527-07:05:44.672120 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.672222 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.672304 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.672387 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.672468 [mod=T2, lvl=DEBUG] [tid=10812] processTr181Objects --out
210527-07:05:44.672548 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:44.672632 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list UPTIME_split : 934
210527-07:05:44.672744 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list CMMAC_split : B8:27:EB:1B:56:
4C
210527-07:05:44.672829 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list xwifi2g_split : false
210527-07:05:44.672913 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list xwifienable_split : false
210527-07:05:44.672996 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list 2G_Radio_Status_split : Up
210527-07:05:44.673079 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list 5G_Radio_Status_split : Up
210527-07:05:44.673164 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list HWREV_split : a020d3
210527-07:05:44.673247 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list FT_split : 2013-11-22T00:00:00
210527-07:05:44.673330 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list WIFI_ACS_2_split : false
210527-07:05:44.673413 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list WIFI_NF_2_split : -99
210527-07:05:44.673492 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:44.673720 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:44.673816 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:44.673898 [mod=T2, lvl=DEBUG] [tid=10812] processTr181Objects ++in
210527-07:05:44.673980 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.674059 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.674139 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.674220 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.Radio.
1.Stats.X_COMCAST-COM_NoiseFloor
210527-07:05:44.676175 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath =
/com/cisco/spvtg/ccsp/wifi
210527-07:05:44.676293 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.676382 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.
Radio.1.Stats.X_COMCAST-COM_NoiseFloor, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and
path /com/cisco/spvtg/ccsp/wifi
210527-07:05:44.958291 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.958483 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.Radio.1.Stats.X_COMCAST-COM_NoiseFloor = -99
210527-07:05:44.958575 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.958657 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.958738 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.958819 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.958901 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.958980 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.959060 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.959141 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
HardwareVersion
210527-07:05:44.961528 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.961673 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.961781 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.HardwareVersion, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco
/spvtg/ccsp/pam
210527-07:05:44.975552 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.975723 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.HardwareVersion = a020d3
210527-07:05:44.975814 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.975896 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.975977 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.976058 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.976139 [mod=T2, lvl=DEBUG] [tid=10812] processTr181Objects --out
210527-07:05:44.976218 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:44.976301 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list WIFI_NF_1_split : -99
210527-07:05:44.976395 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list HWREV_split : a020d3
210527-07:05:44.976476 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:44.976566 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:44.976658 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:44.976763 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:44.976847 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 0 for <message_bus> to logSeekMap
210527-07:05:44.976930 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out

```

```

210527-07:05:44.977010 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:44.977090 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file ArmConsolelog.txt.0
210527-07:05:44.977183 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file ArmConsolelog.txt.0
210527-07:05:44.977263 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:44.977394 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:44.984781 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:44.984899 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:44.985082 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:44.985173 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:44.985296 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:44.985379 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:44.985462 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 38348 for ArmConsolelog.txt.0 to
logSeekMap
210527-07:05:44.985548 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:44.985629 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:44.985709 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file BootTime.log
210527-07:05:44.985793 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file BootTime.log
210527-07:05:44.985883 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:44.985964 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:44.986359 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:44.986446 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:44.986530 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list bootuptime_wifi_split : 63
210527-07:05:44.986613 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list bootuptime_Ethernet_split : 57
210527-07:05:44.986697 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list btime_moca_split : 28
210527-07:05:44.986779 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list bootuptime_SNMPV2Ready_split :
=31
210527-07:05:44.986867 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list btime_laninit_split : 39
210527-07:05:44.986951 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list btime_waninit_split : 38
210527-07:05:44.987054 [mod=T2, lvl=DEBUG] [tid=10812] Adding OCCURENCE to result list SYS_INFO_Factory_reset :
1
210527-07:05:44.987135 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:44.987338 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:44.987446 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:44.987527 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:44.987609 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 497 for BootTime.log to logSeekMap
210527-07:05:44.987692 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:44.987772 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:44.987851 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file Consolelog.txt.0
210527-07:05:44.987934 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file Consolelog.txt.0
210527-07:05:44.988013 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:44.988092 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:45.064220 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:45.064383 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:45.064474 [mod=T2, lvl=DEBUG] [tid=10812] Adding OCCURENCE to result list SYS_INFO_CaptivePortal :
3
210527-07:05:45.064560 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list btime_wcpcnter_split : 77
210527-07:05:45.064648 [mod=T2, lvl=DEBUG] [tid=10812] Adding OCCURENCE to result list
SYS_SH_RDKB_FIREWALL_RESTART : 1
210527-07:05:45.064735 [mod=T2, lvl=DEBUG] [tid=10812] Adding OCCURENCE to result list
RF_INFO_RDKB_FIREWALL_RESTART : 17
210527-07:05:45.064816 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:45.064926 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:45.065017 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:45.065099 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:45.065180 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 441769 for Consolelog.txt.0 to
logSeekMap
210527-07:05:45.065327 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:45.065410 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:45.065491 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file LM.txt.0
210527-07:05:45.065573 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file LM.txt.0
210527-07:05:45.065666 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:45.065745 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:45.067941 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:45.068029 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:45.068111 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:45.068195 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:45.068285 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in

```



```
210527-07:05:45.068366 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:45.068465 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 42121 for LM.txt.0 to logSeekMap
210527-07:05:45.068551 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:45.068632 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:45.068711 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file PAMlog.txt.0
210527-07:05:45.068794 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file PAMlog.txt.0
210527-07:05:45.068874 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:45.068953 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:45.078693 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:45.078796 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:45.078887 [mod=T2, lvl=DEBUG] [tid=10812] Adding OCCURENCE to result list PAM : 299
210527-07:05:45.078968 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:45.079066 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:45.079165 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:45.079247 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:45.079328 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 207823 for PAMlog.txt.0 to
logSeekMap
210527-07:05:45.079413 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:45.079494 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:45.079574 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file PARODUSlog.txt.0
210527-07:05:45.079657 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file PARODUSlog.txt.0
210527-07:05:45.079749 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:45.079830 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:45.080317 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes ++in
210527-07:05:45.080436 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.080522 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.080662 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes --out
210527-07:05:45.080885 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes ++in
210527-07:05:45.080967 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.081050 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.081144 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes --out
210527-07:05:45.081363 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes ++in
210527-07:05:45.081445 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.081527 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.081610 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes --out
210527-07:05:45.081839 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes ++in
210527-07:05:45.081921 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.082004 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.082086 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes --out
210527-07:05:45.082355 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes ++in
210527-07:05:45.082437 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.082530 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.082613 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes --out
210527-07:05:45.082822 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes ++in
210527-07:05:45.082902 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.082985 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.083066 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes --out
210527-07:05:45.083297 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes ++in
210527-07:05:45.083379 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.083462 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.083544 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes --out
210527-07:05:45.083761 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes ++in
210527-07:05:45.083842 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.083942 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.084025 [mod=T2, lvl=DEBUG] [tid=10812] handlerRDKErrCodes --out
210527-07:05:45.084181 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:45.084264 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:45.084343 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:45.084427 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:45.084510 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:45.084590 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:45.084683 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 18859 for PARODUSlog.txt.0 to
logSeekMap
210527-07:05:45.084768 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:45.084850 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:45.084929 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file WEBPAllog.txt.0
210527-07:05:45.085018 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file WEBPAllog.txt.0
210527-07:05:45.085099 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
```

```
210527-07:05:45.085178 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:45.085778 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:45.085864 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:45.085944 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:45.086026 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:45.086116 [mod=T2, lvl=DEBUG] [tid=10812] Updating logseek after processPattern for WEBPalog.txt.0
210527-07:05:45.086196 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:45.086277 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 8586 for WEBPalog.txt.0 to
logSeekMap
210527-07:05:45.086362 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:45.086456 [mod=T2, lvl=DEBUG] [tid=10812] addToJson ++in
210527-07:05:45.086553 [mod=T2, lvl=DEBUG] [tid=10812] addToSearchResult ++in
210527-07:05:45.086633 [mod=T2, lvl=DEBUG] [tid=10812] addToSearchResult --out
210527-07:05:45.086712 [mod=T2, lvl=DEBUG] [tid=10812] addToJson --out
210527-07:05:45.086805 [mod=T2, lvl=DEBUG] [tid=10812] parseMarkerList --out
210527-07:05:45.086885 [mod=T2, lvl=DEBUG] [tid=10812] getDCAResultsInVector --out
210527-07:05:45.086964 [mod=T2, lvl=DEBUG] [tid=10812] getGrepResults --out
210527-07:05:45.087045 [mod=T2, lvl=INFO] [tid=10812] Grep complete for 41 markers
210527-07:05:45.087143 [mod=T2, lvl=DEBUG] [tid=10812] encodeGrepResultInJSON ++in
210527-07:05:45.087293 [mod=T2, lvl=DEBUG] [tid=10812] encodeGrepResultInJSON --Out
210527-07:05:45.087418 [mod=T2, lvl=DEBUG] [tid=10812] encodeEventMarkersInJSON ++in
210527-07:05:45.087516 [mod=T2, lvl=DEBUG] [tid=10812] Marker value for :
bootuptime_ClientConnectComplete_split is 158
210527-07:05:45.087612 [mod=T2, lvl=DEBUG] [tid=10812] Marker value for : WIFI_INFO_clientdisconnect is 3
210527-07:05:45.087741 [mod=T2, lvl=DEBUG] [tid=10812] Marker value for : WIFI_ERROR_PSM_GetRecordFail is 4
210527-07:05:45.087829 [mod=T2, lvl=DEBUG] [tid=10812] Marker value for : WIFI_INFO_CosaWifiinit is 1
210527-07:05:45.087915 [mod=T2, lvl=DEBUG] [tid=10812] encodeEventMarkersInJSON --Out
210527-07:05:45.088004 [mod=T2, lvl=DEBUG] [tid=10812] prepareJSONReport ++in
210527-07:05:45.088175 [mod=T2, lvl=DEBUG] [tid=10812] prepareJSONReport --Out
210527-07:05:45.088369 [mod=T2, lvl=INFO] [tid=10812] cJSON Report = {"searchResult":[{"T2":"1.0"}, {"Profile":
RDKB}], {"Time":"2021-05-27 07:05:43"}, {"mac":"b8:27:eb:1b:56:4c"}, {"erouterIpv4":"192.168.0.3"},
{"erouterIpv6":""}, {"PartnerId":"RDKM"}, {"Version":"rdkb-generic-broadband-image_TDK_rdk-next_20210526115302"},
{"AccountId":""}, {"LT_split":"2021-05-27 07:05:44"}, {"UPTIME_split":"934"}, {"CMMAC_split":"B8:27:EB:1B:56:4C"},
{"xwifi2g_split":"false"}, {"xwifienable_split":"false"}, {"2G_Radio_Status_split":"210527-07:05:45.088502
[mod=T2, lvl=INFO] [tid=10812] Report Size = 1170
210527-07:05:45.088623 [mod=T2, lvl=DEBUG] [tid=10812] sendReportOverHTTP ++in
210527-07:05:45.088726 [mod=T2, lvl=DEBUG] [tid=10812] setHeader ++in
210527-07:05:45.088809 [mod=T2, lvl=DEBUG] [tid=10812] setHeader DEST URL http://35.161.239.220/xconf
/telemetry_upload.php
210527-07:05:45.091974 [mod=T2, lvl=DEBUG] [tid=10812] setHeader --out
210527-07:05:45.570388 [mod=T2, lvl=INFO] [tid=10812] Report Sent Successfully over HTTP : 200
210527-07:05:45.571061 [mod=T2, lvl=DEBUG] [tid=10812] sendReportOverHTTP --ou.txt.0", "pollingFrequency":"0"},
{"header":"SYS_INFO_ip_address_recovered", "content":"sysevent_set_wr: ipv4_wan_ipaddr", "type":"Consolelog.txt.
0", "pollingFrequency":"0"}, {"header":"RF_INFO_RDKB_FIREWALL_RESTART", "content":"Triggering
RDKB_FIREWALL_RESTART", "type":"Consolelog.txt.0", "pollingFrequency":"0"}, {"header":"SYS_INFO_Factory_reset", "
content":"Reroot@RaspberryPi-Gateway:/rdklogs/logs# cat telemetry2_0.txt.0
210527-06:50:44.224195 [mod=T2, lvl=INFO] [tid=2480] Initializing Telemetry 2.0 Component
210527-06:50:44.226510 [mod=T2, lvl=DEBUG] [tid=2480] initTelemetry ++in
210527-06:50:44.226645 [mod=T2, lvl=DEBUG] [tid=2480] initReportProfiles ++in
210527-06:50:44.226775 [mod=T2, lvl=DEBUG] [tid=2480] initScheduler ++in
210527-06:50:44.226867 [mod=T2, lvl=DEBUG] [tid=2480] initScheduler --out
210527-06:50:44.226956 [mod=T2, lvl=DEBUG] [tid=2480] initT2MarkerComponentMap ++in
210527-06:50:44.227054 [mod=T2, lvl=DEBUG] [tid=2480] initT2MarkerComponentMap --out
210527-06:50:44.227137 [mod=T2, lvl=DEBUG] [tid=2480] T2ER_Init ++in
210527-06:50:44.227253 [mod=T2, lvl=DEBUG] [tid=2480] isRbusEnabled ++in
210527-06:50:44.227507 [mod=T2, lvl=DEBUG] [tid=2480] RBUS mode active status = false
210527-06:50:44.227592 [mod=T2, lvl=DEBUG] [tid=2480] isRbusEnabled --out
210527-06:50:44.227673 [mod=T2, lvl=DEBUG] [tid=2480] Register event call back function T2ER_PushDataWithDelim
210527-06:50:44.227764 [mod=T2, lvl=DEBUG] [tid=2480] registerForTelemetryEvents ++in
210527-06:50:44.227870 [mod=T2, lvl=DEBUG] [tid=2480] busInit ++in
210527-06:50:44.227974 [mod=T2, lvl=DEBUG] [tid=2480] isRbusEnabled ++in
210527-06:50:44.228084 [mod=T2, lvl=DEBUG] [tid=2480] RBUS mode active status = false
210527-06:50:44.228167 [mod=T2, lvl=DEBUG] [tid=2480] isRbusEnabled --out
210527-06:50:44.228246 [mod=T2, lvl=DEBUG] [tid=2480] busInit --out
210527-06:50:44.228335 [mod=T2, lvl=DEBUG] [tid=2480] registerCcspT2EventListener ++in
210527-06:50:44.228417 [mod=T2, lvl=DEBUG] [tid=2480] CCSPInterface_Init ++in
210527-06:50:44.242998 [mod=T2, lvl=DEBUG] [tid=2480] CCSPInterface_Init --out
210527-06:50:44.245132 [mod=T2, lvl=INFO] [tid=2480] Registration with CCSP Bus successful, waiting for
Telemetry Events from components...
210527-06:50:44.245330 [mod=T2, lvl=DEBUG] [tid=2480] registerCcspT2EventListener --out
210527-06:50:44.245440 [mod=T2, lvl=DEBUG] [tid=2480] registerForTelemetryEvents --out
```

```
210527-06:50:44.356471 [mod=T2, lvl=DEBUG] [tid=2480] T2ER_Init --out
210527-06:50:44.356699 [mod=T2, lvl=DEBUG] [tid=2480] ProfileXConf_init ++in
210527-06:50:44.356829 [mod=T2, lvl=DEBUG] [tid=2480] fetchLocalConfigs ++in
210527-06:50:44.357081 [mod=T2, lvl=DEBUG] [tid=2480] Config file : /nvram/.t2persistentfolder/DCMresponse.txt
210527-06:50:44.357228 [mod=T2, lvl=INFO] [tid=2480] Filename : DCMresponse.txt Size : 11126
210527-06:50:44.357468 [mod=T2, lvl=DEBUG] [tid=2480] Config data size = 11126
210527-06:50:44.358279 [mod=T2, lvl=DEBUG] [tid=2480] Config data = {"urn:settings:GroupName":"RDKB-RPI-TEST",
urn:settings:CheckOnReboot":true,"urn:settings:CheckSchedule:cron":"2 2 * * *", "urn:settings:CheckSchedule:
DurationMinutes":0, "urn:settings:LogUploadSettings:Message":null, "urn:settings:LogUploadSettings:Name":"RDKB-
RPI-TEST", "urn:settings:LogUploadSettings:NumberOfDays":0, "urn:settings:LogUploadSettings:
UploadRepositoryName":"RDKB-RPI-TEST", "urn:settings:LogUploadSettings:UploadRepository:URL":"h210527-06:50:
44.358694 [mod=T2, lvl=INFO] [tid=2480] Returning 1 local configurations
210527-06:50:44.358823 [mod=T2, lvl=DEBUG] [tid=2480] fetchLocalConfigs --out
210527-06:50:44.358916 [mod=T2, lvl=DEBUG] [tid=2480] Processing config with name : DCMresponse.txt
210527-06:50:44.359020 [mod=T2, lvl=DEBUG] [tid=2480] Config Size = 11126
210527-06:50:44.359138 [mod=T2, lvl=DEBUG] [tid=2480] processConfigurationXConf ++in
210527-06:50:44.359872 [mod=T2, lvl=DEBUG] [tid=2480] config data = {"urn:settings:GroupName":"RDKB-RPI-TEST",
urn:settings:CheckOnReboot":true,"urn:settings:CheckSchedule:cron":"2 2 * * *", "urn:settings:CheckSchedule:
DurationMinutes":0, "urn:settings:LogUploadSettings:Message":null, "urn:settings:LogUploadSettings:Name":"RDKB-
RPI-TEST", "urn:settings:LogUploadSettings:NumberOfDays":0, "urn:settings:LogUploadSettings:
UploadRepositoryName":"RDKB-RPI-TEST", "urn:settings:LogUploadSettings:UploadRepository:URL":"h210527-06:50:
44.361926 [mod=T2, lvl=DEBUG] [tid=2480] profile name = RDKB-RPI-TEST
210527-06:50:44.362060 [mod=T2, lvl=DEBUG] [tid=2480] upload url = http://35.161.239.220/xconf/telemetry_upload.
php
210527-06:50:44.362203 [mod=T2, lvl=DEBUG] [tid=2480] schedule = 2
210527-06:50:44.362285 [mod=T2, lvl=DEBUG] [tid=2480] marker count = 84
210527-06:50:44.362391 [mod=T2, lvl=INFO] [tid=2480] Received profile name : RDKB-RPI-TEST with interval of :
900 secs and upload url : http://35.161.239.220/xconf/telemetry_upload.php
210527-06:50:44.363169 [mod=T2, lvl=INFO] [tid=2480] Number of tr181params/markers successfully added in
profile = 84
210527-06:50:44.363740 [mod=T2, lvl=DEBUG] [tid=2480] processConfigurationXConf --out
210527-06:50:44.363835 [mod=T2, lvl=DEBUG] [tid=2480] ProfileXConf_set ++in
210527-06:50:44.363992 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364088 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364197 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364294 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364389 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364502 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364602 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364703 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364804 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.364905 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365010 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365116 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365224 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365360 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365473 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365586 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365701 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.365820 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366031 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366159 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366291 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366421 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366554 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366692 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.366893 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.367043 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.367246 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.367474 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.367680 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.367811 [mod=T2, lvl=DEBUG] [tid=2480] Found a matching T2Marker
210527-06:50:44.367905 [mod=T2, lvl=DEBUG] [tid=2480] RDKB-RPI-TEST already present in eventlist of
Total_online_clients_split . Ignore updates
210527-06:50:44.368117 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.368339 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.368577 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.368812 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.368996 [mod=T2, lvl=DEBUG] [tid=2480] updateComponentList --out
210527-06:50:44.369127 [mod=T2, lvl=DEBUG] [tid=2480] registerProfileWithScheduler ++in : profile - RDKB-RPI-
TEST
```

```
210527-06:50:44.369281 [mod=T2, lvl=INFO] [tid=2480] Starting TimeoutThread for profile : RDKB-RPI-TEST
210527-06:50:44.369610 [mod=T2, lvl=DEBUG] [tid=2480] registerProfileWithScheduler --out
210527-06:50:44.369716 [mod=T2, lvl=INFO] [tid=2480] Successfully set profile : RDKB-RPI-TEST
210527-06:50:44.369828 [mod=T2, lvl=DEBUG] [tid=2480] ProfileXConf_set --out
210527-06:50:44.369935 [mod=T2, lvl=DEBUG] [tid=2504] TimeoutThread ++in
210527-06:50:44.370145 [mod=T2, lvl=INFO] [tid=2504] Waiting for 900 sec for next TIMEOUT for profile - RDKB-RPI-TEST
210527-06:50:44.369943 [mod=T2, lvl=INFO] [tid=2480] Successfully set new profile: RDKB-RPI-TEST
210527-06:50:44.384757 [mod=T2, lvl=DEBUG] [tid=2480] ProfileXConf_init --out
210527-06:50:44.384917 [mod=T2, lvl=DEBUG] [tid=2480] getParameterValue ++in
210527-06:50:44.385043 [mod=T2, lvl=DEBUG] [tid=2480] getCCSPParamVal ++in
210527-06:50:44.385178 [mod=T2, lvl=DEBUG] [tid=2480] ccspGetParameterValues ++in
210527-06:50:44.385275 [mod=T2, lvl=DEBUG] [tid=2480] findDestComponent ++in for paramName : Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.Version
210527-06:50:44.393891 [mod=T2, lvl=DEBUG] [tid=2480] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath = /com/cisco/spvtg/ccsp/pam
210527-06:50:44.394110 [mod=T2, lvl=DEBUG] [tid=2480] findDestComponent --out
210527-06:50:44.394244 [mod=T2, lvl=DEBUG] [tid=2480] Calling CcspBaseIf_getParameterValues for : Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.Version, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-06:50:44.397406 [mod=T2, lvl=DEBUG] [tid=2480] ccspGetParameterValues --out
210527-06:50:44.397582 [mod=T2, lvl=DEBUG] [tid=2480] Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.Version = 2
210527-06:50:44.397708 [mod=T2, lvl=DEBUG] [tid=2480] getCCSPParamVal --out
210527-06:50:44.397794 [mod=T2, lvl=DEBUG] [tid=2480] getParameterValue --out
210527-06:50:44.397927 [mod=T2, lvl=DEBUG] [tid=2480] ProfileXConf is set
210527-06:50:44.398020 [mod=T2, lvl=DEBUG] [tid=2480] isRbusEnabled ++in
210527-06:50:44.398161 [mod=T2, lvl=DEBUG] [tid=2480] RBUS mode active status = false
210527-06:50:44.398258 [mod=T2, lvl=DEBUG] [tid=2480] isRbusEnabled --out
210527-06:50:44.398368 [mod=T2, lvl=DEBUG] [tid=2480] T2ER_StartDispatchThread ++in
210527-06:50:44.398693 [mod=T2, lvl=DEBUG] [tid=2480] T2ER_StartDispatchThread --out
210527-06:50:44.398800 [mod=T2, lvl=DEBUG] [tid=2512] T2ER_EventDispatchThread ++in
210527-06:50:44.398931 [mod=T2, lvl=DEBUG] [tid=2512] Checking for events in event queue , event count = 0
210527-06:50:44.399016 [mod=T2, lvl=DEBUG] [tid=2512] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:44.398806 [mod=T2, lvl=DEBUG] [tid=2480] initReportProfiles --out
210527-06:50:44.400249 [mod=T2, lvl=INFO] [tid=2480] Init ReportProfiles Successful
210527-06:50:44.400369 [mod=T2, lvl=DEBUG] [tid=2480] initXConfClient ++in
210527-06:50:44.400490 [mod=T2, lvl=DEBUG] [tid=2480] startXConfClient ++in
210527-06:50:44.400962 [mod=T2, lvl=DEBUG] [tid=2480] startXConfClient --out
210527-06:50:44.401059 [mod=T2, lvl=DEBUG] [tid=2513] getUpdatedConfigurationThread ++in
210527-06:50:44.401179 [mod=T2, lvl=DEBUG] [tid=2513] getRemoteConfigURL ++in
210527-06:50:44.401336 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.401462 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.401580 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.401725 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.ConfigURL
210527-06:50:44.401078 [mod=T2, lvl=DEBUG] [tid=2480] initXConfClient --out
210527-06:50:44.402751 [mod=T2, lvl=INFO] [tid=2480] Init Xconf Client Success
210527-06:50:44.403713 [mod=T2, lvl=DEBUG] [tid=2480] initTelemetry --out
210527-06:50:44.403814 [mod=T2, lvl=DEBUG] [tid=2480] initTelemetry --out
210527-06:50:44.403907 [mod=T2, lvl=INFO] [tid=2480] Telemetry 2.0 Component Init Success
210527-06:50:44.404502 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath = /com/cisco/spvtg/ccsp/pam
210527-06:50:44.404643 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.404751 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.ConfigURL, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-06:50:44.408259 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.408442 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.ConfigURL = https://xconf.rdkcentral.com:9092/loguploader/getT2Settings
210527-06:50:44.408533 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.408616 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.408719 [mod=T2, lvl=INFO] [tid=2513] Setting config URL base location to : https://xconf.rdkcentral.com:9092/loguploader/getT2Settings
210527-06:50:44.408803 [mod=T2, lvl=DEBUG] [tid=2513] getRemoteConfigURL --out
210527-06:50:44.408884 [mod=T2, lvl=DEBUG] [tid=2513] fetchRemoteConfiguration ++in
210527-06:50:44.408968 [mod=T2, lvl=DEBUG] [tid=2513] appendRequestParams ++in
210527-06:50:44.409073 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.409180 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.409284 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.409375 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
```

X_COMCAST-COM_WAN_MAC

```
210527-06:50:44.412200 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.412414 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.412521 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST-COM_WAN_MAC, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com
/cisco/spvtg/ccsp/pam
210527-06:50:44.417216 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.417385 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.X_COMCAST-COM_WAN_MAC = b8:27:eb:1b:56:
4c
210527-06:50:44.417476 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.417558 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.417688 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.417773 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.417854 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.417937 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
SoftwareVersion
210527-06:50:44.422401 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.422576 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.422698 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.SoftwareVersion, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco
/spvtg/ccsp/pam
210527-06:50:44.446401 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.446590 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.SoftwareVersion = rdkb-generic-
broadband-image_TDK_rdk-next_20210526115302
210527-06:50:44.446709 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.446793 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.446880 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.446977 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.447059 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.447146 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
ModelName
210527-06:50:44.450205 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.450402 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.450495 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.ModelName, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg
/ccsp/pam
210527-06:50:44.482267 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.482567 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.ModelName = RPI
210527-06:50:44.482709 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.482795 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.482913 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.483015 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.483101 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.483202 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENTRAL-COM_Syndication.PartnerId
210527-06:50:44.491006 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.491186 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.491275 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_RDKCENTRAL-COM_Syndication.PartnerId, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.
pam and path /com/cisco/spvtg/ccsp/pam
210527-06:50:44.493930 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.494096 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.X_RDKCENTRAL-COM_Syndication.PartnerId
= RDKM
210527-06:50:44.494189 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.494280 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.494410 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.494521 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.494639 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.494742 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENTRAL-COM_RFC.Feature.AccountInfo.AccountID
210527-06:50:44.499092 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-06:50:44.499265 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.499373 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AccountInfo.AccountID, paramCount : 1 Destination name : eRT.com.cisco.
spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-06:50:44.502496 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
```

```
210527-06:50:44.502698 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AccountInfo.AccountID =
210527-06:50:44.502818 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.502938 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.503045 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue ++in
210527-06:50:44.503143 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal ++in
210527-06:50:44.503249 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues ++in
210527-06:50:44.503368 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent ++in for paramName : Device.DeviceInfo.X_COMCAST-COM_CM_MAC
210527-06:50:44.510118 [mod=T2, lvl=DEBUG] [tid=2513] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath = /com/cisco/spvtg/ccsp/pam
210527-06:50:44.510291 [mod=T2, lvl=DEBUG] [tid=2513] findDestComponent --out
210527-06:50:44.510395 [mod=T2, lvl=DEBUG] [tid=2513] Calling CcspBaseIf_getParameterValues for : Device.DeviceInfo.X_COMCAST-COM_CM_MAC, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-06:50:44.555974 [mod=T2, lvl=DEBUG] [tid=2513] ccspGetParameterValues --out
210527-06:50:44.556186 [mod=T2, lvl=DEBUG] [tid=2513] Device.DeviceInfo.X_COMCAST-COM_CM_MAC = B8:27:EB:1B:56:4C
210527-06:50:44.556290 [mod=T2, lvl=DEBUG] [tid=2513] getCCSPParamVal --out
210527-06:50:44.556379 [mod=T2, lvl=DEBUG] [tid=2513] getParameterValue --out
210527-06:50:44.556661 [mod=T2, lvl=DEBUG] [tid=2513] appendRequestParams:216 Final http get URL if size 782 is :
https://xconf.rdkcentral.com:9092/loguploader/getT2Settings?estbMacAddress=b8:27:eb:1b:56:4c&firmwareVersion=rdkb-generic-broadband-image_TDK_rdk-next_20210526115302&model=RPI&partnerId=RDKM&accountId=&ecmMacAddress=B8:27:EB:1B:56:4C&env=dev&controllerId=2504&channelMapId=2345&vodId=15660&version=2
210527-06:50:44.556829 [mod=T2, lvl=DEBUG] [tid=2513] appendRequestParams --out
210527-06:50:44.556912 [mod=T2, lvl=DEBUG] [tid=2513] doHttpGet ++in
210527-06:50:44.556995 [mod=T2, lvl=INFO] [tid=2513] doHttpGet with url https://xconf.rdkcentral.com:9092/loguploader/getT2Settings?estbMacAddress=b8:27:eb:1b:56:4c&firmwareVersion=rdkb-generic-broadband-image_TDK_rdk-next_20210526115302&model=RPI&partnerId=RDKM&accountId=&ecmMacAddress=B8:27:EB:1B:56:4C&env=dev&controllerId=2504&channelMapId=2345&vodId=15660&version=2
210527-06:50:44.722913 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:44.723097 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : SYS_SH_RDKB_FIREWALL_RESTART<#=#>1
210527-06:50:44.723246 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : SYS_SH_RDKB_FIREWALL_RESTART
eventValue : 1 to t2event queue
210527-06:50:44.723418 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:50:44.723604 [mod=T2, lvl=DEBUG] [tid=2512] Received signal from T2ER_Push
210527-06:50:44.723692 [mod=T2, lvl=DEBUG] [tid=2512] Checking for events in event queue , event count = 1
210527-06:50:44.723824 [mod=T2, lvl=WARN] [tid=2512] No Matching Profiles for event with MarkerName : SYS_SH_RDKB_FIREWALL_RESTART Value : 1 - Ignoring
210527-06:50:44.723917 [mod=T2, lvl=DEBUG] [tid=2512] Checking for events in event queue , event count = 0
210527-06:50:44.724027 [mod=T2, lvl=DEBUG] [tid=2512] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:44.861693 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:44.861876 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : RF_ERROR_wan_restart<#=#>1
210527-06:50:44.861988 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : RF_ERROR_wan_restart eventValue : 1 to t2event queue
210527-06:50:44.862098 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:50:44.862271 [mod=T2, lvl=DEBUG] [tid=2512] Received signal from T2ER_Push
210527-06:50:44.862375 [mod=T2, lvl=DEBUG] [tid=2512] Checking for events in event queue , event count = 1
210527-06:50:44.862523 [mod=T2, lvl=WARN] [tid=2512] No Matching Profiles for event with MarkerName : RF_ERROR_wan_restart Value : 1 - Ignoring
210527-06:50:44.862617 [mod=T2, lvl=DEBUG] [tid=2512] Checking for events in event queue , event count = 0
210527-06:50:44.862713 [mod=T2, lvl=DEBUG] [tid=2512] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:45.733183 [mod=T2, lvl=INFO] [tid=2513] doHttpGet:320, T2:Telemetry XCONF communication success
210527-06:50:45.747311 [mod=T2, lvl=DEBUG] [tid=2513] doHttpGet --out
210527-06:50:45.747489 [mod=T2, lvl=DEBUG] [tid=2513] fetchRemoteConfiguration --out
210527-06:50:45.747576 [mod=T2, lvl=DEBUG] [tid=2513] Config received successfully from URL : https://xconf.rdkcentral.com:9092/loguploader/getT2Settings
210527-06:50:45.748496 [mod=T2, lvl=DEBUG] [tid=2513] Config received = {"urn:settings:GroupName":"RDKB-RPI-TEST", "urn:settings:CheckOnReboot":true, "urn:settings:CheckSchedule:cron":"2 2 * * *", "urn:settings:CheckSchedule:DurationMinutes":0, "urn:settings:LogUploadSettings:Message":null, "urn:settings:LogUploadSettings:Name":"RDKB-RPI-TEST", "urn:settings:LogUploadSettings:NumberOfDays":0, "urn:settings:LogUploadSettings:UploadRepositoryName":"RDKB-RPI-TEST", "urn:settings:LogUploadSettings:UploadRepository:URL210527-06:50:45.749017 [mod=T2, lvl=DEBUG] [tid=2513] processConfigurationXConf ++in
210527-06:50:45.749773 [mod=T2, lvl=DEBUG] [tid=2513] config data = {"urn:settings:GroupName":"RDKB-RPI-TEST", "urn:settings:CheckOnReboot":true, "urn:settings:CheckSchedule:cron":"2 2 * * *", "urn:settings:CheckSchedule:DurationMinutes":0, "urn:settings:LogUploadSettings:Message":null, "urn:settings:LogUploadSettings:Name":"RDKB-RPI-TEST", "urn:settings:LogUploadSettings:NumberOfDays":0, "urn:settings:LogUploadSettings:UploadRepositoryName":"RDKB-RPI-TEST", "urn:settings:LogUploadSettings:UploadRepository:URL":"h210527-06:50:45.752717 [mod=T2, lvl=DEBUG] [tid=2513] profile name = RDKB-RPI-TEST
210527-06:50:45.752899 [mod=T2, lvl=DEBUG] [tid=2513] upload url = http://35.161.239.220/xconf/telemetry_upload.
```


php

```
210527-06:50:45.752990 [mod=T2, lvl=DEBUG] [tid=2513] schedule = 2
210527-06:50:45.753074 [mod=T2, lvl=DEBUG] [tid=2513] marker count = 84
210527-06:50:45.753160 [mod=T2, lvl=INFO] [tid=2513] Received profile name : RDKB-RPI-TEST with interval of :
900 secs and upload url : http://35.161.239.220/xconf/telemetry_upload.php
210527-06:50:45.754081 [mod=T2, lvl=INFO] [tid=2513] Number of tr181params/markers successfully added in
profile = 84
210527-06:50:45.755185 [mod=T2, lvl=DEBUG] [tid=2513] processConfigurationXConf --out
210527-06:50:45.755354 [mod=T2, lvl=INFO] [tid=2513] Profile exists already, updating the config in file system
210527-06:50:45.755447 [mod=T2, lvl=DEBUG] [tid=2513] saveConfigToFile ++in
210527-06:50:45.757114 [mod=T2, lvl=DEBUG] [tid=2513] saveConfigToFile --out
210527-06:50:45.757265 [mod=T2, lvl=DEBUG] [tid=2513] Disable and Delete old profile RDKB-RPI-TEST
210527-06:50:45.757368 [mod=T2, lvl=DEBUG] [tid=2513] ReportProfiles_deleteProfileXConf ++in
210527-06:50:45.757452 [mod=T2, lvl=DEBUG] [tid=2513] ProfileXConf is set
210527-06:50:45.757540 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_StopDispatchThread ++in
210527-06:50:45.757688 [mod=T2, lvl=DEBUG] [tid=2512] Received signal from T2ER_Push
210527-06:50:45.757791 [mod=T2, lvl=DEBUG] [tid=2512] T2ER_EventDispatchThread --out
210527-06:50:45.757976 [mod=T2, lvl=DEBUG] [tid=2513] flushCacheFromFile ++in
210527-06:50:45.758350 [mod=T2, lvl=DEBUG] [tid=2513] T2: Sending cache event : btime_moca_split<##=>30
210527-06:50:45.758457 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim ++in
210527-06:50:45.758542 [mod=T2, lvl=DEBUG] [tid=2513] Received eventInfo : btime_moca_split<##=>30
210527-06:50:45.758630 [mod=T2, lvl=DEBUG] [tid=2513] Adding eventName : btime_moca_split eventValue : 30 to
t2event queue
210527-06:50:45.758732 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim --out
210527-06:50:45.758816 [mod=T2, lvl=DEBUG] [tid=2513] T2: Sending cache event :
bootuptime_SNMPV2Ready_split<##=>32
210527-06:50:45.758897 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim ++in
210527-06:50:45.758978 [mod=T2, lvl=DEBUG] [tid=2513] Received eventInfo : bootuptime_SNMPV2Ready_split<##=>32
210527-06:50:45.759063 [mod=T2, lvl=DEBUG] [tid=2513] Adding eventName : bootuptime_SNMPV2Ready_split
eventValue : 32 to t2event queue
210527-06:50:45.759145 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim --out
210527-06:50:45.759445 [mod=T2, lvl=DEBUG] [tid=2513] T2: Sending cache event :
SYS_SH_RDKB_FIREWALL_RESTART<##=>1
210527-06:50:45.759559 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim ++in
210527-06:50:45.759643 [mod=T2, lvl=DEBUG] [tid=2513] Received eventInfo : SYS_SH_RDKB_FIREWALL_RESTART<##=>1
210527-06:50:45.759730 [mod=T2, lvl=DEBUG] [tid=2513] Adding eventName : SYS_SH_RDKB_FIREWALL_RESTART
eventValue : 1 to t2event queue
210527-06:50:45.760031 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_PushDataWithDelim --out
210527-06:50:45.760494 [mod=T2, lvl=DEBUG] [tid=2513] fopen failed for /tmp/t2_atom_caching_file
210527-06:50:45.761094 [mod=T2, lvl=DEBUG] [tid=2513] flushCacheFromFile --out
210527-06:50:45.761251 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_StopDispatchThread --out
210527-06:50:45.761352 [mod=T2, lvl=DEBUG] [tid=2513] clearT2MarkerComponentMap ++in
210527-06:50:45.761868 [mod=T2, lvl=DEBUG] [tid=2513] clearT2MarkerComponentMap --out
210527-06:50:45.761989 [mod=T2, lvl=DEBUG] [tid=2513] updateMarkerComponentMap ++in
210527-06:50:45.762073 [mod=T2, lvl=DEBUG] [tid=2513] updateMarkerComponentMap --out
210527-06:50:45.762166 [mod=T2, lvl=DEBUG] [tid=2513] ProfileXConf_delete ++in
210527-06:50:45.762266 [mod=T2, lvl=INFO] [tid=2513] removing profile : RDKB-RPI-TEST
210527-06:50:45.762502 [mod=T2, lvl=DEBUG] [tid=2513] ProfileXConf_delete --out
210527-06:50:45.762590 [mod=T2, lvl=DEBUG] [tid=2513] Set new profile : RDKB-RPI-TEST
210527-06:50:45.762951 [mod=T2, lvl=DEBUG] [tid=2513] ReportProfiles_setProfileXConf ++in
210527-06:50:45.763076 [mod=T2, lvl=DEBUG] [tid=2513] ProfileXConf_set ++in
210527-06:50:45.767168 [mod=T2, lvl=ERROR] [tid=2513] Component name list is not initialized . Re-initializing
210527-06:50:45.767419 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.767541 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.767657 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.767775 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.767874 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.767974 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.768073 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.768330 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.768487 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.768621 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.768740 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.768855 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.768971 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.769137 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.769253 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.770929 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.771069 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.771207 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.771441 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
```

```

210527-06:50:45.771762 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.771942 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.772083 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.772241 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.772411 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.772644 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.772956 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.773137 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.773294 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.773469 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.773610 [mod=T2, lvl=DEBUG] [tid=2513] Found a matching T2Marker
210527-06:50:45.773695 [mod=T2, lvl=DEBUG] [tid=2513] RDKB-RPI-TEST already present in eventlist of
Total_online_clients_split . Ignore updates
210527-06:50:45.774410 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.774631 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.774800 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.774987 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.775328 [mod=T2, lvl=DEBUG] [tid=2513] updateComponentList --out
210527-06:50:45.775434 [mod=T2, lvl=DEBUG] [tid=2513] registerProfileWithScheduler ++in : profile - RDKB-RPI-
TEST
210527-06:50:45.775542 [mod=T2, lvl=INFO] [tid=2513] Scheduler already assigned for profile RDKB-RPI-TEST ,
exiting .
210527-06:50:45.775624 [mod=T2, lvl=DEBUG] [tid=2513] registerProfileWithScheduler --out
210527-06:50:45.775705 [mod=T2, lvl=INFO] [tid=2513] Successfully set profile : RDKB-RPI-TEST
210527-06:50:45.775785 [mod=T2, lvl=DEBUG] [tid=2513] ProfileXConf_set --out
210527-06:50:45.775865 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_StartDispatchThread ++in
210527-06:50:45.776072 [mod=T2, lvl=DEBUG] [tid=2513] T2ER_StartDispatchThread --out
210527-06:50:45.776116 [mod=T2, lvl=DEBUG] [tid=2806] T2ER_EventDispatchThread ++in
210527-06:50:45.776312 [mod=T2, lvl=DEBUG] [tid=2513] ReportProfiles_setProfileXConf --out
210527-06:50:45.776391 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 3
210527-06:50:45.776544 [mod=T2, lvl=INFO] [tid=2513] Successfully set new profile : RDKB-RPI-TEST
210527-06:50:45.776661 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
btime_moca_split Value : 30 - Ignoring
210527-06:50:45.776721 [mod=T2, lvl=DEBUG] [tid=2513] getUpdatedConfigurationThread --out
210527-06:50:45.776750 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 2
210527-06:50:45.776926 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
bootuptime_SNMPV2Ready_split Value : 32 - Ignoring
210527-06:50:45.777011 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:50:45.777148 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
SYS_SH_RDKB_FIREWALL_RESTART Value : 1 - Ignoring
210527-06:50:45.777233 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:50:45.777325 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:47.890478 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:47.890740 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : btime_waninit_split<#=#>38
210527-06:50:47.890878 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : btime_waninit_split eventValue : 38 to
t2event queue
210527-06:50:47.891062 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:50:47.891285 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:50:47.891387 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:50:47.891574 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
btime_waninit_split Value : 38 - Ignoring
210527-06:50:47.891681 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:50:47.891771 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:55.141136 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:55.141327 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : SYS_SH_RDKB_FIREWALL_RESTART<#=#>1
210527-06:50:55.141422 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : SYS_SH_RDKB_FIREWALL_RESTART
eventValue : 1 to t2event queue
210527-06:50:55.141527 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:50:55.141669 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:50:55.141755 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:50:55.141886 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
SYS_SH_RDKB_FIREWALL_RESTART Value : 1 - Ignoring
210527-06:50:55.141969 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:50:55.142048 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:55.903766 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:55.903975 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : btime_eth_split<#=#>46
210527-06:50:55.904092 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : btime_eth_split eventValue : 46 to
t2event queue
210527-06:50:55.904205 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:50:55.904385 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:50:55.904480 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1

```



```
210527-06:50:55.904616 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
btime_eth_split Value : 46 - Ignoring
210527-06:50:55.904721 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:50:55.904804 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:50:56.103099 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:50:56.103339 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : SYS_SH_RDKB_FIREWALL_RESTART<#=#>1
210527-06:50:56.103435 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : SYS_SH_RDKB_FIREWALL_RESTART
eventValue : 1 to t2event queue
210527-06:50:56.103565 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:50:56.103705 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:50:56.103791 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:50:56.103920 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
SYS_SH_RDKB_FIREWALL_RESTART Value : 1 - Ignoring
210527-06:50:56.104005 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:50:56.104084 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:04.031749 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:04.031940 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_ERROR_PSM_GetRecordFail<#=#>1
210527-06:51:04.032051 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_ERROR_PSM_GetRecordFail
eventValue : 1 to t2event queue
210527-06:51:04.032161 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:51:04.032301 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:04.032388 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:04.032542 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_ERROR_PSM_GetRecordFail value : 1
210527-06:51:04.032626 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:51:04.032718 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:51:04.032805 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:51:04.032890 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 1
210527-06:51:04.032970 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:51:04.033062 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:51:04.033147 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:04.033227 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:04.405652 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:04.405769 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_ERROR_PSM_GetRecordFail<#=#>1
210527-06:51:04.405862 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_ERROR_PSM_GetRecordFail
eventValue : 1 to t2event queue
210527-06:51:04.405966 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:51:04.406103 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:04.406190 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:04.406316 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_ERROR_PSM_GetRecordFail value : 1
210527-06:51:04.406412 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:51:04.406493 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:51:04.406574 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:51:04.406659 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 2
210527-06:51:04.406737 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:51:04.406817 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:51:04.406899 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:04.406980 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:05.996497 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:05.996640 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_ERROR_PSM_GetRecordFail<#=#>1
210527-06:51:05.996797 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_ERROR_PSM_GetRecordFail
eventValue : 1 to t2event queue
210527-06:51:05.996903 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:51:05.997036 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:05.997122 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:05.997251 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_ERROR_PSM_GetRecordFail value : 1
210527-06:51:05.997333 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:51:05.997414 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:51:05.997495 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:51:05.997581 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 3
210527-06:51:05.997661 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:51:05.997740 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:51:05.997836 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:05.997917 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:06.142735 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:06.142882 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_ERROR_PSM_GetRecordFail<#=#>1
210527-06:51:06.142977 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_ERROR_PSM_GetRecordFail
eventValue : 1 to t2event queue
210527-06:51:06.143088 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
```

```

210527-06:51:06.143230 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:06.143345 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:06.143495 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_ERROR_PSM_GetRecordFail value : 1
210527-06:51:06.143607 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:51:06.143709 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:51:06.143835 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:51:06.143935 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 4
210527-06:51:06.144020 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:51:06.144099 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:51:06.144186 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:06.144283 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:06.804651 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:06.804836 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_INFO_CosaWifiinit<#=#>1
210527-06:51:06.804949 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_INFO_CosaWifiinit eventValue : 1
to t2event queue
210527-06:51:06.805112 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:51:06.805274 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:06.805375 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:06.805501 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_INFO_CosaWifiinit value : 1
210527-06:51:06.805599 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:51:06.805682 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:51:06.805767 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:51:06.805852 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 1
210527-06:51:06.805931 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:51:06.806032 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:51:06.806116 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:06.806267 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:51:07.121048 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:51:07.121249 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : bootuptime_wifi_split<#=#>57
210527-06:51:07.121345 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : bootuptime_wifi_split eventValue : 57
to t2event queue
210527-06:51:07.121450 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:51:07.121591 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:51:07.121677 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:51:07.121806 [mod=T2, lvl=WARN] [tid=2806] No Matching Profiles for event with MarkerName :
bootuptime_wifi_split Value : 57 - Ignoring
210527-06:51:07.121891 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:51:07.121986 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:52:48.327283 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:52:48.327453 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo :
bootuptime_ClientConnectComplete_split<#=#>158
210527-06:52:48.327610 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : bootuptime_ClientConnectComplete_split
eventValue : 158 to t2event queue
210527-06:52:48.327782 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:52:48.327936 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:52:48.328048 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:52:48.328246 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
bootuptime_ClientConnectComplete_split value : 158
210527-06:52:48.328353 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:52:48.328443 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:52:48.328537 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:52:48.328622 [mod=T2, lvl=DEBUG] [tid=2806] New marker value saved : 158
210527-06:52:48.328702 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:52:48.328781 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:52:48.328865 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:52:48.328944 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:53:48.952569 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:53:48.952792 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_INFO_clientdisconnect<#=#>1
210527-06:53:48.952899 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_INFO_clientdisconnect eventValue
: 1 to t2event queue
210527-06:53:48.953031 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:53:48.953241 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:53:48.953353 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:53:48.953550 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_INFO_clientdisconnect value : 1
210527-06:53:48.953690 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:53:48.953822 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:53:48.953916 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:53:48.954000 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 1

```

```

210527-06:53:48.954080 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:53:48.954169 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:53:48.954299 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:53:48.954433 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:55:50.562218 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:55:50.562399 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_INFO_clientdisconnect<#=#>1
210527-06:55:50.562502 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_INFO_clientdisconnect eventValue
: 1 to t2event queue
210527-06:55:50.562605 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:55:50.562643 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:55:50.562893 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:55:50.563036 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_INFO_clientdisconnect value : 1
210527-06:55:50.563126 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:55:50.563214 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:55:50.563303 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:55:50.563401 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 2
210527-06:55:50.563481 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:55:50.563561 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:55:50.563644 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:55:50.563724 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-06:56:50.182976 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim ++in
210527-06:56:50.183138 [mod=T2, lvl=DEBUG] [tid=2486] Received eventInfo : WIFI_INFO_clientdisconnect<#=#>1
210527-06:56:50.183238 [mod=T2, lvl=DEBUG] [tid=2486] Adding eventName : WIFI_INFO_clientdisconnect eventValue
: 1 to t2event queue
210527-06:56:50.183342 [mod=T2, lvl=DEBUG] [tid=2486] T2ER_PushDataWithDelim --out
210527-06:56:50.183381 [mod=T2, lvl=DEBUG] [tid=2806] Received signal from T2ER_Push
210527-06:56:50.183497 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 1
210527-06:56:50.183632 [mod=T2, lvl=DEBUG] [tid=2806] Found matching profileIDs for event with markerName :
WIFI_INFO_clientdisconnect value : 1
210527-06:56:50.183716 [mod=T2, lvl=DEBUG] [tid=2806] Storing in profile : RDKB-RPI-TEST
210527-06:56:50.183797 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent ++in
210527-06:56:50.183880 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent ++in
210527-06:56:50.183984 [mod=T2, lvl=DEBUG] [tid=2806] Increment marker count to : 3
210527-06:56:50.184064 [mod=T2, lvl=DEBUG] [tid=2806] ProfileXConf_storeMarkerEvent --out
210527-06:56:50.184142 [mod=T2, lvl=DEBUG] [tid=2806] ReportProfiles_storeMarkerEvent --out
210527-06:56:50.184225 [mod=T2, lvl=DEBUG] [tid=2806] Checking for events in event queue , event count = 0
210527-06:56:50.184304 [mod=T2, lvl=DEBUG] [tid=2806] Event Queue size is 0, Waiting events from T2ER_Push
210527-07:05:44.000155 [mod=T2, lvl=INFO] [tid=2504] TIMEOUT for profile - RDKB-RPI-TEST
210527-07:05:44.000380 [mod=T2, lvl=INFO] [tid=2504] ReportProfiles_TimeoutCb ++in
210527-07:05:44.000479 [mod=T2, lvl=DEBUG] [tid=2504] ProfileXConf_notifyTimeout ++in
210527-07:05:44.000763 [mod=T2, lvl=DEBUG] [tid=2504] ProfileXConf_notifyTimeout --out
210527-07:05:44.000840 [mod=T2, lvl=INFO] [tid=10812] CollectAndReportXconf ++in profileName : RDKB-RPI-TEST
210527-07:05:44.000850 [mod=T2, lvl=INFO] [tid=2504] ReportProfiles_TimeoutCb --out
210527-07:05:44.001026 [mod=T2, lvl=INFO] [tid=2504] Waiting for 900 sec for next TIMEOUT for profile - RDKB-
RPI-TEST
210527-07:05:44.001185 [mod=T2, lvl=DEBUG] [tid=10812] getProfileParameterValues ++in
210527-07:05:44.001289 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPProfileParamValues ++in
210527-07:05:44.001381 [mod=T2, lvl=INFO] [tid=10812] TR-181 Param count : 7
210527-07:05:44.001469 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.001552 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_COMCAST-COM_WAN_MAC
210527-07:05:44.003602 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.003719 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.003805 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST-COM_WAN_MAC, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com
/cisco/spvtg/ccsp/pam
210527-07:05:44.005938 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.006072 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.006158 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_COMCAST-COM_WAN_IP
210527-07:05:44.007953 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.008067 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.008169 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST-COM_WAN_IP, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com
/cisco/spvtg/ccsp/pam
210527-07:05:44.010227 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.010346 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.010430 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.

```

X_COMCAST-COM_WAN_IPv6
210527-07:05:44.012460 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath = /com/cisco/spvtg/ccsp/pam
210527-07:05:44.012606 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.012693 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST-COM_WAN_IPv6, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-07:05:44.014713 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.014833 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.014920 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENRAL-COM_Syndication.PartnerId
210527-07:05:44.016763 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath = /com/cisco/spvtg/ccsp/pam
210527-07:05:44.016881 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.016969 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_RDKCENRAL-COM_Syndication.PartnerId, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-07:05:44.019001 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.019121 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.019207 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
SoftwareVersion
210527-07:05:44.021236 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath = /com/cisco/spvtg/ccsp/pam
210527-07:05:44.021362 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.021452 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.SoftwareVersion, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-07:05:44.035007 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.035167 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.035253 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENRAL-COM_RFC.Feature.AccountInfo.AccountID
210527-07:05:44.037183 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath = /com/cisco/spvtg/ccsp/pam
210527-07:05:44.037302 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.037454 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_RDKCENRAL-COM_RFC.Feature.AccountInfo.AccountID, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-07:05:44.039472 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.039596 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.039682 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.Time.
CurrentLocalTime
210527-07:05:44.041650 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath = /com/cisco/spvtg/ccsp/pam
210527-07:05:44.041776 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.041865 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.Time.
CurrentLocalTime, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-07:05:44.074549 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.074704 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPProfileParamValues --Out
210527-07:05:44.074789 [mod=T2, lvl=DEBUG] [tid=10812] getProfileParameterValues --Out
210527-07:05:44.074870 [mod=T2, lvl=INFO] [tid=10812] Fetch complete for TR-181 Object/Parameter Values for parameters
210527-07:05:44.074990 [mod=T2, lvl=DEBUG] [tid=10812] encodeParamResultInJSON ++in
210527-07:05:44.075080 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : mac valueCount = 1
210527-07:05:44.075193 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : erouterIpv4 valueCount = 1
210527-07:05:44.075282 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : erouterIpv6 valueCount = 1
210527-07:05:44.075369 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : PartnerId valueCount = 1
210527-07:05:44.075454 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : Version valueCount = 1
210527-07:05:44.075540 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : AccountId valueCount = 1
210527-07:05:44.075641 [mod=T2, lvl=DEBUG] [tid=10812] Parameter Name : LT_split valueCount = 1
210527-07:05:44.075725 [mod=T2, lvl=DEBUG] [tid=10812] encodeParamResultInJSON --Out
210527-07:05:44.075806 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.075905 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.075986 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076067 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.076146 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076228 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.076307 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076389 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.076468 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076550 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out

```

210527-07:05:44.076629 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076718 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.076797 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues ++in
210527-07:05:44.076881 [mod=T2, lvl=DEBUG] [tid=10812] freeProfileValues --Out
210527-07:05:44.076974 [mod=T2, lvl=DEBUG] [tid=10812] getGrepResults ++in
210527-07:05:44.077063 [mod=T2, lvl=DEBUG] [tid=10812] getDCAResultsInVector ++in
210527-07:05:44.077162 [mod=T2, lvl=DEBUG] [tid=10812] initProperties ++in
210527-07:05:44.077377 [mod=T2, lvl=DEBUG] [tid=10812] updateIncludeConfVal ++in
210527-07:05:44.077577 [mod=T2, lvl=DEBUG] [tid=10812] updateIncludeConfVal --out
210527-07:05:44.077682 [mod=T2, lvl=DEBUG] [tid=10812] initProperties --out
210527-07:05:44.077768 [mod=T2, lvl=DEBUG] [tid=10812] parseMarkerList ++in
210527-07:05:44.077854 [mod=T2, lvl=DEBUG] [tid=10812] vMarkerList for profile RDKB-RPI-TEST is of count = 41
210527-07:05:44.077940 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekMapForProfile ++in
210527-07:05:44.078073 [mod=T2, lvl=DEBUG] [tid=10812] Get profileseek map for RDKB-RPI-TEST
210527-07:05:44.078154 [mod=T2, lvl=DEBUG] [tid=10812] Profile seek map doesn't exist, creating one ...
210527-07:05:44.078240 [mod=T2, lvl=DEBUG] [tid=10812] profileSeekMap count 0
210527-07:05:44.078328 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekMapForProfile --out
210527-07:05:44.078409 [mod=T2, lvl=DEBUG] [tid=10812] logSeekMap is null, add logSeekMap for RDKB-RPI-TEST
210527-07:05:44.078495 [mod=T2, lvl=DEBUG] [tid=10812] addToProfileSeekMap ++in for profileName = RDKB-RPI-TEST
210527-07:05:44.078576 [mod=T2, lvl=DEBUG] [tid=10812] Adding GrepSeekProfile for profile RDKB-RPI-TEST in
profileSeekMap
210527-07:05:44.078667 [mod=T2, lvl=DEBUG] [tid=10812] addToProfileSeekMap --out
210527-07:05:44.079089 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:44.079178 [mod=T2, lvl=DEBUG] [tid=10812] processTrl81Objects ++in
210527-07:05:44.079269 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.079356 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.079436 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.079517 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
UpTime
210527-07:05:44.081727 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.081863 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.081951 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.UpTime, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp
/pam
210527-07:05:44.084014 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.084125 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.UpTime = 934
210527-07:05:44.084213 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.084294 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.084389 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.084492 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.084585 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.084666 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.084746 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.084828 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_COMCAST-COM_CM_MAC
210527-07:05:44.086695 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.086811 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.086899 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST-COM_CM_MAC, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com
/cisco/spvtg/ccsp/pam
210527-07:05:44.106190 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.106363 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.X_COMCAST-COM_CM_MAC = B8:27:EB:1B:56:
4C
210527-07:05:44.106454 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.106536 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.106618 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.106699 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.106781 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.106860 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.106941 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.107023 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_RDKCENTRAL-COM_EnableXDNS
210527-07:05:44.108916 [mod=T2, lvl=ERROR] [tid=10812] Failed to get component for Device.DeviceInfo.
X_RDKCENTRAL-COM_EnableXDNS ret: 204
210527-07:05:44.109025 [mod=T2, lvl=ERROR] [tid=10812] Unable to find supporting component for parameter :
Device.DeviceInfo.X_RDKCENTRAL-COM_EnableXDNS
210527-07:05:44.109167 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.109251 [mod=T2, lvl=ERROR] [tid=10812] Unable to get Device.DeviceInfo.X_RDKCENTRAL-
COM_EnableXDNS

```

```
210527-07:05:44.109331 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.109412 [mod=T2, lvl=DEBUG] [tid=10812] Telemetry data source not found. Type = <message_bus>.
Content string = Device.DeviceInfo.X_RDKCENTRAL-COM_EnableXDNS
210527-07:05:44.109494 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.109573 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.109653 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.109734 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.SSID.
5.Enable
210527-07:05:44.111634 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath =
/com/cisco/spvtg/ccsp/wifi
210527-07:05:44.111768 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.111856 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.
SSID.5.Enable, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and path /com/cisco/spvtg/ccsp
/wifi
210527-07:05:44.113744 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.113845 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.SSID.5.Enable = false
210527-07:05:44.113932 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.114013 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.114093 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.114173 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.114255 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.114334 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.114415 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.114508 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
X_COMCAST_COM_xfinitywifiEnable
210527-07:05:44.116339 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.116455 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.116542 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.X_COMCAST_COM_xfinitywifiEnable, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and
path /com/cisco/spvtg/ccsp/pam
210527-07:05:44.118521 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.118629 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.X_COMCAST_COM_xfinitywifiEnable = false
210527-07:05:44.118717 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.118798 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.118879 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.118976 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.119057 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.119137 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.119217 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.119298 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.Radio.
1.Status
210527-07:05:44.121226 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath =
/com/cisco/spvtg/ccsp/wifi
210527-07:05:44.121345 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.121432 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.
Radio.1.Status, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and path /com/cisco/spvtg/ccsp
/wifi
210527-07:05:44.151756 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.151905 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.Radio.1.Status = Up
210527-07:05:44.152058 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.152141 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.152223 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.152404 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.152491 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.152572 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.152652 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.152733 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.Radio.
2.Status
210527-07:05:44.154799 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath =
/com/cisco/spvtg/ccsp/wifi
210527-07:05:44.154916 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.155005 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.
Radio.2.Status, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and path /com/cisco/spvtg/ccsp
/wifi
210527-07:05:44.185642 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.185792 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.Radio.2.Status = Up
210527-07:05:44.185882 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.185963 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.186044 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.186227 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
```



```
210527-07:05:44.186316 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.186397 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.186478 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.186560 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
HardwareVersion
210527-07:05:44.188560 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.188691 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.188780 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.HardwareVersion, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco
/spvtg/ccsp/pam
210527-07:05:44.202859 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.203016 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.HardwareVersion = a020d3
210527-07:05:44.203107 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.203189 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.203371 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.203458 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.203541 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.203622 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.203716 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.203799 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.
FirstUseDate
210527-07:05:44.205906 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath =
/com/cisco/spvtg/ccsp/pam
210527-07:05:44.206019 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.206107 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.
DeviceInfo.FirstUseDate, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco
/spvtg/ccsp/pam
210527-07:05:44.208435 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.208558 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.FirstUseDate = 2013-11-22T00:00:00
210527-07:05:44.208648 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.208729 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.208966 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.209058 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.209142 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.209222 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.209302 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.209384 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.Radio.
2.AutoChannelEnable
210527-07:05:44.211659 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath =
/com/cisco/spvtg/ccsp/wifi
210527-07:05:44.211792 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.211881 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.
Radio.2.AutoChannelEnable, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and path /com/cisco
/spvtg/ccsp/wifi
210527-07:05:44.213861 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.213985 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.Radio.2.AutoChannelEnable = false
210527-07:05:44.214074 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.214157 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.214238 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.214319 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.214402 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.214482 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.214744 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.214830 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.Radio.
2.Stats.X_COMCAST-COM_NoiseFloor
210527-07:05:44.216751 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath =
/com/cisco/spvtg/ccsp/wifi
210527-07:05:44.216870 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.217069 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.
Radio.2.Stats.X_COMCAST-COM_NoiseFloor, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and
path /com/cisco/spvtg/ccsp/wifi
210527-07:05:44.671877 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.672030 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.Radio.2.Stats.X_COMCAST-COM_NoiseFloor = -99
210527-07:05:44.672120 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.672222 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.672304 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.672387 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.672468 [mod=T2, lvl=DEBUG] [tid=10812] processTr181Objects --out
210527-07:05:44.672548 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:44.672632 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list UPTIME_split : 934
```

```

210527-07:05:44.672744 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list CMMAC_split : B8:27:EB:1B:56:4C
210527-07:05:44.672829 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list xwifi2g_split : false
210527-07:05:44.672913 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list xwifienable_split : false
210527-07:05:44.672996 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list 2G_Radio_Status_split : Up
210527-07:05:44.673079 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list 5G_Radio_Status_split : Up
210527-07:05:44.673164 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list HWREV_split : a020d3
210527-07:05:44.673247 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list FT_split : 2013-11-22T00:00:00
210527-07:05:44.673330 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list WIFI_ACS_2_split : false
210527-07:05:44.673413 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list WIFI_NF_2_split : -99
210527-07:05:44.673492 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:44.673720 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:44.673816 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:44.673898 [mod=T2, lvl=DEBUG] [tid=10812] processTr181Objects ++in
210527-07:05:44.673980 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.674059 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.674139 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.674220 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.WiFi.Radio.1.Stats.X_COMCAST-COM_NoiseFloor
210527-07:05:44.676175 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.wifi destPath = /com/cisco/spvtg/ccsp/wifi
210527-07:05:44.676293 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.676382 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.WiFi.Radio.1.Stats.X_COMCAST-COM_NoiseFloor, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.wifi and path /com/cisco/spvtg/ccsp/wifi
210527-07:05:44.958291 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.958483 [mod=T2, lvl=DEBUG] [tid=10812] Device.WiFi.Radio.1.Stats.X_COMCAST-COM_NoiseFloor = -99
210527-07:05:44.958575 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.958657 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.958738 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.958819 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.958901 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue ++in
210527-07:05:44.958980 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal ++in
210527-07:05:44.959060 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues ++in
210527-07:05:44.959141 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent ++in for paramName : Device.DeviceInfo.HardwareVersion
210527-07:05:44.961528 [mod=T2, lvl=DEBUG] [tid=10812] destCompName = eRT.com.cisco.spvtg.ccsp.pam destPath = /com/cisco/spvtg/ccsp/pam
210527-07:05:44.961673 [mod=T2, lvl=DEBUG] [tid=10812] findDestComponent --out
210527-07:05:44.961781 [mod=T2, lvl=DEBUG] [tid=10812] Calling CcspBaseIf_getParameterValues for : Device.DeviceInfo.HardwareVersion, paramCount : 1 Destination name : eRT.com.cisco.spvtg.ccsp.pam and path /com/cisco/spvtg/ccsp/pam
210527-07:05:44.975552 [mod=T2, lvl=DEBUG] [tid=10812] ccspGetParameterValues --out
210527-07:05:44.975723 [mod=T2, lvl=DEBUG] [tid=10812] Device.DeviceInfo.HardwareVersion = a020d3
210527-07:05:44.975814 [mod=T2, lvl=DEBUG] [tid=10812] getCCSPParamVal --out
210527-07:05:44.975896 [mod=T2, lvl=DEBUG] [tid=10812] getParameterValue --out
210527-07:05:44.975977 [mod=T2, lvl=DEBUG] [tid=10812] appendData ++in
210527-07:05:44.976058 [mod=T2, lvl=DEBUG] [tid=10812] appendData --out
210527-07:05:44.976139 [mod=T2, lvl=DEBUG] [tid=10812] processTr181Objects --out
210527-07:05:44.976218 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:44.976301 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list WIFI_NF_1_split : -99
210527-07:05:44.976395 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list HWREV_split : a020d3
210527-07:05:44.976476 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:44.976566 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:44.976658 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:44.976763 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:44.976847 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 0 for <message_bus> to logSeekMap
210527-07:05:44.976930 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:44.977010 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:44.977090 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file ArmConsolelog.txt.0
210527-07:05:44.977183 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file ArmConsolelog.txt.0
210527-07:05:44.977263 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from getLogSeekValue
210527-07:05:44.977394 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:44.984781 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:44.984899 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:44.985082 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:44.985173 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:44.985296 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:44.985379 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:44.985462 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 38348 for ArmConsolelog.txt.0 to

```

```
logSeekMap
210527-07:05:44.985548 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:44.985629 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:44.985709 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file BootTime.log
210527-07:05:44.985793 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file BootTime.log
210527-07:05:44.985883 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:44.985964 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:44.986359 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:44.986446 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:44.986530 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list bootuptime_wifi_split : 63
210527-07:05:44.986613 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list bootuptime_Ethernet_split : 57
210527-07:05:44.986697 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list btime_moca_split : 28
210527-07:05:44.986779 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list bootuptime_SNMPV2Ready_split :
=31
210527-07:05:44.986867 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list btime_laninit_split : 39
210527-07:05:44.986951 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list btime_waninit_split : 38
210527-07:05:44.987054 [mod=T2, lvl=DEBUG] [tid=10812] Adding OCCURENCE to result list SYS_INFO_Factory_reset :
1
210527-07:05:44.987135 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:44.987338 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:44.987446 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:44.987527 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:44.987609 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 497 for BootTime.log to logSeekMap
210527-07:05:44.987692 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:44.987772 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:44.987851 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file Consolelog.txt.0
210527-07:05:44.987934 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file Consolelog.txt.0
210527-07:05:44.988013 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:44.988092 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:45.064220 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:45.064383 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:45.064474 [mod=T2, lvl=DEBUG] [tid=10812] Adding OCCURENCE to result list SYS_INFO_CaptivePortal :
3
210527-07:05:45.064560 [mod=T2, lvl=DEBUG] [tid=10812] Adding STR to result list btime_wcpenter_split : 77
210527-07:05:45.064648 [mod=T2, lvl=DEBUG] [tid=10812] Adding OCCURENCE to result list
SYS_SH_RDKB_FIREWALL_RESTART : 1
210527-07:05:45.064735 [mod=T2, lvl=DEBUG] [tid=10812] Adding OCCURENCE to result list
RF_INFO_RDKB_FIREWALL_RESTART : 17
210527-07:05:45.064816 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:45.064926 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:45.065017 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:45.065099 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:45.065180 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 441769 for Consolelog.txt.0 to
logSeekMap
210527-07:05:45.065327 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:45.065410 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:45.065491 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file LM.txt.0
210527-07:05:45.065573 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file LM.txt.0
210527-07:05:45.065666 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:45.065745 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:45.067941 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:45.068029 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:45.068111 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:45.068195 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:45.068285 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:45.068366 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:45.068465 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 42121 for LM.txt.0 to logSeekMap
210527-07:05:45.068551 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:45.068632 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:45.068711 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file PAMLog.txt.0
210527-07:05:45.068794 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file PAMlog.txt.0
210527-07:05:45.068874 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:45.068953 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:45.078693 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:45.078796 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:45.078887 [mod=T2, lvl=DEBUG] [tid=10812] Adding OCCURENCE to result list PAM : 299
210527-07:05:45.078968 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
```


```
210527-07:05:45.079066 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:45.079165 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:45.079247 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:45.079328 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 207823 for PAMlog.txt.0 to
logSeekMap
210527-07:05:45.079413 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:45.079494 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:45.079574 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file PARODUSlog.txt.0
210527-07:05:45.079657 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file PARODUSlog.txt.0
210527-07:05:45.079749 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:45.079830 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:45.080317 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes ++in
210527-07:05:45.080436 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.080522 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.080662 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes --out
210527-07:05:45.080885 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes ++in
210527-07:05:45.080967 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.081050 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.081144 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes --out
210527-07:05:45.081363 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes ++in
210527-07:05:45.081445 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.081527 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.081610 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes --out
210527-07:05:45.081839 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes ++in
210527-07:05:45.081921 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.082004 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.082086 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes --out
210527-07:05:45.082355 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes ++in
210527-07:05:45.082437 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.082530 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.082613 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes --out
210527-07:05:45.082822 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes ++in
210527-07:05:45.082902 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.082985 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.083066 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes --out
210527-07:05:45.083297 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes ++in
210527-07:05:45.083379 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.083462 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.083544 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes --out
210527-07:05:45.083761 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes ++in
210527-07:05:45.083842 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode ++in
210527-07:05:45.083942 [mod=T2, lvl=DEBUG] [tid=10812] getErrorCode --out
210527-07:05:45.084025 [mod=T2, lvl=DEBUG] [tid=10812] handleRDKErrCodes --out
210527-07:05:45.084181 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:45.084264 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:45.084343 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:45.084427 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:45.084510 [mod=T2, lvl=DEBUG] [tid=10812] processPattern ++in
210527-07:05:45.084590 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:45.084683 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 18859 for PARODUSlog.txt.0 to
logSeekMap
210527-07:05:45.084768 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:45.084850 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern ++in
210527-07:05:45.084929 [mod=T2, lvl=DEBUG] [tid=10812] Read from log file WEBPAllog.txt.0
210527-07:05:45.085018 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue ++in for file WEBPAllog.txt.0
210527-07:05:45.085099 [mod=T2, lvl=DEBUG] [tid=10812] data is null .. Setting seek value to 0 from
getLogSeekValue
210527-07:05:45.085178 [mod=T2, lvl=DEBUG] [tid=10812] getLogSeekValue --out
210527-07:05:45.085778 [mod=T2, lvl=DEBUG] [tid=10812] processCountPattern --out
210527-07:05:45.085864 [mod=T2, lvl=DEBUG] [tid=10812] addToVector ++in
210527-07:05:45.085944 [mod=T2, lvl=DEBUG] [tid=10812] addToVector --out
210527-07:05:45.086026 [mod=T2, lvl=DEBUG] [tid=10812] processPattern --out
210527-07:05:45.086116 [mod=T2, lvl=DEBUG] [tid=10812] Updating logseek after processPattern for WEBPAllog.txt.0
210527-07:05:45.086196 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek ++in
210527-07:05:45.086277 [mod=T2, lvl=DEBUG] [tid=10812] Adding seekvalue of 8586 for WEBPAllog.txt.0 to
logSeekMap
210527-07:05:45.086362 [mod=T2, lvl=DEBUG] [tid=10812] updateLogSeek --out
210527-07:05:45.086456 [mod=T2, lvl=DEBUG] [tid=10812] addToJson ++in
210527-07:05:45.086553 [mod=T2, lvl=DEBUG] [tid=10812] addToSearchResult ++in
210527-07:05:45.086633 [mod=T2, lvl=DEBUG] [tid=10812] addToSearchResult --out
```

```

210527-07:05:45.086712 [mod=T2, lvl=DEBUG] [tid=10812] addToJson --out
210527-07:05:45.086805 [mod=T2, lvl=DEBUG] [tid=10812] parseMarkerList --out
210527-07:05:45.086885 [mod=T2, lvl=DEBUG] [tid=10812] getDCAResultsInVector --out
210527-07:05:45.086964 [mod=T2, lvl=DEBUG] [tid=10812] getGrepResults --out
210527-07:05:45.087045 [mod=T2, lvl=INFO] [tid=10812] Grep complete for 41 markers
210527-07:05:45.087143 [mod=T2, lvl=DEBUG] [tid=10812] encodeGrepResultInJSON ++in
210527-07:05:45.087293 [mod=T2, lvl=DEBUG] [tid=10812] encodeGrepResultInJSON --Out
210527-07:05:45.087418 [mod=T2, lvl=DEBUG] [tid=10812] encodeEventMarkersInJSON ++in
210527-07:05:45.087516 [mod=T2, lvl=DEBUG] [tid=10812] Marker value for :
bootuptime_ClientConnectComplete_split is 158
210527-07:05:45.087612 [mod=T2, lvl=DEBUG] [tid=10812] Marker value for : WIFI_INFO_clientdisconnect is 3
210527-07:05:45.087741 [mod=T2, lvl=DEBUG] [tid=10812] Marker value for : WIFI_ERROR_PSM_GetRecordFail is 4
210527-07:05:45.087829 [mod=T2, lvl=DEBUG] [tid=10812] Marker value for : WIFI_INFO_CosaWifiinit is 1
210527-07:05:45.087915 [mod=T2, lvl=DEBUG] [tid=10812] encodeEventMarkersInJSON --Out
210527-07:05:45.088004 [mod=T2, lvl=DEBUG] [tid=10812] prepareJSONReport ++in
210527-07:05:45.088175 [mod=T2, lvl=DEBUG] [tid=10812] prepareJSONReport --Out
210527-07:05:45.088369 [mod=T2, lvl=INFO] [tid=10812] cJSON Report = {"searchResult":[{"T2":"1.0"}, {"Profile":"RDKB"}, {"Time":"2021-05-27 07:05:43"}, {"mac":"b8:27:eb:1b:56:4c"}, {"erouterIpv4":"192.168.0.3"}, {"erouterIpv6":""}, {"PartnerId":"RDKM"}, {"Version":"rdkb-generic-broadband-image_TDK_rdk-next_20210526115302"}, {"AccountId":""}, {"LT_split":"2021-05-27 07:05:44"}, {"UPTIME_split":"934"}, {"CMMAC_split":"B8:27:EB:1B:56:4C"}, {"xwifi2g_split":"false"}, {"xwifienable_split":"false"}, {"2G_Radio_Status_split":"210527-07:05:45.088502"}, {"mod=T2, lvl=INFO] [tid=10812] Report Size = 1170
210527-07:05:45.088623 [mod=T2, lvl=DEBUG] [tid=10812] sendReportOverHTTP ++in
210527-07:05:45.088726 [mod=T2, lvl=DEBUG] [tid=10812] setHeader ++in
210527-07:05:45.088809 [mod=T2, lvl=DEBUG] [tid=10812] setHeader DEST URL http://35.161.239.220/xconf/telemetry_upload.php
210527-07:05:45.091974 [mod=T2, lvl=DEBUG] [tid=10812] setHeader --out
210527-07:05:45.570388 [mod=T2, lvl=INFO] [tid=10812] Report Sent Successfully over HTTP : 200
210527-07:05:45.571061 [mod=T2, lvl=DEBUG] [tid=10812] sendReportOverHTTP --out

```

\$ cat /rdklogs/logs/dcmscript.log



Log upload onto HTTPS Server



Verify that Json file displayed in HTTPS server <https://xconf.rdkcentral.com/xconf/upload/display.php?mode=telemetry>


JSON file upload

- open the uploaded json file and ensure the parameters

https://xconf.rdkcentral.com/xconf/upload/b827eb1b564c_TELE_05-26-2021-07-45AM.json

https://xconf.rdkcentral.com/xconf/upload/e45f010d7886_TELE_01-03-2023-09-35AM.json





Telemetry Version : 2.0.1 - Multiprofile

Pre- requisites for enabling Telemetry2_0

Telemetry Version : 2.0.1 (by default telemetry version as 1)


Below are the steps for enabling telemetry 2.0.1 in rpi,

1. dmcli eRT setv Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.Enable bool true
2. dmcli eRT setv Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.Version string 2.0.1
3. dmcli eRT setv Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.ConfigURL string <https://xconf.rdkcentral.com:19092/loguploader/getT2Settings>
4. touch /nvram/enable_t2_debug
5. reboot the device
6. pidof "telemetry2_0" - check the running status of telemetry2
7. T2 DataModel will be loaded


After board boot up, disable log rotation by using the command:

```
$ systemctl disable rdkbLogMonitor
```

Below screenshot for enabling the T2 process of version 2.0.1 in rpi,



After reboot the device,



Telemetry 2.0 Report Profiles

Telemetry 2 brings multi-profile support to RDK telemetry. This allows for multiple report profiles to be active on a device at one time, each with their own data and reporting configuration. Specific profiles may be targeted to data for specific purposes, such as WiFi Happiness, Deviceinfo information or many other areas. Telemetry 2.0 Report Profiles are supported along with legacy Telemetry 1.0/1.1 configurations, so that T2.0 Report Profiles can be actively added and removed without disturbing legacy telemetry.

In addition, Telemetry 2 adds support for RDK Components to send their telemetry data to the T2 component for reporting. This allows for moving away from the CPU-intensive process of searching through log files for telemetry strings.

Telemetry 2.0 allows for an RDK device to be updated with a set of T2 profiles at any time.

T2 DataModel

There are 2 parameters under T2 report profiles,


S.NO	DM	Description
1	Device.X_RDKCENTRAL-COM_T2.ReportProfiles	Value must be JSON configuration blob in string
2	Device.X_RDKCENTRAL-COM_T2.ReportProfilesMsgPack	Value must be JSON configuration blob in base 64 encoded msgpack format

DMCLI SET Command for T2 Report Profile


dmcli command

```
dmcli eRT setv Device.X_RDKCENTRAL-COM_T2.ReportProfiles string '{"profiles":[{"name":"RDKB_CCSPWiFi_Profile","hash":"hash1","value":{"Name":"RDKB_CCSPWiFi_Profile","Description":"Report to check WiFi Parameters","Version":"1","Protocol":"HTTP","EncodingType":"JSON","ReportingInterval":180,"TimeReference":"0001-01-01T00:00:00Z","ActivationTimeOut":1800,"Parameter":[{"type":"dataModel","reference":"Profile.Name"}, {"type":"dataModel","reference":"Profile.Version"}, {"type":"dataModel","reference":"Device.WiFi.Radio.1.Stats.X_COMCAST-COM_NoiseFloor"}, {"type":"event","eventName":"2GclientMac_split","component":"wifihealth","use":"absolute"}, {"type":"event","eventName":"5GclientMac_split","component":"wifihealth","use":"absolute"}, {"type":"event","name":"wifiradio WIFI_COUNT","eventName":"WIFI_MAC_1_TOTAL_COUNT:0","component":"wifiradio","use":"count","reportEmpty":false}, {"type":"dataModel","name":"UPTIME","reference":"Device.DeviceInfo.Uptime","use":"absolute"}]}, {"HTTP":{"URL":"https://xconf.rdkcentral.com/xconf/telemetry_upload.php","Compression":"None","Method":"POST","RequestURIParameter":[{"Name":"deviceId","Reference":"Device.DeviceInfo.X_COMCAST-COM_CM_MAC"}, {"Name":"reportName","Reference":"Profile.Name"}]}}, {"JSONEncoding":{"ReportFormat":"NameValuePair","ReportTimestamp":"None"}}]}, {"name":"RDKB_SelfHeal_Profile","hash":"hash2","value":{"Name":"RDKB_SelfHeal_Profile","Description":"Report to check SelfHeal Parameters","Version":"2","Protocol":"HTTP","EncodingType":"JSON","ReportingInterval":180,"TimeReference":"0001-01-01T00:00:00Z","ActivationTimeOut":1800,"Parameter":[{"type":"dataModel","reference":"Profile.Name"}, {"type":"dataModel","reference":"Profile.Version"}, {"type":"dataModel","name":"UPTIME","reference":"Device.DeviceInfo.Uptime","use":"absolute"}, {"type":"event","eventName":"SYS_ERROR_AdvSecurity_NotRunning","component":"SELF_HEAL","use":"absolute"}, {"type":"event","eventName":"SYS_SH_lighttpdCrash","component":"test-and-diagnostic","use":"count","reportEmpty":false}, {"type":"dataModel","name":"WAN_SSH_STATUS","reference":"Device.DeviceInfo.X_RDKCENTRAL-COM_Syndication.WANsideSSH.Enable","use":"absolute"}]}, {"HTTP":{"URL":"https://xconf.rdkcentral.com/xconf/telemetry_upload.php","Compression":"None","Method":"POST","RequestURIParameter":[{"Name":"deviceId","Reference":"Device.DeviceInfo.X_COMCAST-COM_CM_MAC"}, {"Name":"reportName","Reference":"Profile.Name"}]}}, {"JSONEncoding":{"ReportFormat":"NameValuePair","ReportTimestamp":"None"}}]}'
```


Dmcli Get



RPI Device Logs




cJSON Report




Log Upload

https://xconf.rdkcentral.com/xconf/upload/_TELE_05-27-2021-11-27AM.json



https://xconf.rdkcentral.com/xconf/upload/_TELE_05-27-2021-11-26AM.json



Telemetry 2.0 ProfileMsgPack

The Telemetry 2.0 Component must support T2 report profiles in msgPack format.

1. Parameter Name: Device.X_RDKCENTRAL-COM_T2.ReportProfilesMsgPack
 - a. Type: base64 (base64-encoded msgPack)
 - Access: Read and Write access
 - Persistence: Not persisted
 - Factory default: Null string
 - Usage: When set, T2.0 will use the value of this parameter to configure its T2 active report profiles, as defined in Configuring Active T2.0 Profiles, below.
2. The T2.0 Parameter Device.X_RDKCENTRAL-COM_T2.ReportProfiles that accepts T2 report profiles in JSON format will be deprecated. While deprecated, if report profiles are received via both ReportProfiles and ReportProfilesMsgPack, the last configuration received will be respected.
3. The T2.0 Component must continue to concurrently support the legacy telemetry report profile received from XConf DCM response in JSON format.

Sample JSON Profile

JSON

```
{
  "profiles": [
    {
      "name": "RDKB_WIFI_DM_PROFILE",
      "hash": "hash1",
      "value": {
        "Description": "Report to DeviceInfo",
        "Version": "2",
        "Protocol": "HTTP",
        "EncodingType": "JSON",
        "ReportingInterval": 60,
        "TimeReference": "0001-01-01T00:00:00Z",
        "ActivationTimeout": 120,
        "Parameter": [
          {
            "type": "dataModel", "reference": "Profile.Name",
            "type": "dataModel", "reference": "Profile.Version",
            {
              "type": "dataModel", "name": "CmMac",
              "reference": "Device.DeviceInfo.X_COMCAST-COM_CM_MAC"
            }
          ]
        }
      }
    }
  ]
}
```




```

    }, {
      "type": "dataModel", "name": "2G-SSID",
      "reference": "Device.WiFi.SSID.1.SSID"
    }, {
      "type": "dataModel", "name": "5G-SSID",
      "reference": "Device.WiFi.SSID.2.SSID"
    }, {
      "type": "dataModel", "name": "2G-Name",
      "reference": "Device.WiFi.Radio.1.Name"
    }, {
      "type": "dataModel", "name": "5G-Name",
      "reference": "Device.WiFi.Radio.2.Name"
    }, {
      "type": "dataModel", "name": "2G-PWD",
      "reference": "Device.WiFi.AccessPoint.1.Security.KeyPassphrase"
    }, {
      "type": "dataModel", "name": "5G-PWD",
      "reference": "Device.WiFi.AccessPoint.2.Security.KeyPassphrase"
    }, {
      "type": "dataModel", "name": "2G-Mode",
      "reference": "Device.WiFi.AccessPoint.1.Security.ModeEnabled"
    }, {
      "type": "dataModel", "name": "5G-Mode",
      "reference": "Device.WiFi.AccessPoint.2.Security.ModeEnabled"
    }, {
      "type": "dataModel", "name": "MemStatUsed",
      "reference": "Device.DeviceInfo.MemoryStatus.Used"
    }, {
      "type": "dataModel", "name": "FrMemThreshld",
      "reference": "Device.DeviceInfo.MemoryStatus.X_RDKCENTRAL-COM_FreeMemThreshold"
    }, {
      "type": "dataModel", "name": "CpuUsage",
      "reference": "Device.DeviceInfo.ProcessStatus.CPUUsage"
    }, {
      "type": "dataModel", "name": "Uptime",
      "reference": "Device.DeviceInfo.UpTime"
    }
  ],
  "HTTP": {
    "URL": "https://xconf.rdkcentral.com/xconf/telemetry_upload.php",
    "Compression": "None",
    "Method": "POST",
    "RequestURIParameter": [
      {
        "Name": "deviceId",
        "Reference": "Device.DeviceInfo.X_COMCAST-COM_CM_MAC"
      },
      {
        "Name": "reportName",
        "Reference": "Profile.Name"
      }
    ]
  },
  "JSONEncoding": {
    "ReportFormat": "NameValuePair",
    "ReportTimestamp": "None"
  }
}


```

Convert JSON into base-64


T2 Report Profiles can still be authored in JSON. They will just need to be sent through a msgPack and base64 process, like at <https://toolslick.com/conversion/data/json-to-messagepack#>, to get msgPacked data that has been base64 encoded. Choose Output Type "Base 64".



cJSON Report




og upload



Telemetry 2.0 Report Profiles Generation in xconf,

1. In xconf > Telemetry > Telemetry 2.0 Profiles > create



2. In xconf > Telemetry > Telemetry 2.0 Rules > create

https://xconf.rdkcentral.com:9092/loguploader/getTelemetryProfiles?estbMacAddress=b8:27:eb:1b:56:4c&firmwareVersion=rdkb-generic-broadband-image_rdk-next_20210329055811&model=&partnerId=RDKM&accountId=&ecmMacAddress=B8:27:EB:1B:56:4C&env=dev&controllerId=2504&channelMapId=2345&vodId=15660&version=2

Report Profiles Validation through WebPA Commands

```
root@RaspberryPi-Gateway:~# ps aux | grep webpa
5046 root    0:00 /usr/bin/parodus --hw-model=RPI --hw-serial-number=00000000a31b564c --hw-manufacturer=Raspberry --hw-last-reboot-
reason=unknown --fw-name=rdkb-generic-broadband-image_TDK_rdk-next_20210526115302 --boot-time=1622141278 --hw-mac=B8:27:EB:
1B:56:4C --webpa-ping-time=180 --webpa-interface-used=erouter0 --webpa-url=http://54.148.37.189:8080 --webpa-backoff-max=9 --parodus-
local-url=tcp://127.0.0.1:6666 --partner-id=comcast --ssl-cert-path=/etc/ssl/certs/ca-certificates.crt --force-ipv4
5070 root    0:00 /usr/bin/webpa &
5632 root    0:00 grep webpa
root@RaspberryPi-Gateway:~#
```

ReportProfilesMsgPack

Webpa Set

[illegible]

[illegible][illegible]

```
keerthana@keerthana-INVALID: ~ x keerthana@keerthana-INVALID: ~
root@RaspberryPi-Gateway:/nvram/.t2reportprofiles# ls
profiles.msgpack
root@RaspberryPi-Gateway:/nvram/.t2reportprofiles# cat /rdklogs/logs/telemetry2_0.txt.0 | grep RDKB_DM
root@RaspberryPi-Gateway:/nvram/.t2reportprofiles# cat /rdklogs/logs/telemetry2_0.txt.0 | grep RDKB_WIFI
210527-18:48:32.026801 [mod=T2, lvl=DEBUG] [tid=2201] name_str: RDKB_WIFI_DM_SSID_PROFILE
210527-18:48:32.040976 [mod=T2, lvl=DEBUG] [tid=2201] registerProfileWithScheduler ++in : profile - RDKB_WIFI_DM_SSID_PROFILE
210527-18:48:32.041083 [mod=T2, lvl=INFO] [tid=2201] Starting TimeoutThread for profile : RDKB_WIFI_DM_SSID_PROFILE
210527-18:48:32.041904 [mod=T2, lvl=INFO] [tid=2201] Successfully enabled profile : RDKB_WIFI_DM_SSID_PROFILE
210527-18:48:32.042149 [mod=T2, lvl=INFO] [tid=2217] Waiting for 60 sec for next TIMEOUT for profile - RDKB_WIFI_DM_SSID_PROFILE
210527-18:48:34.415589 [mod=T2, lvl=DEBUG] [tid=2397] Updating component map for profile RDKB_WIFI_DM_SSID_PROFILE
210527-18:49:32.000151 [mod=T2, lvl=INFO] [tid=2217] TIMEOUT for profile - RDKB_WIFI_DM_SSID_PROFILE
210527-18:49:32.000796 [mod=T2, lvl=INFO] [tid=2217] NotifyTimeout: profile RDKB_WIFI_DM_SSID_PROFILE is in Enabled state
210527-18:49:32.001057 [mod=T2, lvl=INFO] [tid=5852] CollectAndReport ++in profileName : RDKB_WIFI_DM_SSID_PROFILE
210527-18:49:32.001198 [mod=T2, lvl=INFO] [tid=2217] Waiting for 60 sec for next TIMEOUT for profile - RDKB_WIFI_DM_SSID_PROFILE
210527-18:49:33.575470 [mod=T2, lvl=INFO] [tid=5852] Elapsed Time for : RDKB_WIFI_DM_SSID_PROFILE = 1.574270587 (Sec.NanoSec)
210527-18:50:32.000162 [mod=T2, lvl=INFO] [tid=2217] TIMEOUT for profile - RDKB_WIFI_DM_SSID_PROFILE
210527-18:50:32.000774 [mod=T2, lvl=INFO] [tid=2217] NotifyTimeout: profile RDKB_WIFI_DM_SSID_PROFILE is in Enabled state
210527-18:50:32.001142 [mod=T2, lvl=INFO] [tid=7904] CollectAndReport ++in profileName : RDKB_WIFI_DM_SSID_PROFILE
210527-18:50:32.001372 [mod=T2, lvl=INFO] [tid=2217] Profile activation timeout for RDKB_WIFI_DM_SSID_PROFILE
210527-18:50:33.600755 [mod=T2, lvl=INFO] [tid=7904] Elapsed Time for : RDKB_WIFI_DM_SSID_PROFILE = 1.599477471 (Sec.NanoSec)
210527-18:52:04.152068 [mod=T2, lvl=INFO] [tid=2224] RDKB_WIFI_DM_SSID_PROFILE is found
210527-18:52:04.152158 [mod=T2, lvl=INFO] [tid=2224] Profile RDKB_WIFI_DM_SSID_PROFILE with hash1 hash already exist
root@RaspberryPi-Gateway:/nvram/.t2reportprofiles#
root@RaspberryPi-Gateway:/nvram/.t2reportprofiles#
```

Limitations

The above screenshots and test logs are generated in dbus mode because rbus is not supported in rpi.

Also, webconfig support is not available in RPI . So T2 related testing with webconfig are not validated yet.

References

<https://github.com/rdkcentral/xconfserver/blob/main/README.md>

<https://wiki.rdkcentral.com/display/RDK/Xconf+Server++User+guide+for+configuration+and+feature+validation>

[RDKB Telemetry](#)