

RDKB EthAgent Component in RPI - User Manual - 2019 M7

- [Build procedure to generate R-Pi image with EthAgent component](#)
- [Flashing the image](#)
 - [Command to flash the image](#)
- [Test Setup Block Diagram](#)
- [Test Procedure](#)

Build procedure to generate R-Pi image with EthAgent component

The build procedures are as follows:

1. `repo init -u https://code.rdkcentral.com/r/manifests -b rdk-next -m rdkb-extsrc.xml`
2. `repo sync -j4 --no-clone-bundle`
3. `source meta-cmf-raspberrypi/setup-environment` (Select option `raspberrypi-rdk-broadband.conf`)
4. `bitbake rdk-generic-broadband-image`

Flashing the image

Command to flash the image

Generated image has to be flashed to an SD card using this command in local PC:

```
$ sudo dd if=<path to ImageName.rpi-sdimg> of=<path to SD card space> bs=4M
```

Ex:


```
$ sudo dd if=rdk-generic-broadband-image-raspberrypi-rdk-broadband.rpi-sdimg of=/dev/sdb bs=4M
```

The SD card is inserted to the Raspberry Pi board and booted to check for containers created.

The Raspberry Pi board is connected to the PC via a USB to serial converter and the logs can be checked in console or can be connected via HDMI cable to a TV and logs will be shown in the terminal

Test Setup Block Diagram


Test Setup Block Diagram for Eth Agent



Test Procedure

Step1: Open the Web UI on any of the Wireless/Wired Client PC using Gateway IP Address(10 series)

Output:



Step2: Login to Web UI either through Remote Management (erouter0 IP Address:8080) or through connected wired / wireless clients (Gateway IP Address) and go to "Connected Device" page

Output:

Connected Devices - Devices - XFINITY - Mozilla Firefox

192.168.2.68:8080/connected_devices_computers.php

Hi admin • [Logout](#) • [Change Password](#)

0% Internet Wi-Fi MoCA Low Security

Connected Devices > Devices

View information about devices currently connected to your network, as well as connection history. [more](#)

Prefer Private Connection ☒

Online Devices

Host Name	DHCP/Reserved IP	RSSI Level	Connection		
CHTSPC2021	DHCP	NA	Ethernet	EDIT	X
MIMAX2-AmritaBanik	DHCP	-67 dBm	Wi-Fi 2.4G	EDIT	X
amrita-ThinkCentre-M72e	DHCP	NA	Ethernet	EDIT	X
devvm3	DHCP	NA	Ethernet	EDIT	X
Redmi3S-Redmi	DHCP	-45 dBm	Wi-Fi 2.4G	EDIT	X

[ADD DEVICE WITH RESERVED IP](#)

Offline Devices

Host Name	DHCP/Reserved IP	Connection
-----------	------------------	------------

[ADD WI-FI PROTECTED SETUP \(WPS\) CLIENT](#)

Xfinity.com • customerCentral • User Guide

Step3: Verify the functionality for "Prefer Private Connection"

Output:

Connected Devices - Devices - XFINITY - Mozilla Firefox

192.168.2.68:8080/connected_devices_computers.php

Hi admin • [Logout](#) • [Change Password](#)

0% Internet Wi-Fi MoCA Low Security

Connected Devices > Devices

View information about devices currently connected to your network, as well as connection history. [more](#)

Prefer Private Connection ☒

Online Devices

Host Name	DHCP/Reserved IP	RSSI Level	Connection		
CHTSPC2021	DHCP	NA	Ethernet	EDIT	X
MIMAX2-AmritaBanik	DHCP	-49 dBm	Wi-Fi 2.4G	EDIT	X
amrita-ThinkCentre-M72e	DHCP	NA	Ethernet	EDIT	X
devvm3	DHCP	NA	Ethernet	EDIT	X
Redmi3S-Redmi	DHCP	-46 dBm	Wi-Fi 2.4G	EDIT	X

[ADD DEVICE WITH RESERVED IP](#)

Offline Devices

Host Name	DHCP/Reserved IP	Connection
-----------	------------------	------------

[ADD WI-FI PROTECTED SETUP \(WPS\) CLIENT](#)

Xfinity.com • customerCentral • User Guide

Step4: Verify that Online Devices section is showing data related to presently connected wired/wireless client

Output:

Connected Devices - Devices - XFINITY - Mozilla Firefox

192.168.2.68:8080/connected_devices_computers.php

Hi admin • [Logout](#) • [Change Password](#)

0% Internet Wi-Fi MoCA Low Security

Connected Devices > Devices

View information about devices currently connected to your network, as well as connection history. [more](#)

Prefer Private Connection ☐

Online Devices

Host Name	DHCP/Reserved IP	RSSI Level	Connection		
amrita-ThinkCentre-M72e	DHCP	NA	Ethernet	EDIT	X
CHTSPC2021	DHCP	NA	Ethernet	EDIT	X
MIMAX2-AmritaBanik	DHCP	-52 dBm	Wi-Fi 2.4G	EDIT	X
CHTSPC2113	DHCP	NA	Ethernet	EDIT	X
CHTSPC2077	DHCP	NA	Ethernet	EDIT	X

[ADD DEVICE WITH RESERVED IP](#)

Offline Devices


Host Name	DHCP/Reserved IP	Connection
-----------	------------------	------------

[ADD WI-FI PROTECTED SETUP \(WPS\) CLIENT](#)

Xfinity.com • customerCentral • User Guide

Step5: Verify that Offline Device section is showing data related to offline(previously connected) wired/wireless client

Output:



Step6: Execute the dmcli command **dmcli eRT getv Device.Hosts.** to view the values on the various fields related to connected wired/wireless clients

Output:

Tested with 5 clients:

```
root@RaspberryPi-Gateway:~# dmcli eRT getv Device.Hosts.
CR component name is: eRT.com.cisco.sptvg.ccsp.CR
subsystem_prefix eRT.
getv from/to component(eRT.com.cisco.sptvg.ccsp.lmlite): Device.Hosts.
Execution succeed.
Parameter 1 name: Device.Hosts.X_CISCO_COM_ConnectedDeviceNumber
type: uint, value: 1
Parameter 2 name: Device.Hosts.X_CISCO_COM_ConnectedWiFiNumber
type: uint, value: 0
Parameter 3 name: Device.Hosts.X_RDKCENTRAL-COM_HostVersionId
type: uint, value: 5
Parameter 4 name: Device.Hosts.X_RDKCENTRAL-COM_HostCountPeriod
type: uint, value: 60
Parameter 5 name: Device.Hosts.X_RDKCENTRAL-COM_LMHost_Sync
type: uint, value: 0
Parameter 6 name: Device.Hosts.X_RDKCENTRAL-COM_LMHost_Sync_From_MoCA
type: string, value:
Parameter 7 name: Device.Hosts.X_RDKCENTRAL-COM_LMHost_Sync_From_WiFi
type: string, value:
Parameter 8 name: Device.Hosts.X_RDKCENTRAL-COM_EthHost_Sync
type: string, value:
Parameter 9 name: Device.Hosts.HostNumberOfEntries
type: uint, value: 5
Parameter 10 name: Device.Hosts.Host.1.Alias
type: string, value:
Parameter 11 name: Device.Hosts.Host.1.PhysAddress
type: string, value: d4:3d:7e:60:08:4d
```

Parameter 12 name: Device.Hosts.Host.1.IPAddress
type: string, value: 10.0.0.206

Parameter 13 name: Device.Hosts.Host.1.DHCPClient
type: string, value: Device.DHCPv4.Server.Pool.1.Client.4

Parameter 14 name: Device.Hosts.Host.1.AssociatedDevice
type: string, value:

Parameter 15 name: Device.Hosts.Host.1.Layer1Interface
type: string, value: Ethernet

Parameter 16 name: Device.Hosts.Host.1.Layer3Interface
type: string, value: Device.IP.Interface.3

Parameter 17 name: Device.Hosts.Host.1.HostName
type: string, value: amrita-ThinkCentre-M72e

Parameter 18 name: Device.Hosts.Host.1.Active
type: bool, value: false

Parameter 19 name: Device.Hosts.Host.1.LeaseTimeRemaining
type: int, value: 601223

Parameter 20 name: Device.Hosts.Host.1.X_CISCO_COM_ActiveTime
type: int, value: -2085978090

Parameter 21 name: Device.Hosts.Host.1.X_CISCO_COM_InactiveTime
type: int, value: -2085978389

Parameter 22 name: Device.Hosts.Host.1.X_COMCAST-COM_LastChange
type: uint, value: 107

Parameter 23 name: Device.Hosts.Host.1.AddressSource
type: string, value: DHCP

Parameter 24 name: Device.Hosts.Host.1.Comments
type: string, value:

Parameter 25 name: Device.Hosts.Host.1.X_CISCO_COM_RSSI
type: int, value: -200

Parameter 26 name: Device.Hosts.Host.1.X_RDKCENTRAL-COM_Parent
type: string, value:

Parameter 27 name: Device.Hosts.Host.1.X_RDKCENTRAL-COM_DeviceType
type: string, value: empty

Parameter 28 name: Device.Hosts.Host.1.X_RDKCENTRAL-COM_Layer1Interface
type: string, value:

Parameter 29 name: Device.Hosts.Host.1.IPv4AddressNumberOfEntries
type: uint, value: 1

Parameter 30 name: Device.Hosts.Host.1.IPv6AddressNumberOfEntries
type: uint, value: 0

Parameter 31 name: Device.Hosts.Host.1.IPv4Address.1.IPAddress
type: string, value: 10.0.0.206

Parameter 32 name: Device.Hosts.Host.2.Alias
type: string, value:

Parameter 33 name: Device.Hosts.Host.2.PhysAddress
type: string, value: f0:4d:a2:dc:15:d6

Parameter 34 name: Device.Hosts.Host.2.IPAddress
type: string, value: 10.0.0.46

Parameter 35 name: Device.Hosts.Host.2.DHCPClient
type: string, value: Device.DHCPv4.Server.Pool.1.Client.3

Parameter 36 name: Device.Hosts.Host.2.AssociatedDevice
type: string, value:

Parameter 37 name: Device.Hosts.Host.2.Layer1Interface
type: string, value: Ethernet

Parameter 38 name: Device.Hosts.Host.2.Layer3Interface
type: string, value: Device.IP.Interface.3

Parameter 39 name: Device.Hosts.Host.2.HostName
type: string, value: CHTSPC2021

Parameter 40 name: Device.Hosts.Host.2.Active
type: bool, value: false

Parameter 41 name: Device.Hosts.Host.2.LeaseTimeRemaining
type: int, value: 601273

Parameter 42 name: Device.Hosts.Host.2.X_CISCO_COM_ActiveTime
type: int, value: -2085978270

Parameter 43 name: Device.Hosts.Host.2.X_CISCO_COM_InactiveTime
type: int, value: -2085978389

Parameter 44 name: Device.Hosts.Host.2.X_COMCAST-COM_LastChange
type: uint, value: 107

Parameter 45 name: Device.Hosts.Host.2.AddressSource
type: string, value: DHCP

Parameter 46 name: Device.Hosts.Host.2.Comments
type: string, value:

Parameter 47 name: Device.Hosts.Host.2.X_CISCO_COM_RSSI
type: int, value: -200

Parameter 48 name: Device.Hosts.Host.2.X_RDKCENTRAL-COM_Parent
type: string, value:

Parameter 49 name: Device.Hosts.Host.2.X_RDKCENTRAL-COM_DeviceType
type: string, value: empty

Parameter 50 name: Device.Hosts.Host.2.X_RDKCENTRAL-COM_Layer1Interface
type: string, value:

Parameter 51 name: Device.Hosts.Host.2.IPv4AddressNumberOfEntries

type: uint, value: 1
Parameter 52 name: Device.Hosts.Host.2.IPv6AddressNumberOfEntries
type: uint, value: 0
Parameter 53 name: Device.Hosts.Host.2.IPv4Address.1.IPAddress
type: string, value: 10.0.0.46
Parameter 54 name: Device.Hosts.Host.3.Alias
type: string, value:
Parameter 55 name: Device.Hosts.Host.3.PhysAddress
type: string, value: EC:D0:9F:59:EF:BF
Parameter 56 name: Device.Hosts.Host.3.IPAddress
type: string, value: 10.0.0.72
Parameter 57 name: Device.Hosts.Host.3.DHCPClient
type: string, value: Device.DHCPv4.Server.Pool.1.Client.5
Parameter 58 name: Device.Hosts.Host.3.AssociatedDevice
type: string, value: Device.WiFi.AccessPoint.1.AssociatedDevice.1
Parameter 59 name: Device.Hosts.Host.3.Layer1Interface
type: string, value: Device.WiFi.SSID.1
Parameter 60 name: Device.Hosts.Host.3.Layer3Interface
type: string, value: Device.IP.Interface.3
Parameter 61 name: Device.Hosts.Host.3.HostName
type: string, value: MIMAX2-AmritaBanik
Parameter 62 name: Device.Hosts.Host.3.Active
type: bool, value: true
Parameter 63 name: Device.Hosts.Host.3.LeaseTimeRemaining
type: int, value: 601813
Parameter 64 name: Device.Hosts.Host.3.X_CISCO_COM_ActiveTime
type: int, value: -2085975121
Parameter 65 name: Device.Hosts.Host.3.X_CISCO_COM_InactiveTime
type: int, value: 0
Parameter 66 name: Device.Hosts.Host.3.X_COMCAST-COM_LastChange
type: uint, value: 3375
Parameter 67 name: Device.Hosts.Host.3.AddressSource
type: string, value: DHCP
Parameter 68 name: Device.Hosts.Host.3.Comments
type: string, value:
Parameter 69 name: Device.Hosts.Host.3.X_CISCO_COM_RSSI
type: int, value: -46
Parameter 70 name: Device.Hosts.Host.3.X_RDKCENTRAL-COM_Parent
type: string, value:
Parameter 71 name: Device.Hosts.Host.3.X_RDKCENTRAL-COM_DeviceType
type: string, value: empty
Parameter 72 name: Device.Hosts.Host.3.X_RDKCENTRAL-COM_Layer1Interface
type: string, value: Device.WiFi.Radio.1
Parameter 73 name: Device.Hosts.Host.3.IPv4AddressNumberOfEntries
type: uint, value: 1
Parameter 74 name: Device.Hosts.Host.3.IPv6AddressNumberOfEntries
type: uint, value: 0
Parameter 75 name: Device.Hosts.Host.3.IPv4Address.1.IPAddress
type: string, value: 10.0.0.72
Parameter 76 name: Device.Hosts.Host.4.Alias
type: string, value:
Parameter 77 name: Device.Hosts.Host.4.PhysAddress
type: string, value: f8:b1:56:db:7d:0e
Parameter 78 name: Device.Hosts.Host.4.IPAddress
type: string, value: 10.0.0.149
Parameter 79 name: Device.Hosts.Host.4.DHCPClient
type: string, value: Device.DHCPv4.Server.Pool.1.Client.2
Parameter 80 name: Device.Hosts.Host.4.AssociatedDevice
type: string, value:
Parameter 81 name: Device.Hosts.Host.4.Layer1Interface
type: string, value: Ethernet
Parameter 82 name: Device.Hosts.Host.4.Layer3Interface
type: string, value: Device.IP.Interface.3
Parameter 83 name: Device.Hosts.Host.4.HostName
type: string, value: CHTSPC2113
Parameter 84 name: Device.Hosts.Host.4.Active
type: bool, value: false
Parameter 85 name: Device.Hosts.Host.4.LeaseTimeRemaining
type: int, value: 602157
Parameter 86 name: Device.Hosts.Host.4.X_CISCO_COM_ActiveTime
type: int, value: -2085978450
Parameter 87 name: Device.Hosts.Host.4.X_CISCO_COM_InactiveTime
type: int, value: -2085978389
Parameter 88 name: Device.Hosts.Host.4.X_COMCAST-COM_LastChange
type: uint, value: 107
Parameter 89 name: Device.Hosts.Host.4.AddressSource
type: string, value: DHCP
Parameter 90 name: Device.Hosts.Host.4.Comments
type: string, value:

Parameter 91 name: Device.Hosts.Host.4.X_CISCO_COM_RSSI
type: int, value: -200

Parameter 92 name: Device.Hosts.Host.4.X_RDKCENTRAL-COM_Parent
type: string, value:

Parameter 93 name: Device.Hosts.Host.4.X_RDKCENTRAL-COM_DeviceType
type: string, value: empty

Parameter 94 name: Device.Hosts.Host.4.X_RDKCENTRAL-COM_Layer1Interface
type: string, value:

Parameter 95 name: Device.Hosts.Host.4.Ipv4AddressNumberOfEntries
type: uint, value: 1

Parameter 96 name: Device.Hosts.Host.4.Ipv6AddressNumberOfEntries
type: uint, value: 0

Parameter 97 name: Device.Hosts.Host.4.Ipv4Address.1.IPAddress
type: string, value: 10.0.0.149

Parameter 98 name: Device.Hosts.Host.5.Alias
type: string, value:

Parameter 99 name: Device.Hosts.Host.5.PhysAddress
type: string, value: 64:00:6a:50:b2:9a

Parameter 100 name: Device.Hosts.Host.5.IPAddress
type: string, value: 10.0.0.136

Parameter 101 name: Device.Hosts.Host.5.DHCPClient
type: string, value: Device.DHCPv4.Server.Pool.1.Client.1

Parameter 102 name: Device.Hosts.Host.5.AssociatedDevice
type: string, value:

Parameter 103 name: Device.Hosts.Host.5.Layer1Interface
type: string, value: Ethernet

Parameter 104 name: Device.Hosts.Host.5.Layer3Interface
type: string, value: Device.IP.Interface.3

Parameter 105 name: Device.Hosts.Host.5.HostName
type: string, value: CHTSPC2077

Parameter 106 name: Device.Hosts.Host.5.Active
type: bool, value: false

Parameter 107 name: Device.Hosts.Host.5.LeaseTimeRemaining
type: int, value: 602896

Parameter 108 name: Device.Hosts.Host.5.X_CISCO_COM_ActiveTime
type: int, value: -2085977548

Parameter 109 name: Device.Hosts.Host.5.X_CISCO_COM_InactiveTime
type: int, value: -2085978389

Parameter 110 name: Device.Hosts.Host.5.X_COMCAST-COM_LastChange
type: uint, value: 107

Parameter 111 name: Device.Hosts.Host.5.AddressSource
type: string, value: DHCP

Parameter 112 name: Device.Hosts.Host.5.Comments
type: string, value:

Parameter 113 name: Device.Hosts.Host.5.X_CISCO_COM_RSSI
type: int, value: -200

Parameter 114 name: Device.Hosts.Host.5.X_RDKCENTRAL-COM_Parent
type: string, value:

Parameter 115 name: Device.Hosts.Host.5.X_RDKCENTRAL-COM_DeviceType
type: string, value: empty

Parameter 116 name: Device.Hosts.Host.5.X_RDKCENTRAL-COM_Layer1Interface
type: string, value:


Parameter 117 name: Device.Hosts.Host.5.Ipv4AddressNumberOfEntries
type: uint, value: 1

Parameter 118 name: Device.Hosts.Host.5.Ipv6AddressNumberOfEntries
type: uint, value: 0

Parameter 119 name: Device.Hosts.Host.5.Ipv4Address.1.IPAddress
type: string, value: 10.0.0.136


Step7: Verify the WAN Network page where Ethernet button is enabled by default

Output:



Step8: Clicking on Docsis button will display the message "DOCSIS Support is not available in RPI Boards" pop up window. Click on OK button on that.

Output:



Step 9: Disabling the Ethernet button using dmcli - "dmcli eRT setv Device.Ethernet.X_RDKCENRAL-COM_WAN.Enabled bool false" will display error message: "Execution fail(error code:CCSP_ERR_INVALID_PARAMETER_VALUE(9007))"

Output:

```
root@RaspberryPi-Gateway:~# dmcli eRT setv Device.Ethernet.X_RDKCENRAL-COM_WAN.Enabled bool false
CR component name is: eRT.com.cisco.spvtg.ccsp.CR
subsystem_prefix eRT.
setv from/to component(eRT.com.cisco.spvtg.ccsp.ethagent): Device.Ethernet.X_RDKCENRAL-COM_WAN.Enabled
Execution fail(error code:CCSP_ERR_INVALID_PARAMETER_VALUE(9007)).
```

Step10: Verify the no. of connected devices displayed while hovering the mouse on the "Internet" tab displayed on the top right of "at-a-glance" page in Web UI

Output:

Connected Devices - Devices - XFINITY - Mozilla Firefox

Connected Devices - Devices X Mail - Amrita.Banik@Ltt X RDKB EthAgent Compon X +

192.168.2.68:8080/connected_devices_computers.php

Most Visited Getting Started Python

xfinity

Hi admin • Logout • Change Password

0% Internet Wi-Fi MoCA Low Security

Connected Devices > Status: Connected 2 devices connected

View information about devices currently connected to your network, as well as connection history. [more](#)

Prefer Private Connection ☒

Online Devices

Host Name	DHCP/Reserved IP	RSSI Level	Connection		
amrita-ThinkCentre-M72e	DHCP	NA	Ethernet	EDIT	X
MIMAX2-AmritaBanik	DHCP	-37 dBm	Wi-Fi 2.4G	EDIT	X

ADD DEVICE WITH RESERVED IP

Offline Devices

Host Name	DHCP/Reserved IP	Connection
-----------	------------------	------------

ADD WI-FI PROTECTED SETUP (WPS) CLIENT

Xfinity.com • customerCentral • User Guide

javascript: void(0);

Step 11: Disconnect any device and verify the count changes on displayed message while hovering mouse on "Internet" tab

Output:

Connected Devices - Devices - XFINITY - Mozilla Firefox

Connected Devices - Devices X

Mail - Amrita.Banik@Ltt X

RDKB EthAgent Compon X

+

192.168.2.68:8080/connected_devices_computers.php

Most Visited

Getting Started

Python

0%

Internet

Wi-Fi

MoCA

Low Security

Hi admin

Logout

Change Password

Gateway

Connected Devices

Parental Control

Advanced

Troubleshooting

Connected Devices >

Status: Connected
1 devices connected

View information about devices currently connected to your network, as well as connection history.

more

Prefer Private Connection ☒

Online Devices

Host Name	DHCP/Reserved IP	RSSI Level	Connection
amrita-ThinkCentre-M72e	DHCP	NA	Ethernet

ADD DEVICE WITH RESERVED IP

Offline Devices

Host Name	DHCP/Reserved IP	Connection
MIMAX2-AmritaBanik	DHCP	Unknown

ADD WI-FI PROTECTED SETUP (WPS) CLIENT

Xfinity.com • customerCentral • User Guide

Step 12: The above steps will work for wireless client also, the snapshot mentioned under each step shows the wireless client data (MIMAX2) as well.