### Tata Elxsi Accelerator UI Customization

- Introduction
- Overview
- Login
  - Steps to Login
- Client setup
  - Box Configuration
- Customize the Application
  - o 1. Home
    - 3. Steps to Disable a Premium App for a customer
    - 4. Steps to update an entry in table
    - 5. Steps to enable a customer to access Metro App content
       6. Steps to Disable a Metro App for a customer

    - 7. Steps to add a Recommended for you content for a customer
    - 8. Steps to Remove a Recommended for you content for a customer
    - 9. Steps to add an icon in InfoBar for a customer
    - 10. Steps to delete an icon from the Infobar for a customer
    - 11. Steps to customize home screen background image/color, font face and font color for a customer
    - 12. Steps to customize settings screen background image/color, font face and font color for a customer
- TroubleShooting

### Introduction

Tata Elxsi Accelerator UI Application can be customized based on the operator requirement using our CustomUI application (Customer Login Page ) . Only the applications and contents configured against a particular operator id will be available to that operator.

### Overview

This document provides the following details:

- Login to CustomUI Application
- Customize the application
- Box configuration

## Login

The steps to login as a new operator to the CustomUI Application is listed here:

#### Steps to Login

Follow the steps listed here to login as an existing Operator

- 1. Click on Customer Login Page or Enter the URL (http://121.244.192.84:9999/CustomUI) in the address bar of browser (Chrome), and press Enter.
- 2. Below login page will be loaded.

## **Admin Login**

UserName:		
Password:		
	Login	

New Operator? sign up

4. Click on Login.

#### Follow the steps below to login as a new operator

- 1. Click on the sign-up link to create a new operator.
- 2. Once clicked below page will be loaded.

# **Operator SignUp Form**

Operator Name	
UserName	
Password	
OEM	realtek 🕶
	Submit

- 3. Enter the operator name, Username, Password and select the OEM.
- 4. Note down the Username since the same value should be given in the OPERATOR\_ID in box configuration discussed later.
- 5. Once all values are entered click on the submit button.
- 6. Dashboard screen will be displayed on successful login.



## Client setup

The steps to connect to the server is given below:

### **Box Configuration**

- 1. Open /opt/www/build/static/server/Serverconfig.json in box.
- 2. Serverconfig.json contains 3 fields:

"SERVER\_URL ": URL of the CustomUI ( http://121.244.192.84:9999/CustomUI/)

"OPERATOR\_ID ": Username given while creating a new operator (for default user : operator\_id : teuser)

"ASSET\_URL": URL of the server from which assets are to be loaded (http://121.224.192.84:9999/)

3. Save and reboot the box.


## **Customize the Application**

**Note:** The configuration is to be done against each operator and each operator is identified by a unique operator\_id. This operator\_id should be same as o perator\_id in /opt/www/build/static/server/Serverconfig.json in box.


#### 1. Home

- The order of the sections in the home screen can be customized by the operator.
- Click the **Home** button on the top bar of dashboard, below page will be displayed
- 1. Click on the customer\_menu\_app\_list table through phpMyAdmin page.

2.



- 3. Click on the Insert button to add Customer data.
- 4. Premium apps feature in main menu of Accelerator UI app can be enabled by setting 6 in the **menu\_id** field. [6 here refers to the Premium app content against that customer id]
- Individual Premium apps in the Accelerator UI app can be enabled by setting the app\_id field.
   [values for app\_id can be referred from app\_list table, see picture below with YouTube is 1, Netflix is 2 etc]



e.g. For enabling YouTube in first position
click on customer\_menu\_app\_list -> click on insert
->Add menu\_id:6
app\_id:1
app\_position:1
customer\_id:boxid (serial\_number)

#### 3. Steps to Disable a Premium App for a customer

- 1. Click on the **customer\_menu\_app\_list** table.
- 2. Delete the entry with app\_id of the app to be disabled corresponding to the required customer\_id.
  - e.g. To delete Netflix premium app for a customer with customer\_id: OEABAgME9i. click on customer\_menu\_app\_list.


    Delete the entry corresponding to customer\_id -> OEABAgME9i with app\_id is 2.

#### 4. Steps to update an entry in table

- 1. Click on the Edit button from the respective rows that is to be updated.
- 2. Make the required update and click on Go button.

#### 5. Steps to enable a customer to access Metro App content

1. Click on the customer\_menu\_app\_list table.




- 2. Click on the Insert button to add Customer data .
- Metro apps feature can be enabled by setting 7 in the menu\_id field. [7 here refers to the Metro app content in menu\_list table]
- Individual Metro apps can be enabled by setting the value in app\_id field. [values for app\_id can be referred from app\_list table]
  - e.g. For enabling CNN in first position.
    click on customer\_menu\_app\_list click on insert
    Add menu\_id: 7
    app\_id: 4
    app\_position:1
    customer\_id: boxid(serial\_number)

#### 6. Steps to Disable a Metro App for a customer

- 1. Click on the customer\_menu\_app\_list table
- 2. Delete the entry with app\_id of the app to be disabled corresponding to the required customer\_id.
  - e.g. To delete Radio line app for a customer with customer\_id: OEABAgME9i. click on **customer\_menu\_app\_list table**. Delete the entry corresponding to customer\_id -> OEABAgME9i with app\_id ->12.

#### 7. Steps to add a Recommended for you content for a customer


1. Click on the customer\_recommended\_list table through phpMyAdmin page.



2. Click on the **Insert** button to add Customer data.

3. Recommended For You content in main menu of demo app can be added for a particular customer by setting the required **recommended\_conte nt\_id** against that **customer\_id**.

[values of recommended\_content\_id can be referred from recommended\_list table, see the picture below]



eg. For enabling Tears of steel.

click on customer\_recommended\_list click on insert

Add recommended\_content\_id: 1

customer\_id : boxid (serial\_number)

Note: To add a new content to recommended\_list table


- i. Add a new recommended\_content\_id for the new content.
- ii. Add the corresponding poster url in "url" field and video content url to "videourl" field.
- iii. Add the corresponding category if it needs to displayed on the poster.

#### 8. Steps to Remove a Recommended for you content for a customer

- 1. Click on the customer\_recommended\_list table.
- 2. Delete the entry with recommended\_content\_id of the content to be removed corresponding to the required customer\_id.

#### 9. Steps to add an icon in InfoBar for a customer

- 1. Click on the info\_settings\_content table through phpMyAdmin page .
- 2. Click on Insert button to add Infobar icon path.
- 3. Infobar icon path can be added to the column of image in the table against corresponding menu name (i.e. icon name). [menu\_id can be referred from menu\_list table]



e.g. For adding bluetooth icon to the infobar.

click on info\_settings\_content table-> click on insert

Add menu\_id: 32 (corresponding to Bluetooth InfoBar icon from menu\_list table)
Image: 'images/info/bluetooth.png' (Add the local path of the icon in static folder)

#### 10. Steps to delete an icon from the Infobar for a customer


- 1. Click on the info\_settings\_content table.
- 2. Delete the entry with path to the corresponding info bar icon to be removed.

e.g. For Deleting Wi-Fi icon from the InfoBar. Click on the **info\_settings\_content** table Delete the entry with path to the Wi-Fi icon

#### 11. Steps to customize home screen background image/color, font face and font color for a customer

- 1. Click on the customer\_theme\_design table .
- 2. Click on the Insert button to add Customer data.
- 3. Background image/ Background color, font face and font color for the Home Screen can be customized by setting 1 in the menu\_id field.
- 4. Value for each field can be added in the appropriate column of the table based on the customization requirements.

Note: If both bg\_image and bg\_color are configured in the table , preference is given to bg\_image.



e.g. For Adding bg\_color/bg\_image, font face and font color for home screen.

click on customer\_theme\_design click on insert

->Add menu\_id:1

bg\_image: images/settings/settings-bg.png

bg\_color : 0xff211d30
FontFace : bold

text\_fontColor: 0xff211d30 customer\_id: boxid(serial\_number)

# 12. Steps to customize settings screen background image/color, font face and font color for a customer

- 1. Click on the **customer\_theme\_design** table.
- 2. Click on the **Insert** button to add Customer data.
- 3. Background image/ Background color, font face and font color for the Home Screen can be customized by setting 4 in the menu\_id field.
- 4. Value for each field can be added in the appropriate column of the table based on the customization requirements .

**Note:** If both bg\_image and bg\_color are configured in the table, preference is given to bg\_image.

e.g. For Adding bg\_color/bg\_image , font face and font color for home screen click on customer\_theme\_design -> click on insert -> Add menu\_id: 1
bg\_image : images/settings/settings-bg.png
bg\_color : 0xff211d30
FontFace : bold
text\_fontColor : 0xff211d30
customer\_id : boxid(serial\_number)

## **TroubleShooting**

#### To confirm the client-server setup is working as expected:

- 1. Ensure firewall is disabled
- 2. Try the following URL in the browser first and then try the same using curl command in the box.

#### Browser

http://localhost:8080/CustomUI/getThemeConfig?customer\_id=OEABAgME9i

#### **Box**

curl http://<Server\_ip>:<Server\_port>/CustomUI/getThemeConfig?customer\_id=OEABAgME9i

If you are not getting data in the box try: ping <Server\_ip>

eg: root@mediabox:~#ping 192.168.18.3

PING 192.168.18.3 (192.168.18.3): 56 data bytes

64 bytes from 192.168.18.3: seq=0 ttl=128 time=35.467 ms

64 bytes from 192.168.18.3: seq=1 ttl=128 time=2.238 ms

64 bytes from 192.168.18.3: seg=2 ttl=128 time=2.214 ms

If Ping is success, try http://192.168.18.3:8080/CustomUl/getPosition?customer\_id=O in the browser to get the corresopnding data.

["premium Apps","Recommended for you","metro Apps"]

Then try the curl for the same in the box:

~# curl http://192.168.18.3:8080/CustomUl/getPosition?customer\_id=OEABAgME9i

response: ["premium Apps", "Recommended for you", "metro Apps"]

If you are getting the appropriate response for the curl, Then the client server connection is successful.

#### To get the corresponding customization changes in UI:

- Add the following in /opt/www/build/static/server/Serverconfig.json
   "Server\_ip": ip address of the server machine in which the xampp server is setup
   Note: Ping to this ip should be successful as we tried in the previous step
   "Server\_port": port of Tomcat server
- 2. Add the following boxid in /opt/www/build/static/server/Serverconfig.json "serial\_number": OEABAgME9i
- 3. Reboot

The corresponding changes will be reflected in the Accelerator UI.